

Boards and Components -Test and Measurement Equipment → Software +

Blog Forum

Projects


Internal Tools •

FREE US shipping on orders \$35+

You are here:: Digilent Reference / Programmable Logic / Eclypse Z7 / Eclypse Z7 Low Level Zmod ADC DAC Demo

Eclypse Z7 Low Level Zmod ADC DAC Demo

Table of Contents •




Overview

The project demonstrates the implementation of a basic signal processing application on the Eclypse platform (Eclypse Z7 + Zmod ADC + Zmod DAC).

Description

The simplified block diagram of the system implemented for this demo is shown below:



format and passed on to the input of a digital low pass filter. The filter's output is converted back to an analog format by the Zmod DAC 1411 and can be measured/visualized on the converter channel 1. The input signal, after the analog to digital conversion, is also looped back to the Zmod DAC 1411 and connected to CH2

output. The Analog Discovery 2's Network Analyzer instrument is then used to plot the frequency characteristic using the CH2 of the Zmod DAC 1411 as reference. The purpose of the digital loopback is to correct the phase errors introduced by the ADC and Zmod ADC 1410 Low Level

Controller latency and the gain errors caused by the mismatch between the ADC and the DAC full scale voltages.

With this setup the frequency response of the filter can be correctly measured regardless of the gain setting of the Zmod

DAC 1411. Only the Zynq's Programmable Logic (PL) is used for this project.

The IPs instantiated in the design and their functionality are described below:

- The Zmod ADC 1410 Low Level Controller initializes the Zmod ADC 1410 hardware and synchronizes the incoming data in the user clock domain, A digital low pass filter – implemented using Xilinx FIR compiler 7.2 IP Core with the coefficients specified in Table 1,
- below. • The Zmod DAC 1411 Low Level Controller - initializes the Zmod DAC 1411 hardware and formats the output data
- according to the AD9717 DAC requirements.
- Table 1. FIR Filter Coefficients

Inventory

Hardware

- George Eclypse Z7
- Including a Micro-USB cable and 12V Power Supply
- Zmod Scope 1410
- Zmod AWG 1411 Analog Discovery 2 (AD2)
- Q Discovery BNC Adapter
- Software

Vivado Design Suite 2019.1 with Digilent Board Support Files installed

- o Follow the Installing Vivado, Xilinx SDK, and Digilent Board Files guide on how to install Vivado and Digilent
 - **Board Support Files.**

Skills

- Waveforms Software
- · Basic familiarity with Vivado

This experience can be found by walking through our "Getting Started with Vivado" guide

Downloads

Viva	do Project Repository	GIT Repo
Wave	eforms workspace and Vivado project generated bit file	ZIP Archive

Demo Setup

Hardware Setup

- Connect the Analog Discovery 2 board to the host computer using a MicroUSB cable. 2. Connect the Eclypse Z7 board to the host computer using a MicroUSB cable through PROG MicroUSB port and power the
- board using the 12V Power Supply. Flip its power switch to turn it on. 3. Connect the two Zmods ADC and DAC to the Zmod connectors of the Eclypse Z7 board as follows:
- Zmod <u>ADC</u> 1410 to ZMOD A connector of the board Zmod DAC 1411 to ZMOD B connector of the board
- 4. Connect the BNC adapter board to the Analog Discovery 2 board 5. Make the following physical connections:
 - Analog Discovery 2 AWG1 to Zmod ADC 1410 CH1 Zmod ADC1410 to Eclypse Z7 SYZYGY ZMOD A
 - Zmod DAC1411 to Eclypse Z7 SYZYGY ZMOD B
 - Zmod DAC1411 CH1 to Analog Discovery 2 SCOPE C2 Zmod DAC1411 CH2 to Analog Discovery 2 SCOPE C1

is recommended for the Zmod to BNC Adapter physical connections.

Software Setup

Note: Since the Zmods use SMA connectors, use of BNC-to-SMA cables (or BNC-to-SMA adapters with BNC or SMA cables)

1. Follow the instructions provided in the README file from ② Digilent Vivado Scripts repository, to recreate the project:

 Using @ git, clone the repository on your host computer: git clone --recursive https://github.com/Digilent/Eclypse-Z7-HW -b low_level_zmod_adc_dac/master

· Open Vivado and use the instructions provided in Workflow 1 (Cloning a Repo that uses this Submodule) of the

- README. Make sure to change directory into the Eclypse-Z7-HW folder that was just cloned, prior to running the following command (if using the Vivado TCL Console instead of Python): set argv ""; source digilent-vivado-scripts/digilent_vivado_checkout.tcl
- 2. Download and extract the demo files, linked in the Downloads section, above.

5. Open Hardware Manager tool from within Vivado and click Open target, Autoconnect:

- 3. After recreating the project in Vivado, generate the bitstream file. 4. Make sure the boot mode jumper on the Eclypse Z7 is on the JTAG position.
 - Q E O H B M B
- Hit the Run button of the Network Analyzer instrument.

6. Select the .bit file, or make sure it is already selected and is located at the correct path in the dialog, and program the

7. Open WaveForms, then open the workspace, "EclypseZ7VhdlFilterDemo.dwf3work", included in the folder extracted from

Operating the Demo The Network Analyzer will be used to generate a sinusoidal signal (perturbation) on the AWG1 channel. The bode plot (see below) is obtained considering the loopback signal (Zmod DAC 411 CH2) as reference.

board.

the demo archive.

For more information about how to use the other Digilent products featured in this demo, please visit their respective

Final Notes

For more guides and example projects for your Eclypse Z7, please visit its Resource Center.

Analog Discovery 2, Zmod Scope, Zmod AWG, BNC Adapter. For technical support, please visit the ② Digilent Forums.

learn, programmable-logic, project, eclypse-z7

Jobs Legal & Privacy

Shipping & Returns

Company

About Us

FAQs

Resource Centers:

Newsletter Events

News

Blog

Technology Partners

List of Distributors

Affiliations

Digilent uses cookies to ensure you get the best experience on our websites. By using our site you agree to our use of cookies. Learn More

upcoming sales Your email address Submit

Subscribe to our newsletter

Get the latest updates on new products and

1300 NE Henley Ct. Suite 3 Pullman, WA 99163 United States of America

Contact Us

Digilent

Support Channels

Got it!

Feedback