

Contact No. 207

New Adaptor Option

LP01*, YB*, & YB2 Series



AT716



AT717




AT718




AT719

Wired adaptor can be connected to a switch already installed on a panel in a single operation



Adaptor installed on a PC board can be connected to a switch already installed on a panel in a single operation



Align part number marking on switch with NKK marking on adaptor. Push switch until mechanical end of switch is fully inserted into adaptor. This is especially important for products made before April 2013 to prevent backwards installation.

TARGET PRODUCTS AND VARIATIONS



LP01
Bushing Mount



YB Round
Bushing Mount



YB Square
Bushing Mount



YB Rectangular
Bushing Mount



YB2 Round




YB2 Square


NKK

SWITCHES

TYPICAL ADAPTOR DIMENSIONS



TYPICAL SWITCH DIMENSIONS WITH ADAPTOR (Shown with AT716)



- Dimension A: Solder Lug .197" (5.0mm), Straight PC .157" (4.0mm)

PANEL THICKNESS

Model	With Adaptor	Without Adaptor
LP01 Bushing Mount	.079" ~ .256" (2.0mm ~ 6.5mm)	.079" ~ .256" (2.0mm ~ 6.5mm)
YB Bushing Mount	.020" ~ .197" (0.5mm ~ 5.0mm)	.020" ~ .197" (0.5mm ~ 5.0mm)
YB2 Round	.020" ~ .161" (0.5mm ~ 4.1mm)	.020" ~ .197" (0.5mm ~ 5.0mm)
YB2 Square	.020" ~ .126" (0.5mm ~ 3.2mm)	.020" ~ .197" (0.5mm ~ 5.0mm)

- If using switches prior to Contact No. 200, panel thickness is below. Contact NKK for further details.

PANEL THICKNESS WITH CHANGE OF MOUNTING NUT (Contact No. 200)

Model	Maximum Panel Thickness of Switch	After Adaptor Installed	
		Maximum Panel Thickness (before change)	Maximum Panel Thickness (after change)
YB Bushing Mount	.197" (5.0mm)	.075" (1.9mm)	.197" (5.0mm)
YB2 Square	.197" (5.0mm)	n/a	.126" (3.2mm)

Availability September 18, 2012

Corporate Headquarters
Nihon Kaiheiki Ind. Co., Ltd.
 Kawasaki, Japan
 T +81.44.813.8008
 F +81.44.813.8038
<http://www.nikkai.co.jp>

International
Nihon Kaiheiki Ind. Co., Ltd.
<http://www.nikkaiswitches.com>