



Features:

- The tap splice is placed over the existing wire, the additional wire inserted and the block crimped with pliers
- The blade splice is crimped over the wire as above. A 6.3 mm push-on blade can then be inserted into the female blade socket. Suitable for splicing or as a break-in test lead
- Simple to use - apply with pliers
- Excellent electrical connection with out cutting tap or run wires

Preparation

To make a top connection as illustrated

Slip the run wire through the side slot and the top wire through the end of the connector

Make the connection by driving down the U element over the conductors, flush with the top of the connector

Snap over the hinged cover

Specification Table:

Max. Diameter Over Cable Insulation	3.68mm
Dimensions	22mm (Length)
	20mm (Depth)
	13.2mm (Height)
Main and Tap Cable Size	0.8mm ² to 2mm ²
Voltage Rating	0 to 600V
Temperature Rating	105°C

Part Number Table

Description	Wire Size		Part Number
	mm ²	AWG	
TAP Splice, Red, PK25	0.5 to 0.75	22 to 18	DS1
TAP Splice, Blue, PK25	0.75 to 2.5	18 to 14	DS2

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.