


### Silicon Planar Power Zener Diodes

For use in stabilizing and clipping circuits with high power rating. Standard Zener voltage tolerance is ±10%.

#### LL-41(DO-213AB)



Glass case MELF Dimensions in mm

## Absolute Maximum Ratings (T<sub>a</sub> = 25°C)

Parameter	Symbol	Value	Unit
Power Dissipation	P <sub>D</sub>	1 <sup>1)</sup>	W
Operating Junction Temperature	Tj	175	°C
Storage Temperature Range	T <sub>stg</sub>	- 65 to + 175	°C

<sup>1)</sup> Valid provided that electrodes are kept at ambient temperature.

#### **Thermal Characteristics**

Parameter	Symbol	Max.	Unit	
Thermal Resistance Junction to Ambient	$R_{\theta JA}$	170 <sup>1)</sup>	°C/W	
Forward Voltage at I <sub>F</sub> = 200 mA	$V_{F}$	1.2	V	

<sup>1)</sup> Valid provided that electrodes are kept at ambient temperature.

# Characteristics at T<sub>a</sub> = 25°C

Туре	Zener Voltage <sup>3)</sup>			Dynamic Resistance 1)			Reverse Current		Maximum Surge Current <sup>4)</sup>	Maximum Regulator	
	Vz	@Izт ('	V)	at I <sub>ZT</sub>	$Z_{ZT}$ at $I_{ZT}$	Z <sub>ZK</sub>	at I <sub>ZK</sub>	I <sub>R</sub> (μA)	at V <sub>R</sub>	at T <sub>a</sub> = 25℃	Current 2)
	Nom	Min.	Max.	(mA)	Max. (Ω)	Max. (Ω)	(mA)	Max.	(V)	I <sub>ZSM</sub> (mA)	I <sub>ZM</sub> (mA)
ZMY12-GS08	12	10.8	13.2	21	9	700	0.25	5	9.1	380	76

<sup>1)</sup> The dynamic resistance is derived from the 60 Hz AC voltage which results when an AC current having an RMS value equal to 10% of the Zener Current (I<sub>ZT</sub> or I<sub>ZK</sub>) is superimposed on I<sub>ZT</sub> or I<sub>ZK</sub>. Dynamic resistance is measured at two points to insure a sharp knee on the breakdown curve and to eliminate unstable units.

<sup>&</sup>lt;sup>2)</sup> Valid provided that electrodes are kept at ambient temperature.

 $<sup>^{3)}</sup>$  Tested with pulses tp = 20 ms.

<sup>&</sup>lt;sup>4)</sup>The rating listed in the electrical characteristics table is maximum peak, non-repetitive, reverse surge current of 1/2 square wave or equivalent sine wave pulse of 1/120 second duration superimposed on the test current I<sub>ZT</sub>.



#### **Attention**

- Any and all HUA XUAN YANG ELECTRONICS products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your HUA XUAN YANG ELECTRONICS representative nearest you before using any HUA XUAN YANG ELECTRONICS products described or contained herein in such applications.
- HUA XUAN YANG ELECTRONICS assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all HUA XUAN YANG ELECTRONICS products described or contained herein.
- Specifications of any and all HUA XUAN YANG ELECTRONICS products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- HUA XUAN YANG ELECTRONICS CO.,LTD. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all HUA XUAN YANG ELECTRONICS products(including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of HUA XUAN YANG ELECTRONICS CO.,LTD.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production.

  HUA XUAN YANG ELECTRONICS believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the HUA XUAN YANG ELECTRONICS product that you intend to use.