

https://www.phoenixcontact.com/us/products/2910322



Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.

300 mm long Rogowski coil. The measuring coil diameter when installed is 95 mm. The Rogowski coil is used for AC current measurement for busbars and power lines.



## Commercial data

Item number	2910322
Packing unit	1 pc
Minimum order quantity	1 pc
Sales key	C444
Product key	CK4A12
Catalog page	Page 219 (C-5-2019)
GTIN	4055626437583
Weight per piece (including packing)	220.5 g
Weight per piece (excluding packing)	210.5 g
Customs tariff number	90309000
Country of origin	DE

# PACT RCP-D95-5M - Coil

2910322

https://www.phoenixcontact.com/us/products/2910322



## Technical data

### Product properties

Product type	Rogowski coil
Set comprises	2910325 PACT RCP-4000A-1A-D95-5M
Data management status	
Article revision	03
Insulation characteristics	
Pollution degree	2

## **Electrical properties**

#### Measuring coil

Conductor structure signal line	2x 0.22 mm (Signal (tinned))
	1x 0.22 mm (Shielding (tinned))
Insulation	double insulation
Rated insulation voltage	1000 V AC (rms CAT III)
	600 V AC (rms CAT IV)
Test voltage	10.45 kV DC (60 s)
Basic accuracy	<± 0.2 %

#### Contoral

Converter type	Rogowski coil

## Input data

#### Frequency


Designation	Measuring coil
Frequency measuring range	40 Hz 20000 Hz
Position error	<± 0.1 % (typical)
Linearity error	< 0.1 %
Current transformer	
Converter type	Rogowski coil

## Output data

#### Signal

Designation	Measuring coil
Output signal (at 50 Hz)	100 mV (no load, at 1,000 A)
Output voltage (in no-load operation)	$V_{OUT} = M * dI/dt$
Output voltage (sinusoidal, in no-load operation)	100 mV (V <sub>OUT</sub> = 2 * π * M * f * I (M = 0.318 μH; example: At 50 Hz; I = 1,000 A))

#### Dimensions



https://www.phoenixcontact.com/us/products/2910322



Measuring coil	
Length	300 mm
Diameter	8.3 mm ±0.2 mm
Measuring coil when installed	
Diameter	95 mm
Signal line	
Length	5 m
Material specifications	
Housing material	PC
Coil material	Elastollan

## Environmental and real-life conditions

Ambient conditions	
Measuring coil degree of protection	IP54 (not assessed by UL)
Ambient temperature (operation)	-30 °C 80 °C (Measuring coil)
Ambient temperature (storage/transport)	-40 °C 80 °C (Measuring coil)
Altitude	< 2000 m
Permissible humidity (operation)	5 % 95 % (non-condensing)


### Approvals

UKCA	
Certificate	UKCA-compliant
СМІМ	
Certificate	CMIM-compliant
UL, USA/Canada	
Identification	UL 61010 Recognized
Note	Measuring coil
Standards and regulations	

IEC 61010-2-030	Standards/regulations	IEC 61010-1
		IEC 61010-2-030
IEC 61869-10		IEC 61869-10

## Mounting

Thread type ()
----------------




https://www.phoenixcontact.com/us/products/2910322



## Approvals


97

🌣 To download certificates, visit the product detail page: https://www.phoenixcontact.com/us/products/2910322



UL Recognized Approval ID: FILE E 357804

cULus Recognized



https://www.phoenixcontact.com/us/products/2910322




## Classifications

### ECLASS

ECLASS-11.0	27210992
ECLASS-12.0	27210992
ECLASS-13.0	27210992

## ETIM

	ETIM 9.0	EC002498	
UNSPSC			
	UNSPSC 21.0	39121000	



https://www.phoenixcontact.com/us/products/2910322



## Environmental product compliance

#### EU RoHS

Fulfills EU RoHS substance requirements	Yes, No exemptions		
China RoHS			
Environment friendly use period (EFUP)	EFUP-E		
	No hazardous substances above the limits		
EU REACH SVHC			
REACH candidate substance (CAS No.)	No substance above 0.1 wt%		



2910322 https://www.phoenixcontact.com/us/products/2910322



Accessories

PACT RCP-CLAMP - Holder

2904895 https://www.phoenixcontact.com/us/products/2904895



The optional holding device ensures the Rogowski coil is securely seated on busbars with a thickness of 10 ... 15 mm. During installation, the coil housing is pushed onto the flange of the holding device and snaps in automatically.

Phoenix Contact 2024 © - all rights reserved https://www.phoenixcontact.com

Phoenix Contact USA 586 Fulling Mill Road Middletown, PA 17057, United States (+717) 944-1300 info@phoenixcon.com