Supplementary Catalogue 4

to Full Line Catalog W4 Volume 1 and Volume 2

NEU
NEW
NOUVEAU
NUOVO
新製品
NOVO
НОВЫЙ

ELECTRICAL INTERCONNECTIONS

Rail-Mounted Terminal Block Systems

PCB Terminal Blocks and Connectors

NOWOŚĆ
NYHET
NUEVO
UUTUUS
신제품
–नया
NIEUW
NY

WAGO®
INNOVATIVE CONNECTIONS

Contents
Volume 1

TOPJOB®S
Double Potential Terminal Blocks 1.5 (2.5) mm²/AWG 16 Series 2001

0.25 – 1.5 (2.5) mm² ❶ | AWG 22 – 14
800 V/8 kV/3
I_N 18 A (24 A)
Terminal block width 4.2 mm / 0.165 in
9 – 11 mm / 0.39 in

❶ can be connected: 0.25 mm² – 2.5 mm² "s + f-st";
can be pushed in directly: 0.5 mm² – 2.5 mm² "s" and
0.75 mm² – 1.5 mm² "insulated ferrule, 12 mm / 0.472 in"



Item No.	Pack.-unit pcs
Double potential terminal block,	
grey **2001-1441**	100

Attention! This double potential terminal block cannot be commoned with push-in type jumper bars!

Accessoires appropriate marking system **WMB/Marker strips** (see Full Line Catalog W4 Volume 1, Section 14)

End and intermediate plate, 0.8 mm / 0.331 in thick

orange **2002-1492** 100 (4 x 25)
grey **2002-1491** 100 (4 x 25)

Insulation stop , 5 pcs/strip 200 strips

light grey **2001-171** 0.25-0.5 mm²

Double potential terminal blocks are space savers. Two independent through terminal blocks are placed in one insulated housing on one level. The width of the housing is only 4.2 mm / 0.165 in. Compared to standard through terminal blocks, the width is only 2.1 mm / 0.083 in.
Input and output contacts of one circuit are placed on the same side of the terminal block. Both circuits can be individually marked according to input and output.

2.5 (4) mm²/AWG 12 Series 2002

0.25 – 2.5 (4) mm² ❷ | AWG 22 – 12
800 V/8 kV/3
I_N 24 A (32 A)
Terminal block width 5.2 mm / 0.205 in
10 – 12 mm / 0.43 in

❷ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and
0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm / 0.472 in"



Item No.	Pack.-unit pcs
Double potential terminal block,	
grey **2002-1441**	100

Attention! This double potential terminal block cannot be commoned with push-in type jumper bars!

End and intermediate plate, 0.8 mm / 0.331 in thick

orange **2002-1492** 100 (4 x 25)
grey **2002-1491** 100 (4 x 25)

Insulation stop , 5 pcs/strip 200 strips

light grey **2001-171** 0.25-0.5 mm²
dark grey **2002-172** 0.75-1 mm²

Protective warning marker,
for 5 terminal block

yellow **2002-115** 100 (4 x 25)

Double potential terminal blocks are space savers. Two independent through terminal blocks are placed in one insulated housing on one level. The width of the housing is only 5.2 mm / 0.205 in. Compared to standard through terminal blocks, the width is only 2.6 mm / 0.103 in.
Input and output contacts of one circuit are placed on the same side of the terminal block. Both circuits can be individually marked according to input and output.

0.25 – 2.5 (4) mm² ❶	AWG 22 – 12
800 V/8 kV/3	600 V, 20 A
I_N 24 A	600 V, 20 A
Terminal block width 5.2 mm / 0.205 in	
10 – 12 mm / 0.43 in	
*	

0.25 – 2.5 (4) mm² ❶	AWG 22 – 12
800 V/8 kV/3	600 V, 20 A
I_N 24 A	600 V, 20 A
Terminal block width 5.2 mm / 0.205 in	
10 – 12 mm / 0.43 in	
*	

❶ can be connected: 0.25 mm² – 4 mm² "s+f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and
0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm/0.472 in"



	Item No.	Pack.-unit pcs
3-conductor through terminal blocks		
grey	**2002-6301**	100
blue	**2002-6304** ❷	100
orange	**2002-6302**	100
more colors are being prepared		
3-conductor ground (earth) terminal block		
green-yellow	**2002-6307**	100
Ex approvals in preparation		
❷ Suitable for Ex i applications		

	Item No.	Pack.-unit pcs
4-conductor through terminal blocks		
grey	**2002-6401**	100
blue	**2002-6404** ❷	100
orange	**2002-6402**	100
more colors are being prepared		
4-conductor ground (earth) terminal block		
green-yellow	**2002-6407**	100
Ex approvals in preparation		
❷ Suitable for Ex i applications		
Attention!		
These terminal blocks cannot be commoned!		

Accessories

appropriate marker system (see Full Line Catalog W4 Vol. 1, Sec. 14)

WMB/Marker strips/WMB Inline

		Item No.	Pack.-unit pcs
End and intermediate plate, 0.8 mm / 0.031 in thick			
	orange	**2002-6392**	100 (4 x 25)
	grey	**2002-6391**	100 (4 x 25)
Insulation stop, 5 pcs/strip			200 strips
	light grey	**2002-171**	0.25-0.5 mm²
	dark grey	**2002-172**	0.75-1 mm²
Push-in type jumper bars, light grey, insulated, I_N 25 A			
	2-way	**2002-402**	200 (8 x 25)
	3-way	**2002-403**	200 (8 x 25)
	4-way	**2002-404**	200 (8 x 25)
	5-way	**2002-405**	100 (4 x 25)
	:	:	
	10-way	**2002-410**	100 (4 x 25)
Push-in type jumper bars, light grey, insulated, I_N 25 A			
	1 - 3	**2002-433**	200 (8 x 25)
	1 - 4	**2002-434**	200 (8 x 25)
	1 - 5	**2002-435**	100 (4 x 25)
	:	:	
	1 - 10	**2002-440**	100 (4 x 25)
Protective warning marker,			
	for 5 terminal blocks		
	yellow	**2002-115**	100 (4 x 25)
Modular TOPJOB®S connector,			
	for jumper contact slot		
	1 pole	**2002-511**	100 (4 x 25)
Spacer, modular		**2002-549**	100 (4 x 25)
Test plug adapter, for test plug 4 mm/0.157 in Ø		**2009-174**	100 (4 x 25)
Testing tap, for max. 2.5 mm²		**2009-182**	100 (4 x 25)

		Item No.	Pack.-unit pcs
End and intermediate plate, 0.8 mm / 0.031 in thick			
	orange	**2002-6392**	100 (4 x 25)
	grey	**2002-6391**	100 (4 x 25)
Insulation stop, 5 pcs/strip			200 strips
	light grey	**2002-171**	0.25-0.5 mm²
	dark grey	**2002-172**	0.75-1 mm²
Protective warning marker,			
	for 5 terminal blocks		
	yellow	**2002-115**	100 (4 x 25)

3- and 4-conductor terminal blocks

The new TOPJOB®S rail-mounted terminal blocks have a conductor entry angle of 35 degrees allowing for a very small bend radius and an extremely short wiring distance to the cable duct. For applications in switchgear and control cabinets using the LSC wiring system from Lütze, for example, the new terminal blocks offer a space and cost saving solution. This way, conductors can be placed very close to the terminal blocks and their height can be kept relatively low.

Product characteristics

- CAGE CLAMP®S connection for all types of conductors, with the additional benefit that stripped solid wires and fine-stranded ferruled wires can be simply pushed in
- Vibration-proof, fast, maintenance-free connection
- 3-conductor through and ground (earth) conductor terminal blocks equipped with dual jumper slot
- 4-conductor terminal blocks allow for the multiplication of potentials without using any jumpers and any additional terminal blocks
- 3- and 4-conductor terminal blocks have the same dimensions

* Further approvals with corresponding ratings can be found at www.wago.com

0.25 – 1.5 (2.5) mm² ❶	AWG 22 – 14
500 V/6 kV/3	300 V, 15 A
I_N 18 A	300 V, 15 A
Terminal block width 4.2 mm / 0.165 in	
9 – 11 mm / 0.39 in	
*	

0.25 – 2.5 (4) mm² ❷	AWG 22 – 12
500 V/6 kV/3	300 V, 20 A
I_N 24 A	300 V, 20 A
Terminal block width 5.2 mm / 0.205 in	
10 – 12 mm / 0.43 in	
*	

0.5 – 4 (6) mm² ❸	AWG 20 – 10
500 V/6 kV/3	300 V, 30 A
I_N 32 A	300 V, 30 A
Terminal block width 6.2 mm / 0.244 in	
11 – 13 mm / 0.47 in	
*	

Item No.	Pack.-unit pcs
Modular TOPJOB®S connectors	
with CAGE CLAMP®S connection, modular, grey,	
1 pole **2001-511**	100 (4 x 25)
Spacer, for bridging over commoned terminal blocks, for example, modular, grey	
2001-549	100 (4 x 25)
❶ can be connected: 0.25 mm² – 2.5 mm² "s + f-st"; can be pushed in directly: 0.5 mm² – 2.5 mm² "s" and 0.75 mm² – 1.5 mm² "insulated ferrule, 12 mm / 0.472 in"	
Item-specific accessories	
End plate, 1.5 mm/0.059 in thick	
grey **2002-541**	100 (4 x 25)
WMB Multi marking card, 10 strips with 10 markers each, white with black printing, 4 – 4.2 mm/0.157 - 0.165 in wide	
793-4 . . .	5 cards
794-4 . . .	5 cards
see Full Line Catalog W4 Volume 1, Section 14	

Item No.	Pack.-unit pcs
Modular TOPJOB®S connectors	
with CAGE CLAMP®S connection, modular, grey,	
1 pole **2002-511**	100 (4 x 25)
Spacer, for bridging over commoned terminal blocks, for example, modular, grey	
2002-549	100 (4 x 25)
❷ can be connected: 0.25 mm² – 4 mm² "s + f-st"; can be pushed in directly: 0.75 mm² – 4 mm² "s" and 0.75 mm² – 2.5 mm² "insulated ferrules, 12 mm / 0.472 in"	
Item-specific accessories	
End plate, 1.5 mm/0.059 in thick	
grey **2002-541**	100 (4 x 25)
WMB Multi marking card, 10 strips with 10 markers each, white with black printing, 5 – 5.2 mm/0.197 - 0.205 in wide	
793-5 . . .	5 cards
794-5 . . .	5 cards
see Full Line Catalog W4 Volume 1, Section 14	

Item No.	Pack.-unit pcs
Modular TOPJOB®S connectors	
with CAGE CLAMP®S connection, modular, grey,	
1 pole **2004-511**	100 (4 x 25)
Spacer, for bridging over commoned terminal blocks, for example, modular, grey	
2004-549	100 (4 x 25)
❸ can be connected: 0.5 mm² – 6 mm² "s + f-st"; can be pushed in directly: 1 mm² – 6 mm² "s" and 0.75 mm² – 4 mm² "insulated ferrule, 12 mm / 0.472 in"	
Item-specific accessories	
End plate, 1.5 mm/0.059 in thick	
grey **2002-541**	100 (4 x 25)
WMB Multi marking card, 10 strips with 10 markers each, white with black printing, 5 – 5.2 mm/0.197 - 0.205 in wide	
793-5 . . .	5 cards
794-5 . . .	5 cards
see Full Line Catalog W4 Volume 1, Section 14	



Snapping together of connectors and spacers to assemble a multi-pole connector

Wire connection:
Screwdriver actuation for connection of all conductor types, i.e. stripped stranded conductors, or push-in connection of solid or ferruled stranded conductors.

Snapping on a strain relief plate

Accessories for TOPJOB®S connectors

appropriate marker system **WMB/Marker strips** (see Full Line Catalog W4 Volume 1, Section 14)

Test plug, with cable 500 mm / 17.7"			
2.3 mm/0.091 in Ø			
yellow	**210-137**		50 (5 x 10)
Test plug, with cable 500 mm / 17.7"			
2 mm/0.079 in Ø			
red	**210-136**		50 (5 x 10)

Strain relief plate, grey			
snappable onto connector strips			
6 mm / 0.236 in wide	**734-327**		100 (4 x 25)
12.5 mm / 0.492 in wide	**734-328**		100 (4 x 25)
25 mm / 0.984 in wide	**734-329**		100 (4 x 25)
35 mm / 1.378 in wide	**734-326**		100 (4 x 25)

Marker strips, withe, plain, on roll			
11 mm / 0.039 in wide			
50 m	**2009-110**		1
Marker strips, withe, plain, on roll			
11 mm / 0.039 in wide			
300 m	**2009-130**		1

* Further approvals with corresponding ratings can be found at www.wago.com

0.25 – 1.5 (2.5) mm² ❶	AWG 22 – 14
500 V/6 kV/3	300 V, 15 A
I_N 18 A	300 V, 15 A
Terminal block width 4.2 mm / 0.165 in	
9 – 11 mm / 0.39 in	

0.25 – 2.5 (4) mm² ❷	AWG 22 – 12
500 V/6 kV/3	300 V, 20 A
I_N 24 A	300 V, 20 A
Terminal block width 5.2 mm / 0.205 in	
10 – 12 mm / 0.43 in	

0.5 – 4 (6) mm² ❸	AWG 20 – 10
500 V/6 kV/3	300 V, 30 A
I_N 32 A	300 V, 30 A
Terminal block width 6.2 mm / 0.244 in	
11 – 13 mm / 0.47 in	

Item No.	Pack.-unit pcs
Modular TOPJOB®S connector strips	
with CAGE CLAMP®S connection, modular, grey,	
2-pole **2001-552**	
3-pole **2001-553**	
4-pole **2001-554**	
5-pole **2001-555**	
6-pole **2001-556**	
7-pole **2001-557**	
8-pole **2001-558**	
9-pole **2001-559**	
10-pole **2001-560**	
❶ can be connected: 0.25 mm² – 2.5 mm² "s + f-st"; can be pushed in directly: 0.5 mm² – 2.5 mm² "s" and 0.75 mm² – 1.5 mm² "insulated ferrule, 12 mm / 0.472 in"	

Item-specific accessories

WMB Multi marking card, 10 strips with 10 markers each, white with black printing, 4 – 4.2 mm / 0.157 - 0.165 in wide

793-4 . . . 5 cards

794-4 . . . 5 cards

see Full Line Catalog W4 Volume 1, Section 14

Item No.	Pack.-unit pcs
Modular TOPJOB®S connector strips	
with CAGE CLAMP®S connection, modular, grey,	
2-pole **2002-552**	
3-pole **2002-553**	
4-pole **2002-554**	
5-pole **2002-555**	
6-pole **2002-556**	
7-pole **2002-557**	
8-pole **2002-558**	
9-pole **2002-559**	
10-pole **2002-560**	
❷ can be connected: 0.25 mm² – 4 mm² "s + f-st"; can be pushed in directly: 0.75 mm² – 4 mm² "s" and 0.75 mm² – 2.5 mm² "insulated ferrules, 12 mm / 0.472 in"	

Item-specific accessories

WMB Multi marking card, 10 strips with 10 markers each, white with black printing, 5 – 5.2 mm / 0.197 - 0.205 in wide

793-5 . . . 5 cards

794-5 . . . 5 cards

see Full Line Catalog W4 Volume 1, Section 14

Miniature WSB Quick marking card, 10 strips with 10 markers each, white with black printing, 5 mm / 0.197 in wide

248- . . . 5 cards

249- . . . 5 cards

see Full Line Catalog W4 volume 1, section 14

WMB Inline, pitch 5 mm / 0.197 in, strechable 5 mm – 5.2 mm / 0.197 in – 0.205 in, on roll, 1,500 markers withe **2009-115** 1

Item No.	Pack.-unit pcs
Modular TOPJOB®S connector strips	
with CAGE CLAMP®S connection, modular, grey,	
2-pole **2004-552**	
3-pole **2004-553**	
4-pole **2004-554**	
5-pole **2004-555**	
❸ can be connected: 0.5 mm² – 6 mm² "s + f-st"; can be pushed in directly: 1 mm² – 6 mm² "s" and 0.75 mm² – 4 mm² "insulated ferrule, 12 mm / 0.472 in"	

Item-specific accessories

WMB Multi marking card, 10 strips with 10 markers each, white with black printing, 5 – 5.2 mm / 0.197 - 0.205 in wide

793-5 . . . 5 cards

794-5 . . . 5 cards

see Full Line Catalog W4 Volume 1, Section 14



The modular connectors provide an additional connection option for conductors of the same cross section range as the terminal blocks being used.



The connector has a test socket for 2 mm / 0.079 in or 2.3 mm / 0.091 in test plugs.

Accessories for TOPJOB®S connectors

appropriate marker system **WMB/Marker strips** (see Full Line Catalog W4 Volume 1, Section 14)

Test plug, with cable 500 mm / 17.7"

2.3 mm / 0.091 in Ø

yellow **210-137** 50 (5 x 10)

Test plug, with cable 500 mm / 17.7"

2 mm / 0.079 in Ø

red **210-136** 50 (5 x 10)

Strain relief plate, grey, snappable onto connector strips

6	mm / 0.236 in wide	**734-327**	100 (4 x 25)
12.5	mm / 0.492 in wide	**734-328**	100 (4 x 25)
25	mm / 0.984 in wide	**734-329**	100 (4 x 25)
35	mm / 1.378 in wide	**734-326**	100 (4 x 25)

Marker strips, withe, plain, on roll

11 mm / 0.039 in wide

50 m **2009-110** 1

Marker strips, withe, plain, on roll

11 mm / 0.039 in wide

300 m **2009-130** 1

TOPJOB®S
Double Deck Terminal Blocks 2.5 (4) mm² /AWG 12
Series 2002

0.25 – 2.5 (4) mm² ❶ **AWG 22 – 12** **500 V/6 kV/3** **600 V, 20 A** **I_N 24 A** **600 V, 20 A** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in** *	**0.25 – 2.5 (4) mm²** ❶ **AWG 22 – 12** **500 V/6 kV/3** **600 V, 20 A** **I_N 24 A** **600 V, 20 A** **Terminal block width 5.2 / 0.205 in** **10 – 12 mm / 0.43 in** *

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and
0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm/0.472 in"



	Item No.	Item No.	Pack.-unit pcs
Double deck terminal blocks, for DIN 35 rail			
Through-/through terminal blocks,			
housing color grey			
Marking carrier with		without	
L/L	**2002-2231**	**2002-2201**	50
N/L	**2002-2232**	**2002-2202**	50
L/N	**2002-2233**	**2002-2203**	50
Housing color blue			
N/N	**2002-2234** ❷	**2002-2204** ❷	50
Ex applications are being prepared			
❷ Suitable for Ex i applications			

	Item No.	Item No.	Pack.-unit pcs
Double deck terminal blocks, for DIN 35 rail			
4-conductor through terminal block, internal commoning,			
housing color grey, conductor entry position colored in violet			
Marking carrier with		without	
L	**2002-2238**	**2002-2208**	50
4-conductor through terminal block,			
internal commoning, housing color blue,			
conductor entry position colored in violet			
N	**2002-2239** ❷	**2002-2209** ❷	50
Ex applications are being prepared			
❷ Suitable for Ex i applications			

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and
0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm/0.472 in"



	Item No.	Item No.	Pack.-unit pcs
Double deck terminal blocks, for DIN 35 rail			
Ground (earth) conductor/through terminal block,			
Housing color grey			
Marking carrier with		without	
PE/N	**2002-2247**	**2002-2217**	50
PE/L	**2002-2257**	**2002-2227**	50
Ex applications are being prepared			

	Item No.	Item No.	Pack.-unit pcs
Double deck terminal blocks, for DIN 35 rail			
4-conductor ground (earth) terminal block,			
internal commoning			
Housing color green-yellow			
Marking carrier with		without	
PE	**2002-2237**	**2002-2207**	50
Ex applications are being prepared			

Item No.	Pack.-unit pcs

Accessories

appropriate marking system **WMB/marker strips/WMB Inline** (see Full Line Catalog W4 Volume 1, Section 14)

End and intermediate plate, 0.8 mm/0.032 in thick

orange	**2002-2292**	100 (4 x 25)
grey	**2002-2291**	100 (4 x 25)

Two-way marking adapter,

pivotable		
2002-121		50 (4 x 25)

Protective warning marker,

for 5 terminal blocks		
yellow	**2002-115**	100 (4 x 25)

Push-in type jumper bars, light grey, insulated, I_N

2-way	**2002-402**	200 (8 x 25)
3-way	**2002-403**	200 (8 x 25)
4-way	**2002-404**	200 (8 x 25)
5-way	**2002-405**	100 (4 x 25)
:	:	
10-way	**2002-410**	100 (4 x 25)

Push-in type jumper bars, light grey, insulated, I_N

1 - 3	**2002-433**	200 (8 x 25)
1 - 4	**2002-434**	200 (8 x 25)
1 - 5	**2002-435**	100 (4 x 25)
:	:	
1 - 10	**2002-440**	100 (4 x 25)

Marker strips, white, plain, for central marking,

11 mm/0.433 in wide,		
on roll		
50 m	**2009-110**	1
300 m	**2009-130**	1

Insulation stop,

see page 17 TOPJOB®S Catalog

* Further approvals with corresponding ratings can be found at www.wago.com

Triple Deck Terminal Blocks 2.5 (4) mm²/AWG 12
Series 2002

0.25 – 2.5 (4) mm² ❶	AWG 22 – 12
500 V/6 kV/3	600 V, 20 A
I_N 24 A	600 V, 20 A
Terminal block width 5.2 / 0.205 in	
10 – 12 mm / 0.43 in	
*	

0.25 – 2.5 (4) mm² ❶	AWG 22 – 12
500 V/6 kV/3	600 V, 20 A
I_N 24 A	600 V, 20 A
Terminal block width 5.2 mm / 0.205 in	
10 – 12 mm / 0.43 in	
*	

0.25 – 2.5 (4) mm² ❶	AWG 22 – 12
500 V/6 kV/3	600 V, 20 A
I_N 24 A	600 V, 20 A
Terminal block width 5.2 mm / 0.205 in	
10 – 12 mm / 0.43 in	
*	

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and 0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm/0.472 in"







	Item No.	Item No.	Pack.-unit pcs
Triple deck terminal blocks, for DIN 35 rail			
Through-/through-/through terminal blocks,			
housing color grey			
Marking carrier with		without	
L/L/L	**2002-3231**	**2002-3201**	50
L/L/N	**2002-3233**	**2002-3203**	50
Housing color blue			
N/N/N	**2002-3234** ❷	**2002-3204** ❷	50
Ⓔx applications are being prepared			
❷ Suitable for Ex i applications			

	Item No.	Item No.	Pack.-unit pcs
Triple deck terminal block, for DIN 35 rail			
6-conductor through terminal block, internal commoning,			
housing color grey, conductor entry position colored in violet			
Marking carrier with		without	
L	**2002-3238**	**2002-3208**	50
6-conductor through terminal block,			
internal commoning, housing color blue,			
conductor entry position colored in violet			
N	**2002-3239** ❷	**2002-3209** ❷	50
Ⓔx applications are being prepared			
❷ Suitable for Ex i applications			

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and 0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm/0.472 in"









	Item No.	Item No.	Pack.-unit pcs
Triple deck terminal blocks, for DIN 35 rail			
Ground (earth)/through/through terminal blocks,			
housing color grey			
Marking carrier with		without	
PE/N/L	**2002-3247**	**2002-3217**	50
PE/L/L	**2002-3257**	**2002-3227**	50
Ⓔx applications are being prepared			

	Item No.	Item No.	Pack.-unit pcs
Triple deck terminal block, for DIN 35 rail			
Shield (screen)/through/through terminal blocks,			
housing color grey			
Marking carrier with		without	
Schirm/N/L	**2002-3248**	**2002-3218**	50
Schirm/L/L	**2002-3258**	**2002-3228**	50
Ⓔx applications are being prepared			

	Item No.	Item No.	Pack.-unit pcs
Triple deck terminal block, for DIN 35 rail			
6-conductor ground (earth) terminal block,			
internal commoning			
housing color green-yellow			
Marking carrier with		without	
PE	**2002-3237**	**2002-3207**	50
Ⓔx applications are being prepared			

Accessories

appropriate marking system **WMB/marker strips/WMB Inline** (see Full Line Catalog W4 Volume 1, Section 14))

End and intermediate plate, 0.8 mm/0.032 in thick

orange	**2002-3292**	100 (4 x 25)
grey	**2002-3291**	100 (4 x 25)

Two-way marking adapter,

pivotable		
2002-131		50 (2 x 25)

Protective warning marker,

for 5 terminal blocks		
yellow	**2002-115**	100 (4 x 25)

Push-in type jumper bars, light grey, insulated, I_N

2-way	**2002-402**	200 (8 x 25)
3-way	**2002-403**	200 (8 x 25)
4-way	**2002-404**	200 (8 x 25)
5-way	**2002-405**	100 (4 x 25)
:	:	
10-way	**2002-410**	100 (4 x 25)

Push-in type jumper bars, light grey, insulated, I_N

1 - 3	**2002-433**	200 (8 x 25)
1 - 4	**2002-434**	200 (8 x 25)
1 - 5	**2002-435**	100 (4 x 25)
:	:	
1 - 10	**2002-440**	100 (4 x 25)

Marker strips, white, plain, for central marking,



11 mm/0.433 in wide,		
on roll		
50 m	**2009-110**	1
300 m	**2009-130**	1

Insulation stop,

see page 17 TOPJOB®S Catalog

TOPJOB®S

Very compact dimensions provide maximum wiring space in standard distribution boxes. The 2003 Series multilevel installation terminal blocks are the smallest terminal blocks with direct insertion wire connection on the market providing the full functionality of a 4 mm²/AWG 12 terminal block.

Push-in type jumper bars with breakable contact lugs offer the same benefits to the TOPJOB®S installation terminal blocks as to the rail-mounted terminal blocks (e.g. individual jumper configuration on site, skipping of potentials, etc.).

Screwless N-disconnect slide link for automatic and safe connection onto the N-busbar by simply sliding the link.

The busbar carrier with end stop function, which is only **7.5 mm / 0.295 in wide** can replace end stop.

The detachable separator plate on the carrier can be used both for separating the different potentials of N-busbars that are directly next to each other or as a touch-proof end plate for an N-busbar.



The compact busbar carrier, which is placed every 200 mm / 7.87 in, is used to additionally support the busbar on a long assembly.

Perforations make it possible to fit the carrier to all TOPJOB®S installation terminal blocks using a single part.

Each connection point has an individual marker receptacle for WMB markers. Additionally, the upper marker receptacle is suitable for marker strips that can be marked manually using a marker pen or automatically by a thermal transfer printer.

Commoning is done using the new staggered jumper system in one single TOPJOB®S jumper slot. The multilevel installation terminal blocks of Series 2003 are therefore suitable for use in very confined spaces.

The optional busbar transparent cover (item no. 777-303) protects the busbar against accidental contact and makes it easy to see which terminal blocks are connected to the busbar.



Removal of staggered jumpers
Insert the screwdriver blade between the jumpers and lift them up.

Environmentally friendly:
TOPJOB®S terminal blocks are **100 % lead-free!**

The conductor entry holes of the multilevel installation terminal blocks are color marked, providing a clear arrangement of the terminals.

The grounding foot automatically guarantees a safe connection to the carrier rail.

TOPJOB®S – The range of terminal blocks for all types of applications.

- The direct connection of solid wires in small distribution boxes saves time and money.
- Operating errors can be prevented as all types of terminal blocks for building installation are equipped with push-in connection technology.
- Terminal blocks for building installation expand circuit design possibilities.
- The use of standard accessories reduces order-processing and stock-holding costs.
- A high level of application safety is achieved through optimum knowledge of the small range of parts.
- As the position of the busbars is the same, the new TOPJOB®S installation terminal blocks are compatible with standard topJob installation terminal blocks.

TOPJOB® S
Multilevel Installation Terminal Blocks 4 mm²/AWG 12
Series 2003

0.25 – 2.5 (4) mm²❶ AWG 22 – 12
250 V/4 kV❷/3 400 V/6 kV❸/3
I_N 32 A
Terminal block width 5.2 mm / 0.205 in
10 – 12 mm / 0.43 in

0.25 – 2.5 (4) mm²❶ AWG 22 – 12
400 V/6 kV/3
I_N 32 A
Terminal block width 5.2 mm / 0.205 in
10 – 12 mm / 0.43 in

Accessories for
2003 Series multilevel installation terminal blocks and
2002/2006/2016 Series N-conductor disconnect terminal blocks

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and
0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm / 0.472 in"



	Item No.	Pack.-unit pcs
Multilevel installation terminal block, grey		
with N-disconnect slide link		
NT/L/PE	**2003-7641**	50

	Item No.	Pack.-unit pcs
Multilevel installation terminal blocks, grey		
L/L	**2003-7642**	50
N/L	**2003-7649**	50

❷ Potential-Ground ❸ Potential-Potential



	Item No.	Pack.-unit pcs
Multilevel installation terminal blocks, grey		
N/L/PE	**2003-7646**	50
L/L/PE	**2003-7645**	50

Staggered jumper with 7 contacts
Breaking off contact lugs

Staggered jumper 1 – 3 – 5 – 7
Marking with a felttip pen

Commoning using staggered jumpers

Individual jumper contacts can be broken off by bending them. The remaining piece of insulation meets the requirements for the air and creepage distance.

This makes it possible to create custom staggered jumpers, e.g. for bridging over a terminal block with a different potential. When creating the jumpers, make sure that only one contact lug is in contact with the terminal block.

That way, staggered jumpers are created whose contact lugs will make contact to the terminal block in the gaps of the second jumper. Insert the jumper into the jumper slot up to the stop.

Two staggered jumpers 1 – 3 – 5 – 7
staggered for use in a jumper slot

Locate red stripes of the **staggered jumpers** on the inside

	Item No.	Pack.-unit pcs
End and intermediate plate, 1 mm / 0.039 in thick		
orange	**2003-7692**	100 (4 x 25)
Busbar carrier, for DIN rail 35 (not suitable for use as end stop)		
1.5 mm / 0.059 in thick		
blue	**2009-304**	100 (4 x 25)
Busbar carrier with end stop function and detachable separator plate, for DIN rail 35; 7.5 mm / 0.295 in thick		
blue	**2009-305**	25
N-busbar, tinned		see page 11
Cover for N-busbar, transparent		see page 11
Neutral supply terminal block, I_N 76 A, 16 mm²/AWG 6, blue, 12 mm / 0.472 in wide	**2016-7114**	25
Ground (earth) supply terminal block, I_N 76 A, 16 mm²/AWG 6, green-yellow, 12 mm / 0.472 in wide	**2016-1207**	20
TOPJOB® S **tool,** special blades 3.5 mm / 0.137 in and 5.5 mm / 0.217 in	**2009-310**	1
Connector, with blue cover		see page 11
Connector, uninsulated,		see page 11
Push-in type jumper bars, light grey, insulated, I_N 25 A		
2-way	**2002-402**	200 (8 x 25)
3-way	**2002-403**	200 (8 x 25)
4-way	**2002-404**	200 (8 x 25)
5-way	**2002-405**	100 (4 x 25)
:	:	
10-way	**2002-410**	100 (4 x 25)
Push-in type jumper bars, light grey, insulated, I_N 25 A		
1 - 3	**2002-433**	200 (8 x 25)
1 - 4	**2002-434**	200 (8 x 25)
1 - 5	**2002-435**	100 (4 x 25)
:	:	
1 - 10	**2002-440**	100 (4 x 25)
Staggered jumper, light grey, insulated, I_N 25 A		
2-way	**2002-472**	100 (4 x 25)
3-way	**2002-473**	100 (4 x 25)
4-way	**2002-474**	100 (4 x 25)
5-way	**2002-475**	50 (2 x 25)
:	:	
12-way	**2002-482**	50 (2 x 25)
Pre-assembled staggered jumpers, with contact lugs that are factory removed with circuit printing, I_N 25 A		
1-3	**2002-473/0011-0000**	
1-3-5	**2002-475/0011-0000**	
1-3-5-7	**2002-477/0011-0000**	
1-3-5-7-9	**2002-479/0011-0000**	
1-3-5-7-9-11	**2002-481/0011-0000**	
Test plug, Ø 2 mm / 0.079 in	**210-136**	50 (5 x 10)
Test plug adapter, for test plug Ø 4 mm / 0.157 in	**2009-174**	100 (4 x 25)
Testing tap, for max. 2.5 mm²/AWG 14	**2009-182**	100 (4 x 25)

Multilevel Installation Terminal Blocks 6 mm²/AWG 8 Series 2005

0.5 – 4 (6) mm² ❶ AWG 20 – 10
250 V/4 kV ❷/3 400 V/6 kV ❸/3
I_N 36 A
Terminal block width 6.2 mm / 0.244 in
11 – 13 mm / 0.47 in

0.5 – 4 (6) mm² ❶ AWG 20 – 10
400 V/6 kV/3
I_N 36 A
Terminal block width 6.2 mm / 0.244 in
11 – 13 mm / 0.47 in

Accessories for
2005 Series multilevel installation terminal blocks and
2002/2006/2016 Series N-conductor disconnect terminal blocks

❶ can be connected: 0.5 mm² – 6 mm² "s + f-st";
can be pushed in directly: 1 mm² – 6 mm² "s" and
0.75 mm² – 4 mm² "insulated ferrule, 12 mm / 0.472 in"







	Item No.	Pack.-unit pcs
Multilevel installation terminal block, grey		
with N-disconnect slide link		
NT/L/PE	**2005-7641**	50

❷ Potential-Ground ❸ Potential-Potential

	Item No.	Pack.-unit pcs
Multilevel installation terminal blocks, grey		
L/L	**2005-7642**	50
N/L	**2005-7649**	50

	Item No.	Pack.-unit pcs
Multilevel installation terminal blocks, grey		
N/L/PE	**2005-7646**	50
L/L/PE	**2005-7645**	50

	Item No.	Pack.-unit pcs
End and intermediate plate, 1 mm / 0.039 in thick		
orange	**2005-7692**	100 (4 x 25)
Busbar carrier, for DIN rail 35 (not suitable for use as end stop)		
1.5 mm / 0.059 in thick		
blue	**2009-304**	100 (4 x 25)
Busbar carrier with end stop function and detachable separator plate, for DIN rail 35; 7.5 mm / 0.295 in thick		
blue	**2009-305**	25
N-busbar, tinned		
Copper 10 mm x 3 mm, I_N 140 A, 1000 mm / 39.37 in long	**210-133**	20 (20 x 1)
Cover for N-busbar		
transparent		
1000 mm / 39.37 in long	**777-303**	1
Neutral supply terminal block, I_N 76 A, 16 mm², blue		
12 mm / 0.472 in wide	**2016-7114**	25
Ground (earth) supply terminal block, I_N 76 A, 16 mm²/AWG 6, green-yellow, 12 mm / 0.472 in wide	**2016-1207**	20
14 Connector, with blue cover, for N-busbar 2.5 mm² – 16 mm²/AWG 14 – 6	**210-281**	100 (2 x 50)
Connector, uninsulated, for N-busbar 2.5 mm² – 35 mm²/AWG 14 – 2	**209-105**	50 (2 x 25)
TOPJOB®S **tool,** special blades 3.5 mm / 0.137 in and 5.5 mm / 0.217 in	**2009-310**	1
Push-in type jumper bars, light grey, insulated, I_N 32 A		
2-way	**2004-402**	100 (4 x 25)
3-way	**2004-403**	100 (4 x 25)
4-way	**2004-404**	100 (4 x 25)
5-way	**2004-405**	50 (2 x 25)
:	:	
10-way	**2004-410**	50 (2 x 25)
Push-in type jumper bars, light grey, insulated, I_N 32 A		
1 - 3	**2004-433**	100 (4 x 25)
1 - 4	**2004-434**	100 (4 x 25)
1 - 5	**2004-435**	50 (2 x 25)
:	:	
1 - 10	**2004-440**	50 (2 x 25)
Test plug, Ø 2 mm / 0.079 in	**210-136**	50 (5 x 10)
Test plug adapter, for test plug Ø 4 mm / 0.157 in	**2009-174**	100 (4 x 25)
Testing tap, for max. 2.5 mm²/AWG 14	**2009-182**	100 (4 x 25)

TOPJOB®S
N-Disconnect Terminal Blocks and Power Distribution Disconnect Terminal Blocks Series 2002, 2006 and 2016

0.25 – 2.5 (4) mm² ❶ 250 V/4 kV/3 I_N 32 A | AWG 22 – 12	0.5 – 6 (10) mm² ❶ 250 V/4 kV/3 I_N 51 A | AWG 20 – 8	0.5 – 16 (25 "f") mm² ❶ 250 V/4 kV/3 I_N 76 A | AWG 20 – 4
Terminal block width 5.2 mm / 0.205 in	Terminal block width 7.5 mm / 0.295 in	Terminal block width 12 mm / 0.472 in
10 – 12 mm / 0.43 in	13 – 15 mm / 0.55 in	18 – 20 mm / 0.75 in







	Item No.	Pack.-unit pcs
1-conductor N-disconnect terminal block		
blue	**2002-7114** ❷	50
1-conductor power distribution disconnect terminal block		
grey	**2002-7111** ❸	50
End and intermediate plate, 0.8 mm / 0.031 in thick		
orange	**2002-7192**	100 (4 x 25)
For appropriate through and earth conductor terminal blocks see page 17 in TOPJOB®S catalog		

	Item No.	Pack.-unit pcs
1-conductor N-disconnect terminal block		
blue	**2006-7114** ❷	50
1-conductor power distribution disconnect terminal block		
grey	**2006-7111** ❸	50
End and intermediate plate, 1 mm / 0.039 in thick		
orange	**2006-7192**	100 (4 x 25)
For appropriate through and earth conductor terminal blocks see page 17 in TOPJOB®S catalog		

	Item No.	Pack.-unit pcs
1-conductor N-disconnect terminal block		
blue	**2016-7114** ❷	25
1-conductor power distribution disconnect terminal block		
grey	**2016-7111** ❸	25
End and intermediate plate, 1 mm / 0.039 in thick		
orange	**2016-7192**	100 (4 x 25)
For appropriate through and earth conductor terminal blocks see page 17 in TOPJOB®S catalog		

Testing with test plug Ø 2 mm

Operation of the slide link using a simple screwdriver



Removing the separator plate from the busbar carrier.

Insertion of the separator plate.
To protect the N-busbar against accidental contact

❶ see also appropriate through terminal blocks

❷ For the construction and operation of power installations in fire hazardous locations or public buildings, such as meeting places, stores, hospitals, schools, theaters, hotels etc., the VDE 0100 or VDE 0108-1 standards must be observed. VDE 0100-482 must be observed for fire hazardous locations. Both VDE regulations determine that insulation testing must be possible for every circuit without disconnecting the N-conductor.
WAGO N-disconnect terminal blocks meet this requirement.

❸ According to VDE 0107 "Installing and testing electrical installations in medical locations", the equipotential bonding conductors must be connected to a potential equalization busbar. The potential equalization busbar and the protective earth conductor busbar must be accommodated in a common housing and be connected by means of a disconnectable connection using a copper conductor with a minimum cross section of 16 mm²/AWG 6. Furthermore, all equipotential bonding conductors must be connected to the potential equalization busbar in such a way that they are clearly arranged, that they can be disconnected individually and accessed at any time and, depending on their function, they must be provided with captive marking.
The WAGO power distribution disconnect terminal blocks meet these requirements.

TOPJOB®S

Movable knife disconnects clearly indicate the circuit state.



2- and 4-conductor disconnect terminal blocks

The 5.2 mm/0.205 in wide 2- and 4-conductor disconnect terminal blocks, that can be used in both control and process measurement systems as well as transformer circuits, are an addition to the range of TOPJOB®S rail-mounted terminal blocks.





Two lateral and one center marker receptacle for WMB markers or marking strips. Dual jumper slots, in the same position as the other 2002 Series terminal blocks. Commoning options in front of or behind the knife disconnect, depending on which is the power supply side.

Additional marking option using pivoting marking adapters.

Double deck double disconnect terminal blocks

Disconnect terminal blocks of independent potentials are accommodated on two levels in a double deck disconnect terminal block. This results in a space saving arrangement without compromising the clarity of operation. The knife disconnects are located between the conductors and are therefore always in full view of the operator.





One disconnect and one through terminal block are accommodated on two levels in a terminal block that is only 5.2 mm/0.205 in wide.

Diode terminal blocks

These diode terminal blocks have been specially developed for custom diode circuits such as lamp test and collective fault signal circuits.

Using LED terminal blocks, monitoring units can be designed for control and operating circuits.

The terminal blocks provide high density wiring maintaining a width of only 5.2 mm / 0.205 in.

Using push-in type jumper bars opens up additional possibilities when designing custom circuits.



Polarized diode gate, common cathode

Double deck diode terminal blocks





Lamp test circuit

Triple deck diode terminal blocks





Open diode gate, can be connected individually. Using push-in type jumper bars, individual levels can be turned into polarized diode gates.

TOPJOB®S
Disconnect Terminal Blocks for Test and Measurement with Movable Knife Disconnect and Through Terminal Blocks, Series 2002

0.25 – 2.5 (4) mm² ❶ | **AWG 22 – 12** **400 V/6 kV/3** **I_N 16 A** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	**0.25 – 2.5 (4) mm² ❶** | **AWG 22 – 12** **400 V/6 kV/3** **I_N 16 A** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and
0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm / 0.472 in"



	Item No.	Pack.-unit pcs		Item No.	Pack.-unit pcs
2-conductor disconnect terminal block for test and measurement			**2-conductor through terminal blocks,** same profile as disconnect terminal block		
grey	**2002-1671**		grey	**2002-1601**	
blue	**2002-1674**		blue	**2002-1604**	
orange	**2002-1672**		orange	**2002-1602**	

Item-specific accessories

	Item No.	Pack.-unit pcs		Item No.	Pack.-unit pcs
End and intermediate plate, 1 mm / 0.039 in thick			**End and intermediate plate,** 1 mm / 0.039 in thick		
orange	**2002-1692**	100 (4 x 25)	orange	**2002-1692**	100 (4 x 25)
grey	**2002-1691**	100 (4 x 25)	grey	**2002-1691**	100 (4 x 25)

Accessories Series 2002

appropriate marker system **WMB/Marker strips/WMB Inline** (see Full Line Catalog W4 Volume 1, Section 14)

	Item No.	Pack.-unit pcs		Item No.	Pack.-unit pcs
Insulation stop, 5 pcs/strip		200 strips	**Protective warning marker,** for 5 terminal blocks		
light grey	**2002-171**	0.25-0.5 mm²	yellow	**2002-115**	100 (4 x 25)
dark grey	**2002-172**	0.75-1 mm²			
Push-in type jumper bars, light grey, insulated, I_N 25 A			**Staggered jumper,** light grey, insulated, I_N 25 A		
2-way	**2002-402**	200 (8 x 25)	2-way	**2002-472**	100 (4 x 25)
3-way	**2002-403**	200 (8 x 25)	3-way	**2002-473**	100 (4 x 25)
4-way	**2002-404**	200 (8 x 25)	4-way	**2002-474**	100 (4 x 25)
5-way	**2002-405**	100 (4 x 25)	5-way	**2002-475**	50 (2 x 25)
:	:		:	:	
10-way	**2002-410**	100 (4 x 25)	12-way	**2002-482**	50 (2 x 25)
Push-in type jumper bars, light grey, insulated, I_N 25 A			**Test plug adapter,** for test plug Ø 4 mm / 0.157 in		
				2009-174	100 (4 x 25)
1 - 3	**2002-433**	200 (8 x 25)			
1 - 4	**2002-434**	200 (8 x 25)			
1 - 5	**2002-435**	100 (4 x 25)			
:	:				
1 - 10	**2002-440**	100 (4 x 25)	**Testing tap,** for max. 2.5 mm²/AWG 14		
				2009-182	100 (4 x 25)
Modular TOPJOB®S connector, for jumper contact slot			**Two-way marking adapter,** pivotable		
1 pole	**2002-511**	100 (4 x 25)		**2002-121**	50 (4 x 25)
Spacer, modular	**2002-549**	100 (4 x 25)			
Test plug, with cable 500 mm / 17.7"					
Ø 2 mm / 0.079 in					
red	**210-136**	50 (5 x 10)			

Disconnect Terminal Blocks for Test and Measurement with Movable Knife Disconnect and Through Terminal Blocks, Series 2002

0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12 **400 V/6 kV/3** **I_N 16 A** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	**0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12** **400 V/6 kV/3** **I_N 16 A** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and
0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm / 0.472 in"



	Item No.	Pack.-unit pcs
4-conductor disconnect terminal block for test and measurement		
grey	**2002-1871**	
blue	**2002-1874**	
orange	**2002-1872**	
4-conductor through terminal blocks, same profile as disconnect terminal block		
grey	**2002-1801**	
blue	**2002-1804**	
orange	**2002-1802**	

Item-specific accessories

		Item No.	Pack.-unit pcs
End and intermediate plate, 1 mm / 0.039 in thick			
	orange	**2002-1892**	100 (4 x 25)
	grey	**2002-1891**	100 (4 x 25)
End and intermediate plate, 1 mm / 0.039 in thick			
	orange	**2002-1892**	100 (4 x 25)
	grey	**2002-1891**	100 (4 x 25)

Accessories Series 2002

appropriate marker system **WMB/Marker strips/WMB Inline** (see Full Line Catalog W4 Volume 1, Section 14)

		Item No.	Pack.-unit pcs
Insulation stop, 5 pcs/strip			200 strips
	light grey	**2002-171**	0.25-0.5 mm²
	dark grey	**2002-172**	0.75-1 mm²
Protective warning marker, for 5 terminal blocks			
	yellow	**2002-115**	100 (4 x 25)
Push-in type jumper bars, light grey, insulated, I_N 25 A			
	2-way	**2002-402**	200 (8 x 25)
	3-way	**2002-403**	200 (8 x 25)
	4-way	**2002-404**	200 (8 x 25)
	5-way	**2002-405**	100 (4 x 25)
	:	:	
	10-way	**2002-410**	100 (4 x 25)
Staggered jumper, light grey, insulated, I_N 25 A			
	2-way	**2002-472**	100 (4 x 25)
	3-way	**2002-473**	100 (4 x 25)
	4-way	**2002-474**	100 (4 x 25)
	5-way	**2002-475**	50 (2 x 25)
	:	:	
	12-way	**2002-482**	50 (2 x 25)
Push-in type jumper bars, light grey, insulated, I_N 25 A			
	1 - 3	**2002-433**	200 (8 x 25)
	1 - 4	**2002-434**	200 (8 x 25)
	1 - 5	**2002-435**	100 (4 x 25)
	:	:	
	1 - 10	**2002-440**	100 (4 x 25)
Test plug adapter, for test plug Ø 4 mm / 0.157 in			
		**2009-174**	100 (4 x 25)
Testing tap, for max. 2.5 mm²/AWG 14			
		2009-182	100 (4 x 25)
Modular TOPJOB®S connector,** for jumper contact slot			
	1 pole	**2002-511**	100 (4 x 25)
Two-way marking adapter, pivotable			
		**2002-121**	50 (4 x 25)
Spacer, modular		**2002-549**	100 (4 x 25)
Test plug, with cable 500 mm / 17.7" Ø 2 mm / 0.079 in			
	red	**210-136**	50 (5 x 10)

TOPJOB®S
Double Deck Double Disconnect Terminal Blocks for Test and Measurement with Movable Knife Disconnect, Series 2002

0.25 – 2.5 (4) mm² ❶ | **AWG 22 – 12** **400 V/6 kV/3** **I_N 16 A** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	**0.25 – 2.5 (4) mm² ❶** | **AWG 22 – 12** **400 V/6 kV/3** **I_N 16 A** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	**0.25 – 2.5 (4) mm² ❶** | **AWG 22 – 12** **400 V/6 kV/3** **I_N 16 A** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and 0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm / 0.472 in"



	Item No.	Pack.-unit pcs
4-conductor double deck double disconnect terminal blocks		
grey	**2002-2951**	
blue	**2002-2954**	
grey N/L	**2002-2952**	
4-conductor double deck double disconnect terminal blocks, lower deck and upper deck internally commoned on right side and with violet marking		
grey	**2002-2958**	
blue	**2002-2959**	
4-conductor double deck disconnect terminal blocks, with disconnect on uper deck only, same profile as double deck double disconnect terminal blocks		
grey	**2002-2971**	
blue	**2002-2974**	
grey N/L	**2002-2972**	

Item-specific accessories

	Item No.	Pack.-unit pcs
End and intermediate plate, 1 mm / 0.039 in thick		
orange	**2002-2992**	100 (4 x 25)
grey	**2002-2991**	100 (4 x 25)

Accessories Series 2002

appropriate marker system **WMB/Marker strips/WMB Inline** (see also Full Line Catalog W4 Volume 1, Section 14)

	Item No.	Pack.-unit pcs
Insulation stop, 5 pcs/strip		200 strips
light grey	**2002-171**	0.25-0.5 mm²
dark grey	**2002-172**	0.75-1 mm²
Protective warning marker, for 5 terminal blocks		
yellow	**2002-115**	100 (4 x 25)
Test plug, with cable 500 mm / 1'7.7" Ø 2 mm / 0.079 in		
red	**210-136**	50 (5 x 10)
Push-in type jumper bars, light grey, insulated, I_N 25 A		
2-way	**2002-402**	200 (8 x 25)
3-way	**2002-403**	200 (8 x 25)
4-way	**2002-404**	200 (8 x 25)
5-way	**2002-405**	100 (4 x 25)
:	:	
10-way	**2002-410**	100 (4 x 25)
Push-in type jumper bars, light grey, insulated, I_N 25 A		
1 - 3	**2002-433**	200 (8 x 25)
1 - 4	**2002-434**	200 (8 x 25)
1 - 5	**2002-435**	100 (4 x 25)
:	:	
1 - 10	**2002-440**	100 (4 x 25)
Staggered jumper, light grey, insulated, I_N 25 A		
2-way	**2002-472**	100 (4 x 25)
3-way	**2002-473**	100 (4 x 25)
4-way	**2002-474**	100 (4 x 25)
5-way	**2002-475**	50 (2 x 25)
:	:	
12-way	**2002-482**	50 (2 x 25)
Modular TOPJOB®S connector,** for jumper contact slot		
1 pole	**2002-511**	100 (4 x 25)
Spacer, modular	**2002-549**	100 (4 x 25)
Test plug adapter, for test plug Ø 4 mm / 0.157 in	**2009-174**	100 (4 x 25)
Testing tap, for max. 2.5 mm²/AWG 14	**2009-182**	100 (4 x 25)

Diode Terminal Blocks 1.5 (2.5) mm² / AWG 14 and LED Terminal Blocks 1.5 (2.5) mm² / AWG 14; Series 2001

0.25 – 1.5 (2.5) mm² | AWG 22 – 14 **U_N 250 V; U_{RM} 1000 V** **1 N 4007 – 0.5 A continuous current** **Terminal block width 4.2 mm / 0.165 in** **9 – 11 mm / 0.39 in**	**0,25 – 1,5 (2.5) mm² | AWG 22 – 14** **U_N 250 V; U_{RM} 1000 V** **1 N 4007 – 0.5 A continuous current** **Terminal block width 4.2 mm / 0.165 in** **9 – 11 mm / 0.39 in**	**0.25 – 1.5 (2.5) mm² | AWG 22 – 14** **DC 24 V** **I_F 0.025 A max.** **Terminal block width 4.2 mm / 0.165 in** **9 – 11 mm / 0.39 in**

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.5 mm² – 2.5 mm² "s" and 0.75 mm² – 1.5 mm² "insulated ferrule, 12 mm / 0.472 in"





	Item No.	Pack.-unit pcs
2-cond. diode term. blocks with diode 1 N 4007		
Circuit I, grey	**2001-1211/1000-410**	100
Circuit II, grey	**2001-1211/1000-411**	100
Examples of circuit configuration see page see 21		
Through terminal block with the same shape		
grey	**2001-1201**	
End and intermediate plate, 0.8 mm / 0.032 in thick		
orange	**2002-1292**	100 (4 x 25)
grey	**2002-1291**	100 (4 x 25)

	Item No.	Pack.-unit pcs
3-cond. diode term. blocks with diode 1 N 4007		
Circuit I, grey	**2001-1311/1000-410**	100
Circuit II, grey	**2001-1311/1000-411**	100
Examples of circuit configuration see page see 21		
Through terminal block with the same shape		
grey	**2001-1301**	
End and intermediate plate, 0.8 mm / 0.032 in thick		
orange	**2002-1392**	100 (4 x 25)
grey	**2002-1391**	100 (4 x 25)

	Item No.	Pack.-unit pcs
3-cond. LED term. blocks with red LED, DC 24 V		
Circuit I, grey	**2001-1321/1000-434**	100
Circuit II, grey	**2001-1321/1000-413**	100
Examples of circuit configuration see page see 21		
Through terminal block with the same shape		
grey	**2001-1301**	
End and intermediate plate, 0.8 mm / 0.032 in thick		
orange	**2002-1392**	100 (4 x 25)
grey	**2002-1391**	100 (4 x 25)





	Item No.	Pack.-unit pcs
4-cond. diode term. blocks with diode 1 N 4007		
Circuit I, grey	**2001-1411/1000-410**	100
Circuit II, grey	**2001-1411/1000-411**	100
Examples of circuit configuration see page see 21		
Through terminal block with the same shape		
grey	**2001-1401**	
End and intermediate plate, 0.8 mm / 0.032 in thick		
orange	**2002-1492**	100 (4 x 25)
grey	**2002-1491**	100 (4 x 25)

	Item No.	Pack.-unit pcs
4-cond. LED term. blocks with red LED, DC 24 V		
Circuit I, grey	**2001-1421/1000-434**	100
Circuit II, grey	**2001-1421/1000-413**	100
Examples of circuit configuration see page see 21		
Through terminal block with the same shape		
grey	**2001-1401**	
End and intermediate plate, 0.8 mm / 0.032 in thick		
orange	**2002-1492**	100 (4 x 25)
grey	**2002-1491**	100 (4 x 25)

TOPJOB®S
Diode Terminal Blocks 2.5 (4) mm² / AWG 12 and LED Terminal Blocks 2.5 (4) mm²; Series 2002

0.25 – 2.5 (4) mm² | AWG 22 – 12 **U_N 250 V; U_{RM} 1000 V** **1 N 4007 – 0.5 A continuous current** **Terminal block width 5,2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	**0.25 – 2.5 (4) mm² | AWG 22 – 12** **U_N 250 V; U_{RM} 1000 V** **1 N 4007 – 0.5 A continuous current** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	**0.25 – 2.5 (4) mm² | AWG 22 – 12** **DC 24 V** **I_F 0.025 A max.** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and 0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm / 0.472 in"





Item No.	Pack.-unit pcs	Item No.	Pack.-unit pcs	Item No.	Pack.-unit pcs
2-cond. diode term. blocks with diode 1 N 4007		**3-cond. diode term. blocks with diode 1 N 4007**		**3-cond. LED term. blocks with red LED, DC 24 V**	
Circuit I, grey **2002-1211/1000-410**	100	Circuit I, grey **2002-1311/1000-410**	100	Circuit I, grey **2002-1321/1000-434**	100
Circuit II, grey **2002-1211/1000-411**	100	Circuit II, grey **2002-1311/1000-411**	100	Circuit II, grey **2002-1321/1000-413**	100
Examples of circuit configuration see page see 21		Examples of circuit configuration see page see 21		Examples of circuit configuration see page see 21	
Through terminal block with the same shape		**Through terminal block with the same shape**		**Through terminal block with the same shape**	
grey **2002-1201**		grey **2002-1301**		grey **2002-1301**	
End and intermediate plate, 0.8 mm / 0.032 in thick		**End and intermediate plate,** 0.8 mm / 0.032 in thick		**End and intermediate plate,** 0.8 mm / 0.032 in thick	
orange **2002-1292**	100 (4 x 25)	orange **2002-1392**	100 (4 x 25)	orange **2002-1392**	100 (4 x 25)
grey **2002-1291**	100 (4 x 25)	grey **2002-1391**	100 (4 x 25)	grey **2002-1391**	100 (4 x 25)





Item No.	Pack.-unit pcs	Item No.	Pack.-unit pcs
4-cond. diode term. blocks with diode 1 N 4007		**4-cond. LED term. blocks with red LED, DC 24 V**	
Circuit I, grey **2002-1411/1000-410**	100	Circuit I, grey **2002-1421/1000-434**	100
Circuit II, grey **2002-1411/1000-411**	100	Circuit II, grey **2002-1421/1000-413**	100
Examples of circuit configuration see page see 21		Examples of circuit configuration see page see 21	
Through terminal block with the same shape		**Through terminal block with the same shape**	
grey **2002-1401**		grey **2002-1401**	
End and intermediate plate, 0.8 mm / 0.032 in thick		**End and intermediate plate,** 0.8 mm / 0.032 in thick	
orange **2002-1492**	100 (4 x 25)	orange **2002-1492**	100 (4 x 25)
grey **2002-1491**	100 (4 x 25)	grey **2002-1491**	100 (4 x 25)

Accessories and Examples of Circuit Configuration
Diode Terminal Blocks and LED Terminal Blocks; Series 2001/2002

Accessories Series 2001

Accessories Series 2002

	Item No.		Pack.-unit pcs
Push-in type jumper bars, light grey, insulated, I_N 18 A			
	2-way	**2001-402**	200 (8 x 25)
	3-way	**2001-403**	200 (8 x 25)
	4-way	**2001-404**	200 (8 x 25)
	5-fway	**2001-405**	100 (4 x 25)
	:	:	
	10-way	**2001-410**	100 (4 x 25)
Push-in type jumper bars, light grey, insulated, I_N 18 A			
	1 - 3	**2001-433**	200 (8 x 25)
	1 - 4	**2001-434**	200 (8 x 25)
	1 - 5	**2001-435**	100 (4 x 25)
	:	:	
	1 - 10	**2001-440**	100 (4 x 25)

	Item No.		Pack.-unit pcs
Push-in type jumper bars, light grey, insulated, I_N 25 A			
	2-way	**2002-402**	200 (8 x 25)
	3-way	**2002-403**	200 (8 x 25)
	4-way	**2002-404**	200 (8 x 25)
	5-way	**2002-405**	100 (4 x 25)
	:	:	
	10-way	**2002-410**	100 (4 x 25)
Push-in type jumper bars, light grey, insulated, I_N 25 A			
	1 - 3	**2002-433**	200 (8 x 25)
	1 - 4	**2002-434**	200 (8 x 25)
	1 - 5	**2002-435**	100 (4 x 25)
	:	:	
	1 - 10	**2002-440**	100 (4 x 25)

Examples of cuircuit configuration

2-conductor diode terminal block



Open diode gate

3-conductor diode terminal block



Polarized diode gate, common cathode

4-conductor diode terminal block



Polarized diode gate, common cathode

3-conductor LED terminal block



Voltage indication

4-conductor LED terminal block



Voltage indication

TOPJOB®S
Double Deck Diode Terminal Blocks / Double Deck LED Terminal Blocks 2.5 mm²/4 mm² / AWG 12, Series 2002

	0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12 **U_N 250 V; U_{RM} 1000 V** **1 N 4007 – 0.5 A continuous current** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	**0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12** **U_N 250 V; U_{RM} 1000 V** **1 N 4007 – 0.5 A continuous current** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and
0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm/0.472 in"



Through terminal blocks with the same shape
see page 6





Description		Item No.	Pack. unit pcs		Item No.	Pack. unit pcs
Double deck diode terminal block		**Double deck diode terminal blocks**			**Double deck diode terminal blocks**	
and		**with diode 1 N 4007**			**with 2 diodes 1 N 4007**	
double deck LED terminal block, for DIN 35 rail	Circuit I, grey	**2002-2211/1000-0410**	50	Circuit I, grey	**2002-2214/1000-0492**	50
	Circuit II, grey	**2002-2211/1000-0411**	50	Circuit II, grey	**2002-2214/1000-0491**	50

Accessories

Appropriate marking system **WMB/WMB Inline** (see also Full Line Catalog W4 Volume 1, Section 14)

	**End and**	0.8 mm / 0.032 in thick			0.8 mm / 0.032 in thick		
	intermediate plate	orange	**2002-2292**	100 (4 x 25)	orange	**2002-2292**	100 (4 x 25)
		grey	**2002-2291**	100 (4 x 25)	grey	**2002-2291**	100 (4 x 25)
	**Push-in type jumper bars,**	2-way	**2002-402**	200 (8 x 25)	2-way	**2002-402**	200 (8 x 25)
	light grey, insulated,	3-way	**2002-403**	200 (8 x 25)	3-way	**2002-403**	200 (8 x 25)
	I_N 25 A	4-way	**2002-404**	200 (8 x 25)	4-way	**2002-404**	200 (8 x 25)
		5-way	**2002-405**	100 (4 x 25)	5-way	**2002-405**	100 (4 x 25)
		:	:		:	:	
		10-way	**2002-410**	100 (4 x 25)	10-way	**2002-410**	100 (4 x 25)
	**Push-in type jumper bars,**						
	light grey, insulated,	1 - 3	**2002-433**	200 (8 x 25)	1 - 3	**2002-433**	200 (8 x 25)
	I_N 25 A	1 - 4	**2002-434**	200 (8 x 25)	1 - 4	**2002-434**	200 (8 x 25)
		1 - 5	**2002-435**	100 (4 x 25)	1 - 5	**2002-435**	100 (4 x 25)
		:	:		:	:	
		1 - 10	**2002-440**	100 (4 x 25)	1 - 10	**2002-440**	100 (4 x 25)
	**Two-way marking adapter,**						
	pivotable		**2002-121**	50 (2 x 25)		**2002-121**	50 (2 x 25)

Examples of circuit configuration



Used as recovery diodes



Used in lamp test circuit

0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12 **U_N 250 V; U_{RM} 1000 V** **1 N 4007 – 0.5 A continuous current** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	**0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12** **U_N 250 V; U_{RM} 1000 V** **1 N 4007 – 0.5 A continuous current** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	**0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12** **DC 24 V** **I_F 25 mA max.** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**













Item No.	Pack. unit pcs	Item No.	Pack. unit pcs	Item No.	Pack. unit pcs
Double deck diode terminal blocks with 2 diodes 1 N 4007		**Double deck diode terminal blocks with 2 diodes 1 N 4007**		**Double deck LED terminal blocks with red LED,** DC 24 V	
Circuit I, grey **2002-2213/1000-0487**	50	Circuit I, grey **2002-2214/1000-0489**	50	Circuit I, grey **2002-2221/1000-0434**	50
Circuit II, grey **2002-2213/1000-0488**	50	Circuit II, grey **2002-2214/1000-0490**	50	Circuit II, grey **2002-2221/1000-0413**	50
Appropriate marking system **WMB/WMB Inline** (see also Full Line Catalog W4 Volume 1 Section 14)					
0.8 mm / 0.032 in thick		0.8 mm / 0.032 in thick		0.8 mm / 0.032 in thick	
orange **2002-2292**	100 (4 x 25)	orange **2002-2292**	100 (4 x 25)	orange **2002-2292**	100 (4 x 25)
grey **2002-2291**	100 (4 x 25)	grey **2002-2291**	100 (4 x 25)	grey **2002-2291**	100 (4 x 25)
2-way **2002-402**	200 (8 x 25)	2-way **2002-402**	200 (8 x 25)	2-way **2002-402**	200 (8 x 25)
3-way **2002-403**	200 (8 x 25)	3-way **2002-403**	200 (8 x 25)	3-way **2002-403**	200 (8 x 25)
4-way **2002-404**	200 (8 x 25)	4-way **2002-404**	200 (8 x 25)	4-way **2002-404**	200 (8 x 25)
5-way **2002-405**	100 (4 x 25)	5-way **2002-405**	100 (4 x 25)	5-way **2002-405**	100 (4 x 25)
:	:	:	:	:	:
10-way **2002-410**	100 (4 x 25)	10-way **2002-410**	100 (4 x 25)	10-way **2002-410**	100 (4 x 25)
1 - 3 **2002-433**	200 (8 x 25)	1 - 3 **2002-433**	200 (8 x 25)	1 - 3 **2002-433**	200 (8 x 25)
1 - 4 **2002-434**	200 (8 x 25)	1 - 4 **2002-434**	200 (8 x 25)	1 - 4 **2002-434**	200 (8 x 25)
1 - 5 **2002-435**	100 (4 x 25)	1 - 5 **2002-435**	100 (4 x 25)	1 - 5 **2002-435**	100 (4 x 25)
:	:	:	:	:	:
1 - 10 **2002-440**	100 (4 x 25)	1 - 10 **2002-440**	100 (4 x 25)	1 - 10 **2002-440**	100 (4 x 25)
2002-121	50 (2 x 25)	**2002-121**	50 (2 x 25)	**2002-121**	50 (2 x 25)



Used in lamp test circuit



Used for collective fault indication



Used for voltage indication

TOPJOB®S
Triple Deck Diode Terminal Blocks / Triple Deck LED Terminal Blocks 2.5 mm²/4 mm² / AWG 12, Series 2002

	0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12 U_N 250 V; U_{RM} 1000 V 1 N 4007 – 0.5 A continuous current Terminal block width 5.2 mm / 0.205 in 10 – 12 mm / 0.43 in	0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12 U_N 250 V; U_{RM} 1000 V 1 N 4007 – 0.5 A continuous current Terminal block width 5.2 mm / 0.205 in 10 – 12 mm / 0.43 in



Through terminal blocks with the same shape
see page 7

❶ can be connected: 0.25 mm² – 4 mm² "s + f-st";
can be pushed in directly: 0.75 mm² – 4 mm² "s" and 0.75 mm² – 2.5 mm² "insulated ferrule, 12 mm/0.472 in"









Description		Item No.	Pack. unit pcs		Item No.	Pack. unit pcs
Triple deck diode terminal block	**Triple deck diode terminal blocks**			**Triple deck diode terminal blocks**		
and	**with diode 1 N 4007**			**with diode 1 N 4007**		
Triple deck LED terminal block, for DIN 35 rail	Circuit I, grey	**2002-3211/1000-0410**	50	Circuit I, grey	**2002-3211/1000-0675**	50
	Circuit II, grey	**2002-3211/1000-0411**	50	Circuit II, grey	**2002-3211/1000-0676**	50

Accessories

Appropriate marking system **WMB/WMB Inline** (see also Full Line Catalog W4 Volume 1, Section 14)

	**End and**	0.8 mm / 0.032 in thick			0.8 mm / 0.032 in thick		
	intermediate plate	orange	**2002-3292**	100 (4 x 25)	orange	**2002-3292**	100 (4 x 25)
		grey	**2002-3291**	100 (4 x 25)	grey	**2002-3291**	100 (4 x 25)
	**Push-in type jumper bars,**	2-way	**2002-402**	200 (8 x 25)	2-way	**2002-402**	200 (8 x 25)
	light grey, insulated,	3-way	**2002-403**	200 (8 x 25)	3-way	**2002-403**	200 (8 x 25)
	I_N 25 A	4-way	**2002-404**	200 (8 x 25)	4-way	**2002-404**	200 (8 x 25)
		5-way	**2002-405**	100 (4 x 25)	5-way	**2002-405**	100 (4 x 25)
		:	:		:	:	
		10-way	**2002-410**	100 (4 x 25)	10-way	**2002-410**	100 (4 x 25)
	**Push-in type jumper bars,**						
	light grey, insulated,	1 - 3	**2002-433**	200 (8 x 25)	1 - 3	**2002-433**	200 (8 x 25)
	I_N 25 A	1 - 4	**2002-434**	200 (8 x 25)	1 - 4	**2002-434**	200 (8 x 25)
		1 - 5	**2002-435**	100 (4 x 25)	1 - 5	**2002-435**	100 (4 x 25)
		:	:		:	:	
		1 - 10	**2002-440**	100 (4 x 25)	1 - 10	**2002-440**	100 (4 x 25)
	**Two-way marking adapter,**						
	pivotable		**2002-131**	50 (2 x 25)		**2002-131**	50 (2 x 25)

0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12 **U_N 250 V; U_{RM} 1000 V** **1 N 4007 – 0.5 A continuous current** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	**0.25 – 2.5 (4) mm² ❶ | AWG 22 – 12** **DC 24 V** **I_F 25 mA max.** **Terminal block width 5.2 mm / 0.205 in** **10 – 12 mm / 0.43 in**	









	Item No.	Pack. unit pcs		Item No.	Pack. unit pcs	
Triple deck diode terminal blocks			**Triple deck LED terminal blocks**			
with 3 diodes 1 N 4007			**with red LED,** DC 24 V			
Circuit I, grey	**2002-3212/1000-0673**	50	Circuit I, grey	**2002-3221/1000-0434**	50	
Circuit II, grey	**2002-3212/1000-0674**	50	Circuit II, grey	**2002-3221/1000-0413**	50	
Appropriate marking system **WMB/WMB Inline** (see also Full Line Catalog W4 Volume 1 Section 14)						
0.8 mm / 0.032 in thick			0.8 mm / 0.032 in thick			
orange	**2002-3292**	100 (4 x 25)	orange	**2002-3292**	100 (4 x 25)	
grey	**2002-3291**	100 (4 x 25)	grey	**2002-3291**	100 (4 x 25)	
2-way	**2002-402**	200 (8 x 25)	2-way	**2002-402**	200 (8 x 25)	
3-way	**2002-403**	200 (8 x 25)	3-way	**2002-403**	200 (8 x 25)	
4-way	**2002-404**	200 (8 x 25)	4-way	**2002-404**	200 (8 x 25)	
5-way	**2002-405**	100 (4 x 25)	5-way	**2002-405**	100 (4 x 25)	
:	:		:	:		
10-way	**2002-410**	100 (4 x 25)	10-way	**2002-410**	100 (4 x 25)	
1 - 3	**2002-433**	200 (8 x 25)	1 - 3	**2002-433**	200 (8 x 25)	
1 - 4	**2002-434**	200 (8 x 25)	1 - 4	**2002-434**	200 (8 x 25)	
1 - 5	**2002-435**	100 (4 x 25)	1 - 5	**2002-435**	100 (4 x 25)	
:	:		:	:		
1 - 10	**2002-440**	100 (4 x 25)	1 - 10	**2002-440**	100 (4 x 25)	
	2002-131	50 (2 x 25)		**2002-131**	50 (2 x 25)	

Push-in Type Wire Jumpers and Star Point Jumpers

Wire jumpers		Star point jumpers	
Nominal voltage:	**800 V/8 kV/3**	**Nominal voltage:**	**800 V/8 kV/3**
Nominal current:	**16 A**	**Nominal current:**	**$I_N \triangleq I_N$ Terminal block of the relevant series**
Nominal cross section:	**1.5 mm²/AWG 16**		
Conductor lengths:	**60/110/250 mm 2.36/4.33/9.84 in**		

	Item No.	Pack.-unit pcs
Push-in type wire jumpers,		
insulated, conductor cross section 1.5 mm²/AWG 16,		
suitable for rail-mounted terminal blocks		
series 2001 and 2002		
Wire length		
60 mm / 2.36 in	**2009-412**	10
110 mm / 4.33 in	**2009-414**	10
250 mm / 9.84 in	**2009-416**	10

	Item No.	Pack.-unit pcs
Star Point Jumpers,		
light grey, insulated		
suitable for series		
2002	**2002-0405/0011-000**	
2004	**2004-0405/0011-000**	
2006	**2006-0405/0011-000**	
2010	**2010-0405/0011-000**	
2016	**2016-0405/0011-000**	

Applications notes



Push down the wire jumper until fully inserted.
Lift the jumper with a screwdriver for rewiring.



This jumper has been specially developed to create a "star point" and is used on motor terminal boards equipped with TOPJOB® S rail-mounted terminal blocks.

Finger Guard Cover

Finger guard cover
for TOPJOB® S rail-mounted terminal blocks

	Item No.	Pack.-unit pcs
Finger guard cover,		
serves as touchproof protection		
for unused clamping units		
for TOPJOB® S rail-mounted terminal blocks series		
2010	**2010-100**	100 (4 x 25)
2016	**2016-100**	100 (4 x 25)

Insert finger guard cover into unused clamping unit

Pivotable Group marker carrier

WAGO pivotable group marker carrier
– for TOPJOB® S rail-mounted terminal blocks
– for rail-mounted terminal blocks from 5 mm / 0.197 in on and in spacer housings



* from upper edge of terminal block

	Item No.	Pack.-unit pcs
Pivotable group marker carrier		
	249-105	50
Marker card, 4 x 30 pcs per sheet		
	209-183	1 sheet
Protection cover, transparent		
	209-184	50



This pivotable group marker carrier has been developed for group marking of rail-mounted terminal blocks and brings together many requirements of our customers.

- Can be used in all multiprofile marker receptacles for rail-mounted terminal bocks from 5 mm width on or in spacer housings as shown in the picture
- Pivotable in 7 different stable positions, providing the best visual angle in case of difficult mounting conditions
- Two levels for different marking systems

  Level a:
  for marker card (4 x 34) mm (see picture)

  Level b:
  for 12 WCB-Combi markers
  (see left column)

Group Marker Carriers Series 2009

TOPJOB® S group marker carriers,

Module width 5 mm / 0.197 in
Module width 10 mm / 0.394 in
Module width 15 mm / 0.591 in

for marker cards and self-adhesive marker cards

	Item No.	Pack.-unit pcs
TOPJOB® S group marker carriers,		
snap-on type for jumper slot		
5 mm/0.197 in wide	**2009-191**	50
10 mm/0.394 in wide	**2009-192**	50
15 mm/0.591 in wide	**2009-193**	50
WAGO Multi marking system WMB,		
miniature WSB Quick marking system,		
marker strips, 11 mm / 0.433 in wide		
for marker cards and self-adhesive marker cards		
	2009-196	50

(see also Full Line Catalog W4 Volume 1, Section 14)



TOPJOB® S group marker carrier (equipped with WMB Multi marking system). Suitable for all TOPJOB® S rail-mounted terminal blocks from Series 2001 to 2016

WAGO Marking System WMB Inline Series 2009



Marking

WMB or miniature WSB markers can be used in three positions of the TOPJOB®S products. Moreover, a full length marking strip can be used in the top position of a terminal block. The terminal blocks from 1.5 mm²/AWG 16 to 6 mm²/AWG 10 as well as 10 mm²/AWG 8 and 16 mm²/AWG 6 are at the same height which allows quick marking even of terminal blocks of different sizes. The WAGO "smart Designer" software and a thermal transfer printer generate the marking.

WMB – Inline

- Markers "from the roll" save time and money
- A thermal transfer printer and the WAGO "smart Designer" software generate the marking
- Markers fit 5 mm / 0.197 in and 5.2 mm / 0.205 in wide terminal blocks and can hence be used for all 2.5 mm² WAGO rail-mounted terminal blocks
- Can be separated easily
- When separated they can also be fitted on all wider WAGO rail-mounted terminal blocks

WMB Inline, pitch 5 mm / 0.197 in,
for 5 mm / 0.197 in and 5.2 mm / 0.205 in,
on roll, 10 m

white	**2009-115**	1 roll
1500 markers / roll		

Connecting conductors up to 95 mm²/AWG 4/0 with a turn of the hand

The 285 Series of rail-mounted terminal blocks are suitable for applications with rated currents up to 232 A. Based on a unique patented technology, the largest version,

285-195, rated for **25-95 mm²/AWG 4 to AWG 4/0** has been holding its ground in the market for many years.

Now, two additional terminal blocks for wire sizes down to 6 mm² (AWG 8) have been added to the range:

285–135, 6–35 mm²/AWG 8 to AWG 2

285–150, 10–50 mm²/AWG 8 to 2/0 (70 mm² "f-st").

Operation of these new terminals is essentially the same as the 95 mm² terminal block. **The 35 mm² terminal block has the following differences.**

In addition to the WMB marking system, custom marking strips can also be used.



Testing using plug adapters for Ø 4 mm plugs.

Commoning adjacent terminal blocks using centrally positioned adjacent jumper.

Move the marking strip laterally to remove the jumper.

Counter-clockwise rotation using a screwdriver 5.5 mm/ 0.217 in. Hold clamp in open position using the latch.

Introduce stripped wire into the clamping unit up to the stop and hold it in position . . .

. . . A small counter-clockwise rotation releases the latch ❶. Once the screwdriver ❷ has been removed the conductor is safely clamped.



The voltage tap is inserted into the jumper contact slot. It can be fitted with a strain relief plate and provides test option for Ø 2 mm test sockets.

Side entry wiring means that even larger cables, which are flexible to a limited degree, can be connected without a problem.

High Current Through/Ground (Earth) Conductor Terminal Blocks 35 mm²/AWG 2, Series 285, Side-entry

6 – 35 mm² **1000 V/8 kV/3 ❶** **I_N 125 A** **AWG 8 – 2** **600 V, 115 A** **600 V** **Terminal block width 16 mm / 0.63 in** **25 – 26 mm / 0.98 in**	**6 – 35 mm²** **AWG 8 – 2** **Terminal block width 16 mm / 0.63 in** **25 – 26 mm / 0.98 in**	**0.2 – 6 mm²** **800 V/8 kV/3** **I_N 32 A** **AWG 24 – 10** **Terminal block width 8 mm / 0.315 in** **12 – 13 mm / 0.49 in**





	Item No.	Pack. unit pcs
2-conductor through terminal blocks		
grey	**285-135**	15
blue	**285-134**	15
To be used **exclusively** on DIN 35 x 15; 2.3 mm / 0.091 in thick		

	Item No.	Pack. unit pcs
2-conductor ground (earth) terminal blocks		
green-yellow	**285-137**	15
To be used **exclusively** on DIN 35 x 15; 2.3 mm / 0.091 in thick, Cu		

	Item No.	Pack. unit pcs
Voltage tap,		
grey	**285-427**	5

Accessories

Appropriate marking system **WMB/Marker strips** (see W4 Volume 1, Section 14)

Adjacent jumper, insulated,

I_N 100 A for 1 jumper
I_N 85 A for 2 to 4 jumpers
grey **285-435** 50 (2 x 25)

Screwdriver with partially insulated shaft,

type 3, blade 5.5 x 0.8 mm / 0.217 in x 0.031 in
210-621 1

Protective warning marker,

with high voltage symbol, black
yellow **285-420** 50 (2 x 25)

Finger guard cover, serves as touchproof protection for unused clamping units

yellow **285-421** 25

Test plug adapter, 11.6 mm / 4.57 in wide, for test plug 4 mm / 0.157 in Ø
283-404 25

Test plug, Ø 4 mm / 0.157 in, protected against accidental contact, not offered by WAGO
e. g. Fa. Multi-Contact Deutschland GmbH
Postfach 16 06 · 79551 Weil am Rhein
Hegenheimerstraße 19 · 79576 Weil am Rhein

Adjacent jumper, insulated,

I_N 100 A for 1 jumper
I_N A for 2 to 4 jumpers
grey **285-435** 50 (2 x 25)

crewdriver with partially insulated shaft,

type 3, blade 5.5 x 0.8 mm / 0.217 in x 0.031 in
210-621 1

Protective warning marker,

with high voltage symbol, black
yellow **285-420** 50 (2 x 25)

Finger guard cover, serves as touchproof protection for unused clamping units

yellow **285-421** 25

Test plug adapter, 11.6 mm / 4.57 in wide, for test plug 4 mm / 0.157 in Ø
283-404 25

Test plug, Ø 4 mm / 0.157 in, protected against accidental contact, not offered by WAGO
e. g. Fa. Multi-Contact Deutschland GmbH
Postfach 16 06 · 79551 Weil am Rhein
Hegenheimerstraße 19 · 79576 Weil am Rhein

Appropriate marking system **WMB**

Strain relief plate, snap-on type for voltage tap

grey **769-410** 100 (4 x 25)

Test plug, with cable 500 mm / 17.7"

2 mm Ø, red **210-136** 50 (5 x 10)

❶ 1000 V = rated voltage
8 kV = rated surge voltage
3 = pollution degree
(see also Full Line Catalog W4 Volume 1, Section 15)

2 High Current Through/Ground (Earth) Conductor Terminal Blocks 50 (70 "f-st") mm²/AWG 2/0; Series 285, Side-entry

POWER CAGE CLAMP®

10 – 50 (70 "f-st") mm² | AWG 8 – 2/0 1000 V/8 kV/3 ❶ I_N 150 A | 600 V 600 V	10 – 50 (70 "f-st") mm² | AWG 8 – 2/0	2 x 0,2 – 6 mm² | AWG 24 – 10 1000 V/8 kV/3 I_N 41 A
Terminal block width 20 mm / 0.78 in 30 mm / 1.18 in	Terminal block width 20 mm / 0.78 in 30 mm / 1.18 in	Module width 16 mm / 0.63 in 12 – 13 mm / 0.49 in





	Item No.	Pack. unit pcs
2-conductor through terminal blocks		
grey	**285-150**	5
blue	**285-154**	5
To be used **exclusively** on DIN 35 x 15; 2.3 mm / 0.091 in thick		

	Item No.	Pack. unit pcs
2-conductor ground (earth) terminal blocks		
green-yellow	**285-157**	5
To be used **exclusively** on DIN 35 x 15; 2.3 mm / 0.091 in thick, Cu		

	Item No.	Pack. unit pcs
Voltage tap,		
grey	**285-447**	5

Accessories

Appropriate marking system **WMB** (see Full Line Catalog W4 Volume 1, Section 14)

	Item No.	Pack. unit pcs
Adjacent jumper, insulated, I_N 150 A		
grey	**285-450**	25
Hex wrench with partially insulated shaft		
	285-172	1
Protective warning marker, with high voltage symbol, black		
yellow	**285-420**	50 (2 x 25)
Finger guard cover, serves as touchproof protection for unused clamping units		
yellow	**285-421**	25
Test plug, Ø 4 mm / 0.157 in, protected against accidental contact, not offered by WAGO		
e. g. Fa. Multi-Contact Deutschland GmbH Postfach 16 06 · 79551 Weil am Rhein Hegenheimerstraße 19 · 79576 Weil am Rhein		

	Item No.	Pack. unit pcs
Adjacent jumper, insulated, I_N 150 A		
grey	**285-450**	25
Hex wrench with partially insulated shaft		
	285-172	1
Protective warning marker, with high voltage symbol, black		
yellow	**285-420**	50 (2 x 25)
Finger guard cover, serves as touchproof protection for unused clamping units		
yellow	**285-421**	25
Test plug, Ø 4 mm / 0.157 in, protected against accidental contact, not offered by WAGO		
e. g. Fa. Multi-Contact Deutschland GmbH Postfach 16 06 · 79551 Weil am Rhein Hegenheimerstraße 19 · 79576 Weil am Rhein		

Appropriate marking system **WMB**

❶ 1000 V = rated voltage
8 kV = rated surge voltage
3 = pollution degree
(see also Full Line Catalog W4 Volume 1, Section 15)

Collective Carrier for Standard and Special Jumpers, Series 282

Collective carrier for standard and special jumpers in longitudinal disconnect and transverse switch terminal blocks, Series 282, can be snapped onto DIN 35 rail
Width 15.8 mm / 0.62 in
(≙ 2 x pitch 8 mm)

Storage

Safe storage for jumpers that are only needed temporarily in longitudinal disconnect and transverse switch terminal blocks.

Jumpers are used as a "switch" for the transformer short circuit, for example with the longitudinal disconnect terminal blocks. Pre-locking positions in the terminal blocks hold the jumpers captive during normal operation. For users who prefer to store the jumpers outside the terminal block, the collective carrier is an ideal solution.



	Item No.	Pack. unit pcs
Collective carrier for jumpers		
	282-369	25
Suitable for jumpers for		
transverse switch t. bl.	282-811 and	
longitudinal disc. t. bl.	282-821	

Appropriate for the following jumpers:

Jumpers, orange, I_N 30 A			
	2-way	**282-432**	50 (5 x 10)
	3-way	**282-433**	50 (5 x 10)
	4-way	**282-434**	50 (5 x 10)
	5-way	**282-435**	50 (5 x 10)
	6-way	**282-436**	50 (5 x 10)
	7-way	**282-437**	50 (5 x 10)
	8-way	**282-438**	50 (5 x 10)
	9-way	**282-439**	50 (5 x 10)
	10-way	**282-440**	50 (5 x 10)
Jumpers, special version, orange, I_N 30 A			
3-way (1-3-5)		**282-435/011-000**	50 (5 x 10)
4-way (1-3-5-7)		**282-437/011-000**	50 (5 x 10)

The collective carrier can be snapped onto DIN 35 rails. It serves as a depository for jumpers, e.g. during maintenance work.



Insertion of a jumper

Transformer test circuits and complex wiring tasks...

...are no problem and only require minimum space.

Customised jumpers are available on request

Application areas:
– Power supply
– Transformer test circuits

X-COM® SYSTEM
2-Conductor/1-Pin Receptacle Terminal Blocks

	0.08 – 4 mm² | AWG 28 – 12 500 V/6 kV/3 ❶ | 300 V, 20 A I_N 32 A* | 300 V, 20 A Terminal block width 5 mm / 0.197 in 8 – 9 mm / 0.33 in *	0.08 – 4 mm² | AWG 28 – 12 Terminal block width 5 mm / 0.197 in 8 – 9 mm / 0.33 in *

❶ 500 V = rated voltage
6 kV = rated surge voltage
3 = pollution degree
(see also Full Line Catalog W4 Volume 1, Section 15)
❷ See application notes in our Full Line Catalog W4 Volume 1, pages 2.43 – 2.45





Description		Item No.	Pack. unit pcs		Item No.	Pack. unit pcs
2-conductor/1-pin receptacle terminal block,		**2-conductor/1-pin receptacle terminal block**			**2-conductor/1-pin ground (earth) receptacle**	
suitable for DIN 35 rail acc. to EN 50 022		grey	**769-251**	50	**terminal block**	
					green-yellow	**769-257**	50

Accessories

appropriate marking system **Mini-WSB** (see also Full Line Catalog W4 Volume 1, Section 14)

	**End and**		1.1 mm / 0.043 in thick			1.1 mm / 0.043 in thick	
	intermediate plate		grey	**769-320**	100 (4 x 25)	grey	**769-320**	100 (4 x 25)
			orange	**769-321**	100 (4 x 25)	orange	**769-321**	100 (4 x 25)
	**Screwless**							
	end stop		6 mm / 0.236 in wide	**249-116**	100 (4 x 25)	6 mm / 0.236 in wide	**249-116**	100 (4 x 25)
			10 mm / 0.394 in wide	**249-117**	50 (2 x 25)	10 mm / 0.394 in wide	**249-117**	50 (2 x 25)
	**Insulation stop ❷,**	white	0.08 – 0.2 mm²	**769-470**	200 strips	0.08 – 0.2 mm²	**769-470**	200 strips
	5 pcs/strip	light grey	0.25 – 0.5 mm²	**769-471**	200 strips	0.25 – 0.5 mm²	**769-471**	200 strips
		dark grey	0.75 – 1 mm²	**769-472**	200 strips	0.75 – 1 mm²	**769-472**	200 strips
	**Adjacent jumper,**	I_N 24 A	grey	**280-402**	200 (8 x 25)	yellow-green	**280-422**	200 (8 x 25)
	insulated							
	Alternate jumper		grey	**280-409**	100 (4 x 25)	grey	**280-409**	100 (4 x 25)
	**Staggered jumper ❷,**	from 1 to 2	I_N 24 A	**780-452**	100 (4 x 25)	I_N 24 A	**780-452**	100 (4 x 25)
	insulated,	from 1 to 3		**780-453**	100 (4 x 25)		**780-453**	100 (4 x 25)
	width 5 mm / 0.197 in	from 1 to 4		**780-454**	100 (4 x 25)		**780-454**	100 (4 x 25)
		from 1 to 5		**780-455**	50 (2 x 25)		**780-455**	50 (2 x 25)
		:		:			:	
		from 1 to 8		**780-458**	50 (2 x 25)		**780-458**	50 (2 x 25)
	**Push-in type wire jumper ❷,**		L = 60 mm / 2.362 in	**249-125**	10	L = 60 mm / 2.362 in	**249-125**	10
	insulated, 9 A – conductor		L = 110 mm / 4.331 in	**249-126**	10	L = 110 mm / 4.331 in	**249-126**	10
	cross section 0.75 mm²/AWG 18		L = 250 mm / 9.843 in	**249-127**	10	L = 250 mm / 9.843 in	**249-127**	10
	**Coding pin,**							
	for coding of female plugs		orange	**769-435**	100 (4 x 25)	orange	**769-435**	100 (4 x 25)
	**Protective warning marker,**							
	for 5 terminal blocks,		yellow	**280-415**	100 (4 x 25)			
	fits into screwdriver slot							
	**Test plug,** w. cable 500 mm/17.7"							
	2 mm/0.079 in Ø		red	**210-136**	50 (5 x 10)	red	**210-136**	50 (5 x 10)
	2.3 mm/0.091 in Ø		yellow	**210-137**	50 (5 x 10)	yellow	**210-137**	50 (5 x 10)
	**Test plug module,**		Item numbers and application notes see			Item numbers and application notes see		
	for test using jumper position in		Full Line Catalog W4 Volume, pages 2.38 – 2.40			Full Line Catalog W4 Volume 1, pages 2.38 – 2.40		
	current bar or cond. wire opening							
	**Test plug adapter**		5 mm / 0.197 in wide			5 mm / 0.197 in wide		
				280-404	100 (4 x 25)		**280-404**	100 (4 x 25)
			for test plug 210-137 (Ø 2.3 mm)			for test plug 210-137 (Ø 2.3 mm)		
	**1-conductor female plug,**							
	straight or angled		see Full Line Catalog W4 Volume 1, pages 9.44/9.46			see Full Line Catalog W4 Volume 1, pages 9.44/9.46		
	**2-conductor female plug**							
			see Full Line Catalog W4 Volume 1, page 9.45			see Full Line Catalog W4 Volume 1, page 9.45		

* Further approvals with corresponding ratings can be found at www.wago.com

Types of Assembly
2-Conductor/1-pin Receptacle Terminal Blocks and 1-/2-Conductor Female Plugs



1-conductor female plug straight and angled
Commoning possibility of receptacle terminal blocks with jumper contact systems, series 280 and 780, and testing possibility with test plug adapter 280-4..

2-conductor female plug
Commoning possibility of receptacle terminal blocks only with adjacent jumpers and alternate jumpers, series 280



Ground (earth) receptacle terminal block



Receptacle terminal block



Operating lever, loose,
for female plugs and male connectors
with CAGE CLAMP® connection
Item number: **769-434**



Wire connection using operating lever

X-COM® SYSTEM
1-Conductor/1-Conductor
Disconnect Receptacle Terminal Blocks with 2 Jumper Positions

0.08 – 4 mm² | **AWG 28 – 12**
400 V/6 kV/3 ❶ | **300 V, 10 A**
I_N 32 A

Terminal block width 5 mm / 0.197 in
8 – 9 mm / 0.33 in



❶ 500 V = rated voltage
6 kV = rated surge voltage
3 = pollution degree
(see also Full Line Catalog W4 Volume 1, Section 15)
❷ See application notes in our Full Line Catalog W4 Volume 1, pages 2.43 – 2.45

Description			Item No.	Pack. unit pcs
1-conductor/1-conductor disconnect receptacle terminal block without/with shield (screen) contact and 2 jumper positions, suitable for DIN 35 rail acc. to EN 60715		**1-cond./1-cond. disconnect receptacle term. block** grey	**769-242**	50
		1-cond./1-cond. disconnect receptacle term. block with shield (screen) contact (no picture) grey	**769-243**	50
Accessories appropriate marking system **Mini-WSB** (see also Full Line Catalog W4 Volume 1, Section 14)				
	**End and intermediate plate**	1.1 mm / 0.043 in thick grey	**769-317**	100 (4 x 25)
		orange	**769-318**	100 (4 x 25)
	**Separator plate,** oversized	1.1 mm / 0.043 in thick orange	**769-319**	100 (4 x 25)
	**Screwless end stop**	6 mm / 0.236 in wide	**249-116**	100 (4 x 25)
		10 mm / 0.394 in wide	**249-117**	50 (2 x 25)
	**Insulation stop ❷,** 5 pcs/strip white	0.08 – 0.2 mm²	**769-470**	200 strips
	light grey	0.25 – 0.5 mm²	**769-471**	200 strips
	dark grey	0.75 – 1 mm²	**769-472**	200 strips
	**Adjacent jumper,** I_N 24 A insulated	grey	**280-402**	200 (8 x 25)
	Alternate jumper	grey	**280-409**	100 (4 x 25)
	**Staggered jumper ❷,** from 1 to 2 insulated,	I_N 24 A	**780-452**	100 (4 x 25)
	from 1 to 3		**780-453**	100 (4 x 25)
width 5 mm / 0.197 in	from 1 to 4		**780-454**	100 (4 x 25)
	from 1 to 5		**780-455**	50 (2 x 25)
	:		:	
	from 1 to 8		**780-458**	50 (2 x 25)
	**Push-in type wire jumper ❷,** insulated, 9 A – conductor cross section 0.75 mm²/AWG 18	L = 60 mm / 2.362 in	**249-125**	10
		L = 110 mm / 4.331 in	**249-126**	10
		L = 250 mm / 9.843 in	**249-127**	10
	**Protective warning marker,** for 5 terminal blocks fits into screwdriver slot,	yellow	**280-415**	100 (4 x 25)
	**Test plug,** w. cable 500 mm/1'7.7" Ø 2 mm / 0.079 in	red	**210-136**	50 (5 x 10)
	Ø 2.3 mm / 0.091 in	yellow	**210-137**	50 (5 x 10)





X-COM®-SYSTEM
2-Conductor/2-Pin Double Deck Receptacle Terminal Blocks
Series 870

	500 V/6 kV/3 ❶ **I_N 16 A** **Terminal block width 5 mm / 0.197 in**	**Terminal block width 5 mm / 0.197 in**

❶ 500 V = rated voltage
6 kV = rated surge voltage
3 = pollution degree
(see also Full Line Catalog W4 Volume 1, Section 15)





Description		Item No.	Pack. unit pcs		Item No.	Pack. unit pcs
2-pin/2-pin double deck receptacle terminal block, suitable for DIN 35 rail	**Through/through terminal blocks,** housing color grey					
	L / L	**870-151**	50			
4-pin double deck receptacle terminal block, suitable for DIN 35 rail				**4-pin ground (earth) conductor terminal block,** internal commoning, housing color green-yellow		
				PE	**870-157**	50

Accessories

appropriate marking system **WMB/Mini-WSB** (see also Full Line Catalog W4 Volume 1, Section 14)

	**End and intermediate plate**	1 mm / 0.039 in thick			1 mm / 0.039 in thick		
		grey	**870-168**	100 (4 x 25)	grey	**870-168**	100 (4 x 25)
		orange	**870-169**	100 (4 x 25)	orange	**870-169**	100 (4 x 25)
	**Push-in type jumper bars,** light grey, insulated, I_N 18 A	2-way	**870-402**	200 (8 x 25)	2-way	**870-402**	200 (8 x 25)
		3-way	**870-403**	200 (8 x 25)	3-way	**870-403**	200 (8 x 25)
		4-way	**870-404**	200 (8 x 25)	4-way	**870-404**	200 (8 x 25)
		5-way	**870-405**	100 (4 x 25)	5-way	**870-405**	100 (4 x 25)
		:	:		:	:	
		10-way	**870-410**	100 (4 x 25)	10-way	**870-410**	100 (4 x 25)
	**Push-in type jumper bars,** light grey, insulated, I_N 18 A						
		from 1 to 3	**870-433**	200 (8 x 25)	from 1 to 3	**870-433**	200 (8 x 25)
		from 1 to 4	**870-434**	200 (8 x 25)	from 1 to 4	**870-434**	200 (8 x 25)
		from 1 to 5	**870-435**	100 (4 x 25)	from 1 to 5	**870-435**	100 (4 x 25)
		:	:		:	:	
		from 1 to 10	**870-440**	100 (4 x 25)	from 1 to 10	**870-440**	100 (4 x 25)
	**Miniature WSB quick marking card,** 10 strips with 10 markers each, white with black printing	see Full Line Catalog W4 Volume 1, Section 14			see Full Line Catalog W4 Volume 1, Section 14		
	**1-connector female plug,** straight	see Full Line Catalog W4 Volume 1, Section 9			see Full Line Catalog W4 Volume 1, Section 9		
	**1-connector female plug,** angled	see Full Line Catalog W4 Volume 1, Section 9			see Full Line Catalog W4 Volume 1, Section 9		

X-COM®-SYSTEM
Blue Components

0.08 – 4 mm² / 500 V/6 kV/3 ❶ / I_N 32 A**	AWG 28 – 12 / 300/600 V, 10/5 A / 300 V, 10 A	0.08 – 4 mm² / 500 V/6 kV/3 ❶ / I_N 32 A**	AWG 28 – 12	0.08 – 4 mm² / 500 V/6 kV/3 ❶ / I_N 32 A**	AWG 28 – 12
Module width 5 mm / 0.197 in 8 – 9 mm / 0.33 in		Module width 5 mm / 0.197 in 8 – 9 mm / 0.33 in		Terminal block width 5 mm / 0.197 in 8 – 9 mm / 0.33 in	

*

No. of poles	Item No.	Pack. unit pcs
1-conductor female plugs, with coding fingers, blue, commoning possibility with miniature adjacent jumpers		
1 pole	**769-101/000-006**	200
2 poles	**769-102/000-006**	100
3 poles	**769-103/000-006**	50
4 poles	**769-104/000-006**	50
5 poles	**769-105/000-006**	50
6 poles	**769-106/000-006**	50
7 poles	**769-107/000-006**	50
8 poles	**769-108/000-006**	50
9 poles	**769-109/000-006**	50
10 poles	**769-110/000-006**	50
11 poles	**769-111/000-006**	50
12 poles	**769-112/000-006**	50
13 poles	**769-113/000-006**	50
14 poles	**769-114/000-006**	50
15 poles	**769-115/000-006**	50

❶ 500 V = rated voltage
6 kV = rated surge voltage
3 = pollution degree

No. of poles	Item No.	Pack. unit pcs
1-conductor female plug, with coding fingers, grey, blue, green-yellow, commoning possibility with miniature adjacent jumpers		
3 poles	**769-103/000-038**	50
1-conductor female plug, with coding fingers, green-yellow, blue, grey commoning possibility with miniature adjacent jumpers		
3 poles	**769-103/000-039**	50

No. of poles	Item No.	Pack. unit pcs
1-conductor female plug, with coding fingers, grey, blue, green-yellow, commoning possibility with miniature adjacent jumpers		
5 poles	**769-105/000-038**	50
1-conductor female plug, with coding fingers, green-yellow, blue, grey commoning possibility with miniature adjacent jumpers		
5 poles	**769-105/000-039**	50

Miniature adjacent jumper,
insulated, I_N 24 A, grey, suitable for 1-conductor female plugs

769-402 100 (4 x 25)

* Further approvals with corresponding ratings can be found at www.wago.com
** Current-carrying capacity curves and accessories see Full Line Catalog W4 Volume 1, Section 9

0.08 – 4 mm² / 500 V/6 kV/3 ❶ / I_N 32 A**	AWG 28 – 12 / 300/600 V, 10/5 A / 300 V, 10 A	0.08 – 4 mm² / 500 V/6 kV/3 ❶ / I_N 32 A**	AWG 28 – 12 / 300/600 V, 10/5 A / 300 V, 10 A	0.08 – 4 mm² / 500 V/6 kV/3 ❶ / I_N 32 A**	AWG 28 – 12 / 300/600 V, 10/5 A / 300 V, 10 A
Module width 5 mm / 0.197 in		Module width 5 mm / 0.197 in		Terminal block width 5 mm / 0.197 in	
8 – 9 mm / 0.33 in		8 – 9 mm / 0.33 in		8 – 9 mm / 0.33 in	
*		*		*	

No. of poles	Item No.	Pack. unit pcs	No. of poles	Item No.	Pack. unit pcs	No. of poles	Item No.	Pack. unit pcs
1-conductor/1-pin receptacle terminal block,			**2-conductor/1-pin receptacle terminal block,**			**2-conductor/2-pin receptacle terminal block,**		
blue			blue			blue		
suitable for DIN 35 rail acc. to EN 60715			suitable for DIN 35 rail acc. to EN 60715			suitable for DIN 35 rail acc. to EN 60715		
	769-176/000-006	100		**769-251/000-006**	50		**769-171/000-006**	50

❶ 500 V = rated voltage
6 kV = rated surge voltage
3 = pollution degree

Adjacent jumper,

unsulated, I_N 24 A, grey
280-402 200 (8 x 25)

Alternate jumper,

unsulated, I_N 24 A, grey
280-409 100 (4 x 25)

X-COM®-SYSTEM
Female Plugs for Self-Assembly

	0.08 – 4 mm² / AWG 28 – 12 500 V/6 kV/3 ❶ I_N 32 A** Module width 5 mm / 0.197 in 8 – 9 mm / 0.33 in	0.08 – 4 mm² / AWG 28 – 12 500 V/6 kV/3 ❶ I_N 32 A** Module width 5 mm / 0.197 in 8 – 9 mm / 0.33 in
		

	Color	Item No.	Pack.-unit pcs	Color	Item No.	Pack.-unit pcs
	**1-conductor base module with integrated end plate**			**2-conductor base module with integrated end plate**		
	grey	**769-501**	250	grey	**769-504**	250
	blue	**769-501/000-006**	250	blue	**769-504/000-006**	250
	green-yellow	**769-501/000-016**	250	green-yellow	**769-504/000-016**	250
	**1-conductor center module**			**2-conductor center module**		
	grey	**769-502**	250	grey	**769-505**	250
	blue	**769-502/000-006**	250	blue	**769-505/000-006**	250
	green-yellow	**769-502/000-016**	250	green-yellow	**769-505/000-016**	250
	**1-conductor end module**			**2-conductor end module**		
	grey	**769-503**	250	grey	**769-506**	250
	blue	**769-503/000-006**	250	blue	**769-506/000-006**	250
	green-yellow	**769-503/000-016**	250	green-yellow	**769-506/000-016**	250
	**Mounting tool**			**Mounting tool**		
		298-646	1		**298-641**	1

❶ 500 V = rated voltage
6 kV = rated surge voltage
3 = pollution degree

** Current-carrying capacity curves and accessories see Full Line Catalog W4 Volume 1, Section 9

0.08 – 4 mm² / AWG 28 – 12 500 V/6 kV/3 ❶ I_N 32 A** Module width 5 mm / 0.197 in 8 – 9 mm / 0.33 in		

Color	Item No.	Pack.-unit pcs
1-conductor base module, 45° angled, with integrated end plate		
grey	**769-512**	250
blue	**769-512/000-006**	250
green-yellow	**769-512/000-016**	250
1-conductor end module, 45° angled		
grey	**769-513**	250
blue	**769-513/000-006**	250
green-yellow	**769-513/000-016**	250
1-conductor end module, 45° angled		
grey	**769-515**	250
blue	**769-515/000-006**	250
green-yellow	**769-515/000-016**	250
Mounting tool		
	298-642	1

Self-assembly of individual female plugs

Using modular female plugs from the X-COM-SYSTEM, female plugs can be customized for applications requiring varying numbers of poles (e.g. when designing prototypes).

Modules and pole numbers

A self assembled female plug consists of a base module with integrated end plate, up to 13 center modules (corresponding to a 15-pole female plug = maximum number of poles) as well as an end module.

Female plugs with ground (earth) modules (green-yellow)

According to the "norm", connectors should be inserted and disengaged off load. This is why pre-mating the ground (earth) contact is required when connectors need to be connected or disengaged "under load".

This is guaranteed using a ground (earth) module in the middle of female plugs equipped with up to 7 poles or two ground (earth) modules at both ends of 8 - 15 pole female plugs to ensure a preceding ground (earth) connection.

Mounting

In order to guarantee that the individual modules are properly snapped into each other without damaging the locking latches, it is necessary to use the appropriate mounting tool.

Example of a 5-pole 1-conductor female plug

Compact Connector for Flexible Conductors Series 222

2 x 0.08 – 2.5 mm² "s+f-st" | AWG 28 – 12 4 mm² "f-st" 400 V/4 kV/2** I_N 32 A 9 – 10 mm / 0.37 in *	5 x 0.08 – 2.5 mm² "s+f-st" | AWG 28 – 12 4 mm² "f-st" 400 V/4 kV/2** I_N 32 A 9 – 10 mm / 0.37 in * ENEC	

Item No.	Pack.-unit pcs	Item No.	Pack.-unit pcs	
Compact connector,		**Compact connector,**		
2-wire connector, with levers		5-wire connector, with levers		
max. continuous service temperature 85 °C		max. continuous service temperature 85 °C		
grey **222-412**		grey **222-415**	400 (10 x 40)	





Compact connector

It clamps up to 5 stripped flexible wires of 0.08 mm²/AWG 28 to 4 mm²/AWG 12 or solid or stranded wires up to 2.5 mm²/AWG 14, without tools.

This is how it works:
Open the clamping point using one of the small orange colored levers so that the lever engages and keeps the clamping point in its open position. The wire can now be inserted, then the lever can be returned to its rest position, flush with the terminal block housing.

The safety:
The special rest position of the lever reliably prevents accidental unclamping of a connected wire. The additional application safety for any type of conductor (solid, stranded, flexible) is confirmed by approbations like ENEC or UL.
The ENEC mark is a European safety mark including 20 countries.



* You can find approvals on the Internet at www.wago.com.
** in grounded (earthed) supply systems

Mounting Carrier and Push-Wire Connectors for Junction Boxes Series 773

4 x 0.75 – 2.5 mm² "s" 4 x 1.5 – 2.5 mm² "str." 400 V/ 4 kV/ 2** I_N 24 A	4 x AWG 18 – 12 "sol." 4 x AWG 16 – 12 "str." 600 V, 20 A UL	3 x 2.5 – 6 mm² "s" 400 V/ 4 kV/ 2** I_N 41 A	AWG 14 – 10 "sol." 600 V, 30 A UL	Mounting carrier for push-wire connectors for junction boxes Series 773 Adapter width 18 mm / 0.71 in	
12 mm / 0.47 in * UL		12 – 13 mm / 0.53 in * UL			



Item No.	Pack.-unit pcs	Item No.	Pack.-unit pcs	Item No.	Pack.-unit pcs
Push-wire connector for junction boxes,		**Push-wire connectors for junction boxes,**		**Mounting carrier**	
3-wire connector, black,		3-wire connector, color of housing transparent,		orange **773-332**	50 (5 x 10)
max. continuous service temperature 150 °C		color of cover red		**Marker strips,**	
773-514	1000 (10 x 100)	**773-173**	500 (10 x 50)	plain **210-334**	1 card







For time and cost saving push-in wiring up to 6 mm² in distribution and junction boxes as well as other equipment.

As an addition to the 273 Series push wire connectors for AWG 16 to AWG 12 (1.5 – 4 mm²), the new 3-conductor push wire connector expands the range of wire sizes up to AWG 10 (6 mm²) and is suitable for both solid and fine-stranded wires.

A mounting carrier (see accessories) is suitable for applications where the connectors must be marked and fixed in position. The carrier fits up to two connectors on DIN 35 carrier rails or screw mounting on level surfaces.

Using this push wire connector, a large range of wiring applications can be realized in distribution or junction boxes, for example. To mention just a few: potential multiplication of an AWG 10 (6 mm²) conductor in a junction box, changing from or to AWG 10 (6 mm²) wire size.

Shield (Screen) Clamps, Carrier with Grounding Foot
Series 790, 791

Shield (Screen) Clamps	Carrier with grounding foot	Carrier with grounding foot
Note: **Cannot be used for the connection of ground (earth) conductors!**		

			Pack.-unit pcs		Item No.	Pack.-unit pcs		Item No.	Pack.-unit pcs
Shield (screen) clamps				**Carrier w. grounding foot,**			**Carrier w. grounding foot,**		
				for DIN 35 rail, bar parallel to the rail,			for DIN 35 rail, bar parallel to the rail,		
		Diameter of		10 mm (0.394 in) x 3 mm (0.118 in), bar a. foot –			10 mm (0.394 in) x 3 mm (0.118 in), bar a. foot –		
H_{max}	B	connectable conductor		Cu with tin plating			Cu with tin plating		
40 mm	10 mm	1.5 mm to 6.5 mm	**791-107**	15 mm long/0.59 in	**790-110**	25	45 mm long/1.772 in	**790-114**	25
47 mm	17 mm	5 mm to 11 mm	**791-111**						
				Carrier w. grounding foot,					
63 mm	23 mm	10 mm to 17 mm	**791-117**	for DIN 35 rail, bar parallel to the rail,					
				10 mm (0.394 in) x 3 mm (0.118 in), bar a. foot –					
78 mm	30 mm	16 mm to 24 mm	**791-124**	Cu with tin plating					
				25 mm long/0.98 in	**790-112**	25			

Dimensions (in mm), Application notes



Item No.	Length	suitable shield (screen) clamping saddle	
		790-	**791-**
790-110	15 mm / 0.59 in	**max. 790-108**	**–**
790-112	25 mm / 0.98 in	**max. 790-116**	**791-111, 791-117**
790-114	45 mm / 1.772 in	**790-108 to 790-140**	**791-111 to 791-124**
		see Full Line Catalog W4 Volume 1, Section 12	

Busbar Carrier	Busbar Carrier	Shield termination

Item No.	Pack.-unit pcs	Item No.	Pack.-unit pcs	Item No.	Pack.-unit pcs
Busbar Carrier		**Busbar Carrier**		**Shield termination**	
for busbars Cu 10 mm x 3 mm		for busbars Cu 10 mm x 3 mm		including cable tie	
				for shield diameter	
790-300		**790-301**		5 mm / 0.197 in to 10 mm / 0.394 in	
				55 mm / 2.17 in long **709-350**	100 (4 x 25)
				150 mm / 5.9 in long **709-352**	100 (4 x 25)

Remove the busbar carrier using a screwdriver (blade width 5.5 mm / 0.217 in)



To remove the busbar, compress the spring using pliers

Dimensions (in mm)





Wire marking

The following marker cards are available:
Marker cards for plotter marking ...

... or marker cards on roll
for thermal transfer printing

Remove the thermal transfer printed marker card from the roll …

Slide the plotted marker card into the marking sleeve receptacle. Changing the marking is also possible after the wire has been connected



Compress the sleeve and slide it onto the wire to be marked





Plotter IP 350

WAGO smart Marking software (see also Full Line Catalog W4 Volume 1, Section 14)

Thermal transfer printer TP 298

. . . Description and Handling

… and slide it through the marker receptacle up to the end of the sleeve …

… then remove the rest of the card by twisting it off

Fix the marking sleeve 211-129 using cable ties to individual wire or cable

Cable marking

Self-laminating labels are available on A4 sheets for the laser printer (plotter) …

… or are supplied on roll for the thermal transfer printer

Remove the printed label from the sheet or roll …

… and wrap it around the wire or cable

The transparent laminate protects the marking

Wire marking sleeve, halogen-free for marker card, for wires ranging from AWG 24 to 4 (0.25mm² to 16 mm²) (to be fitted before wire connection)	Wire marking sleeve, halogen-free for marker card, for wires ranging from AWG 24 to 4 (0.25mm² to 16 mm²) (to be fitted before wire connection)	

Item No.	Pack.-unit pcs	Item No.	Pack.-unit pcs	
Marking sleeve		**Marking sleeve**		
12 mm long / 0.472 in		23 mm long / 0.9 in		
for wire Ø 1.6 – 3.2 mm or AWG 24 – 16 (0.25 mm² – 1.5 mm²)		for wire Ø 1.6 – 3.2 mm or AWG 24 – 16 (0.25 mm² – 1.5 mm²)		
211-112	2000	**211-122**	2000	
for wire Ø 2.2 – 4.5 mm or AWG 20 – 12 (0.5 mm² – 4 mm²)		for wire Ø 2.2 – 4.5 mm or AWG 20 – 12 (0.5 mm² – 4 mm²)		
211-113	2000	**211-123**	2000	
for wire Ø 3.7 – 5.9 mm or AWG 14 – 10 (2.5 mm² – 6 mm²)		for wire Ø 3.7 – 5.9 mm or AWG 14 – 10 (2.5 mm² – 6 mm²)		
211-114	1000	**211-124**	1000	
for wire Ø 4.8 – 7.5 mm or AWG 10 – 4 (6 mm² – 16 mm²)		for wire Ø 4.8 – 7.5 mm or AWG 10 – 4 (6 mm² – 16 mm²)		
211-115	1000	**211-125**	1000	
Article specific accessories		**Article specific accessories**		
Marker card, for thermal transfer printer, 12 mm long / 0.472 in, white		**Marker card,** for thermal transfer printer, 23 mm long / 0.9 in, white		
211-111	1 x 3000	**211-121**	1 x 3000	
Marker card, for plotter, 12 mm long / 0.472 in, white		**Marker card,** for plotter, 23 mm long / 0.9 in, white		
211-110	18 x 57	**211-120**	30 x 34	
Plotter receptacle, for marker card		**Plotter receptacle,** for marker card		
258-370	1	**258-370**	1	

Accessories (see also Full Line Catalog W4 Volume 1, Section 14)

Thermal transfer printer, TP 298 Resolution 300 dpi		**Plotter IP 350**	
258-298	1	**258-350**	1
Thermal transfer printer, TP 297 Resolution 203 dpi		**WAGO plotter pen,** line width 0.35 mm	
258-297	1	**258-228**	1
Ink ribbon, 90 mm / 3.54 in width, 300 m roll		**WAGO disposable pen,** line width 0.35 mm	
258-150	1	**258-328**	1

Cable Marking

Cable marking sleeve, halogen-free for marker card, for wire sizes from AWG 8 (10 mm²) for cable tie (can also be fitted subsequently)	**Self-laminating labels on DIN A4 sheets or roll for cable marking.** **Cable diameter approx. 3 mm/0.118 in – 14 mm/0.55 in**	

Item No.	Pack.-unit pcs
Marking sleeve, for cable tie	
23 mm long / 0.9 in	
for wires from AWG 8 (10 mm²)	
211-129	1000

Article specific accessories

Marker card, for thermal transfer printer,	
23 mm / 0.9 in long, white	
211-121	1 x 3000
Marker card, for plotter,	
23 mm / 0.9 in long, white	
211-120	30 x 34
Plotter receptacle, for marker card	
258-370	1
Cable tie,	
(2,5 x 100) mm	
807-0090/0101-0100	25

Item No.	Pack.-unit pcs
Labels on DIN A4 sheets	
for **laser printer**	
Marker surface "S" = 9 mm x "B" = 17 mm	
"L" = 35 mm	
for max. cable Ø 8 mm / 0.315 in	
70 labels per sheet	
211-150	20
Marker surface "S" = 13 mm x "B" = 21 mm	
"L" = 56 mm	
for max. cable Ø 14 mm / 0.55 in	
32 labels per sheet	
211-151	25
Labels on roll	
for **thermal transfer printer**	
Marker surface "S" = 8 mm x "B" = 18 mm	
"L" = 35 mm	
for max. cable Ø 9 mm / 0.354 in	
9,000 labels per roll	
211-155	1
Marker surface "S" = 13 mm x "B" = 23 mm	
"L" = 51 mm	
for max. cable Ø 12 mm / 0.472 in	
5,000 labels per roll	
211-156	1

Accessories (see also Full Line Catalog W4 Volume 1, Section 14)

Thermal transfer printer, TP 298	**Plotter IP 350**
Resolution 300 dpi	**258-350** 1
258-298 1	
Thermal transfer printer, TP 297	**WAGO plotter pen,** line width 0.35 mm
Resolution 203 dpi	**258-228** 1
258-297 1	
Ink ribbon 90 mm / 3.54 in width, 300 m roll	**WAGO disposable pen,** line width 0.35 mm
258-150 1	**258-328** 1

Dimensions of self-laminating label (in mm)



Marker carriers for WCB Combi Marking System

Marker carriers for 4 WCB markers	WCB Combi marking system 20 markers with identical numbers/letters each tag	

Item No.	Pack.-unit pcs	Marking per tag	Item No.	Marking per tag	Item No.
Marker carriers for 4 WCB markers		plain	**249-200**	A (20x)	**249-211**
2009-184		1 (20x)	**249-201**	B (20x)	**249-212**
		2 (20x)	**249-202**	C (20x)	**249-213**
suitable for terminal blocks with WMB marking		3 (20x)	**249-203**	D (20x)	**249-214**
receptacle		4 (20x)	**249-204**	E (20x)	**249-215**
		5 (20x)	**249-205**	F (20x)	**249-216**
		6 (20x)	**249-206**	G (20x)	**249-217**
		7 (20x)	**249-207**	H (20x)	**249-218**
		8 (20x)	**249-208**	I (20x)	**249-219**
		9 (20x)	**249-209**	J (20x)	**249-220**
		0 (20x)	**249-210**	K (20x)	**249-221**
				L (20x)	**249-222**
		1 . . . 0 (2x)	**249-239**	M (20x)	**249-223**
				N (20x)	**249-224**
		1. (20x)	**249-241**	O (20x)	**249-225**
		2. (20x)	**249-242**	P (20x)	**249-226**
		3. (20x)	**249-243**	Q (20x)	**249-227**
		4. (20x)	**249-244**	R (20x)	**249-228**
		5. (20x)	**249-245**	S (20x)	**249-229**
		6. (20x)	**249-246**	T (20x)	**249-230**
		7. (20x)	**249-247**	U (20x)	**249-231**
		8. (20x)	**249-248**	V (20x)	**249-232**
		9. (20x)	**249-249**	W (20x)	**249-233**
		0. (20x)	**249-250**	X (20x)	**249-234**
				Y (20x)	**249-235**
		+ (20x)	**249-237**	Z (20x)	**249-236**
		– (20x)	**249-238**		
		Pieces per packing unit: 10 tags			

Insert WCB Combi marker into marker carrier

Twist the marker carrier off the carrier holder . . .

. . . and insert the marker carrier into the WMB marking receptacle of the terminal block

Contents
Volume 2

PCB Terminal Strips for THR Soldering
Terminal Strips with Locking Slide 0.5 mm²/AWG 20
Pin spacings 2.5 mm and 2.54 mm; Series 218

Pin spacing 2.5 mm / 0.098 in	Pin spacing 2.54 mm / 0.1 in	Terminal strips in tape on reel
0.08 – 0.5 mm² ❶ | AWG 28 – 20 ❶	0.08 – 0.5 mm² ❶ | AWG 28 – 20 ❶	Pin pacing 2.5 mm
160 V/2.5 kV/2 | 150 V, 4 A	160 V/2.5 kV/2 | 150 V, 4 A	Pin pacing 2.54 mm
I_N 6 A | 150 V, 4 A	I_N 6 A | 150 V, 4 A	
5 – 6 mm / 0.22 in	5 – 6 mm / 0.22 in	
*	*	

No. of poles	Item No.	Pack. unit pcs
1-conductor terminal strips with locking slide,		
2 solder pins/pole in line, black,		
locking slide, white		
2	**218-102/000-604**	1000 (10 x 100)
3	**218-103/000-604**	1000 (10 x 100)
4	**218-104/000-604**	500 (5 x 100)
5	**218-105/000-604**	500 (5 x 100)
6	**218-106/000-604**	280 (4 x 70)
7	**218-107/000-604**	240 (4 x 60)
Other numbers of poles and pin spacings on request		

No. of poles	Item No.	Pack. unit pcs
1-conductor terminal strips with locking slide,		
2 solder pins/pole in line, black,		
locking slide, white		
2	**218-502/000-604**	1000 (10 x 100)
3	**218-503/000-604**	1000 (10 x 100)
4	**218-504/000-604**	500 (5 x 100)
5	**218-505/000-604**	500 (5 x 100)
6	**218-506/000-604**	280 (4 x 70)
7	**218-507/000-604**	240 (4 x 60)
Other numbers of poles and pin spacings on request		

No. of poles	Item No.	Width of reel (W)
1-conductor terminal strips with locking slide,		
2 solder pins/pole in line, black,		
locking slide, white		
Terminal strips with additional suction pad in a tape on reel according to IEC 60286-3,		
Reel diameter 330 mm / 13 in		
Pin spacing 2.5 mm / 0.098 in	Pack. unit 250 pcs	(mm)
2	**218-102/000-604/997-403**	16
3	**218-103/000-604/997-405**	32
4	**218-104/000-604/997-405**	32
5	**218-105/000-604/997-405**	32
6	**218-106/000-604/997-405**	32
7	**218-107/000-604/997-405**	32
Pin spacing 2.54 mm / 0.1 in	Pack. unit 250 pcs	(mm)
2	**218-502/000-604/997-403**	16
3	**218-503/000-604/997-405**	32
4	**218-504/000-604/997-405**	32
5	**218-505/000-604/997-405**	32
6	**218-506/000-604/997-405**	32
7	**218-507/000-604/997-405**	32

Accessories

Test pin, Ø 1 mm/0.039 in



735-500 1

Test wire for sold. onto test plug

Screwdriver with partially insulated shaft,

2.5 x 0.4 mm / 0.098 in x 0.016 in

210-619 1

Test pin, Ø 1 mm/0.039 in



735-500 1

Test wire for sold. onto test plug

Screwdriver with partially insulated shaft,

2.5 x 0.4 mm / 0.098 in x 0.016 in

210-619 1

Terminal strips with white printing upon request

Dimensions (in mm)



Diameter of drilled hole: 1.1$^{+0.1}$ mm
L = (No. of poles x pin spacing) + 1.5 mm



Diameter of drilled hole: 1.1$^{+0.1}$ mm
L = (No. of poles x pin spacing) + 1.5 mm



❶ in adjacent positions 0.75 mm²/AWG 18

❷ A groove at the back of the terminal block differentiates between the two pin spacings

* Further approvals with corresponding ratings can be found at www.wago.com

PCB Terminal Strips for THR Soldering Series 236 and Series 250

Pin spacing 5/ 0.197 in	Pin spacing 2.5 mm / 0.098 in	Pin spacing 3.5 mm / 0.138 in
0.08 – 2.5 mm² | AWG 28 – 12**	0.4 – 0.8 mm Ø "s" ❷ | AWG 26 – 20 "sol."	0.5 – 1.5 mm² "s+f-st" | AWG 20 – 16 "sol."
200 V/4 kV/3, I_N 16 A | 300 V, 15 A	250 V/2.5 kV/2 | 300 V, 5 A	400 V/4 kV/2 | 300 V, 5 A
320 V/4 kV/2, I_N 16 A	I_N 2 A	I_N 2 A
5 – 6 mm / 0.22 in	8.5 – 9.5 mm / 0.35 in	8.5 – 9.5 mm / 0.35 in
*	*	*



No. of poles	Item No.	Pack. unit pcs
Terminal strips, reflow soldering technology, **2 solder pins / pole,** black		
2	**236-402/334-604**	420 (4 x 105)
3	**236-403/334-604**	280 (4 x 70)
4	**236-404/334-604**	220 (4 x 55)
5	**236-405/334-604**	160 (4 x 40)
6	**236-406/334-604**	140 (4 x 35)
Other numbers of poles and pin spacings on request		

No. of poles	Item No.	Pack. unit pcs
Terminal strips with push-button, reflow soldering technology, **1 solder pin/pole staggered,** black, with test slot for test pin up to 1.3 mm Ø		
2	**250-402/350-604**	720 (4 x 180)
3	**250-403/350-604**	520 (4 x 130)
4	**250-404/350-604**	400 (4 x 100)
5	**250-405/350-604**	340 (4 x 85)
6	**250-406/350-604**	280 (4 x 70)
7	**250-407/350-604**	240 (4 x 60)
8	**250-408/350-604**	220 (4 x 55)
❷ 0.2 mm² – 0.5 mm² "f-st"		
Other numbers of poles and pin spacings on request		

No. of poles	Item No.	Pack. unit pcs
Terminal strips with push-button, reflow soldering technology, **1 solder pin/pole staggered,** black, with test slot for test pin up to 1.3 mm Ø		
2	**250-202/350-604**	560 (4 x 140)
3	**250-203/350-604**	400 (4 x 100)
4	**250-204/350-604**	300 (4 x 75)
5	**250-205/350-604**	240 (4 x 60)
6	**250-206/350-604**	200 (4 x 50)
7	**250-207/350-604**	180 (4 x 45)
8	**250-208/350-604**	160 (4 x 40)
Other numbers of poles and pin spacings on request		

Accessories

Operating tools ❶,

Plastic	**236-332**	1
Metal	**236-335**	1



Test pin, Ø 1 mm/0.039 in

735-500 1

Test wire for sold. onto test plug

Test pin, Ø 1 mm/0.039 in

735-500 1

Test wire for sold. onto test plug

Double savings are now available with WAGO PCB terminal blocks: as always, the time-saving CAGE CLAMP® and push-wire connections and now additional savings from their suitability for the THR solder process. This is achieved by changing the length of the solder pin which is adapted to the reflow process and by the use of high temperature resistant plastic for the insulating housing.

The new terminal blocks are simply pushed into the solder paste filled PCB holes and then soldered along with the SMT components. The previous wave soldering process is no longer necessary. The result is a perfect connection both from the mechanical and the electrical point of view.

Packings for pick and place applications on request

Dimensions (in mm)



L = (No. of poles x pin spacing) + 2.3 mm
Diameter of metal plated hole 1.1$^{+0.1}$ mm
optimised for PCB width of up to 2 mm



L = (No. of poles x pin spacing) + 1.5 mm
Diameter of metal plated hole 1.0$^{+0.1}$ mm
optimised for PCB width of up to 2 mm



L = (No. of poles x pin spacing) + 1.5 mm
Diameter of metal plated hole 1.0$^{+0.1}$ mm
optimised for PCB width of up to 2 mm

** AWG 12: THHN, THWN ❶ for factory wiring

THR (Through-Hole-Reflow)

Design and application recommendations for the THR solder process

The THR preparation and solder process

In the manufacture of electronic products, **S**urface **M**ount **T**echnology has led to a rapid rise in productivity.

The integration of classic electromechanical components such as connectors or PCB terminal blocks into the reflow soldering process offers even more potential for economy.

By using high temperature resistant plastic and an optimized pin design, the WAGO **T**hrough **H**ole **R**eflow PCB terminal blocks meet the requirement for SMT process capability while maintaining the necessary stability.

Metal plated PCB bore hole



SMD positioning pattern



Application of solder paste



THR product series

Series	d_i(mm)	d_A(mm)	H(mm)	d_s(mm)	D_s(µm)	d(mm)	L(mm)
734	$1.4^{+0,1}$	2.5	< 2	2.4	150	1.2	2.4
231	$1.4^{+0,1}$	2.5	< 2	2.4	150	1.2	2.4
236	$1.1^{+0,1}$	2.2	< 2	2.1	150	0.9	3.6
250	$1.0^{+0,1}$	2.0	< 2	2.1	150	0.9	3.6

d_i: Inner diameter metal plated PCB bore hole
d_A: Outer diameter metal plated PCB bore hole*
H: PCB thickness
d_s: Pattern hole diameter
D_s: Pattern thickness
d: Pin diagonal
L: Pin length



Solder pin

* When laying out the metal plated bore holes, consider the requirements of air and creepage distances of the equipment standards.

We recommend a temperature profile in accordance with EN 61760-1 and the use of forced convection ovens.

Component assembly automatic / by hand



Reflow soldering process





"Tape on Reel" packings for pick and place applications

THR soldering joint



PCB Terminal Strips 2.5 mm²/AWG 14
Pin spacings 5 mm/0.197 in and 7.5 mm/0.295 in; Series 804

Pin spacing 5 mm / 0.197 in	Pin spacing 7.5 mm / 0.295 in	Accessoires
0.5 – 2.5 mm² „s+f-st" | AWG 20 – 12 "s+f-st" 250 V/4 kV/3; I_N 16 A | 300 V, 10 A 500 V/4 kV/2; I_N 16 A |	0.5 – 2.5 mm² „s+f-st" | AWG 20 – 12 "s+f-st" 400 V/6 kV/3; I_N 16 A | 300 V, 10 A 800 V/6 kV/2; I_N 16 A |	
10 – 11 mm / 0.41 in	10 – 11 mm / 0.41 in	Internal commoning
*	*	



No. of poles	Item No.	Pack. unit pcs
1-conductor terminal strips with push button,		
2 solder pins/pole staggered, grey,		
with test slot for test pin Ø 1 mm/0.039 in		
2	**804-102**	420 (4 x 105)
3	**804-103**	280 (4 x 70)
4	**804-104**	220 (4 x 55)
5	**804-105**	180 (4 x 45)
6	**804-106**	140 (4 x 35)
7	**804-107**	120 (4 x 30)
8	**804-108**	100 (4 x 25)
9	**804-109**	100 (4 x 25)
10	**804-110**	80 (4 x 20)
11	**804-111**	80 (4 x 20)
12	**804-112**	60 (4 x 15)
13	**804-113**	60 (4 x 15)
14	**804-114**	60 (4 x 15)
15	**804-115**	60 (4 x 15)
16	**804-116**	40 (4 x 10)
Pin spacing 10 mm (with spacer) on request		

No. of poles	Item No.	Pack. unit pcs
1-conductor terminal strips with push button,		
2 solder pins/pole staggered, grey,		
with test slot for test pin Ø 1 mm/0.039 in		
2	**804-302**	320 (4 x 85)
3	**804-303**	220 (4 x 55)
4	**804-304**	160 (4 x 40)
5	**804-305**	120 (4 x 30)
6	**804-306**	100 (4 x 25)
7	**804-307**	80 (4 x 20)
8	**804-308**	80 (4 x 20)
9	**804-309**	60 (4 x 15)
10	**804-310**	60 (4 x 15)
11	**804-311**	60 (4 x 15)
12	**804-312**	40 (4 x 10)

Additional item number for coloured terminal strips			
red	. . . /**000-005**	Ordering example	
blue	. . . /**000-006** (1)	Terminal strip, pin spacing 5 mm/0.197 in, 8 poles,	
orange	. . . /**000-012**	orange	**804-108/000-012**
light green	. . . /**000-017**		

(1) Terminal blocks with blue insulation are suitable for Ex i applications (only for pin spacing 7.5 mm/0.295 in and 10 mm/0.394 in)

	Item No.	Pack. unit pcs
Marker cards,		
	100 self-adhesive strips per card	
Print - Pin spacing 5 mm/0.197 in		
1–12 (300 x)	**210-331/0500-0103**	1 card
13–24 (300 x)	**210-331/0500-0104**	1 card
Print - Pin spacing 7.5 mm/0.295 in		
1–16 (100 x)	**210-331/0750-0202**	1 card
Direct printing on request		
Test pin, Ø 1 mm/0.039 in		
	735-500	1
	Test wire for sold. onto test plug	
Screwdriver with partially insulated shaft,		
	3.5 x 0.4 mm/0.137 in x 0.016 in	
	210-620	1

Internal commoning

For example, the requirement of not routing the ground (earth) conductors over the board is met by WAGO through the "internal commoning" of 804 Series terminal strips. This way, custom terminal strips can be commoned to each other and marked at the factory.

Dimensions (in mm)



Diameter of drilled hole: $1^{+0.1}$ mm
L = (No. of poles x pin spacing) + 1.5 mm



Diameter of drilled hole: $1^{+0.1}$ mm
L = (No. of poles – 1) x pin spacing + 5 mm + 1.5 mm

* Marks and approval data can be found on the Internet at www.wago.com.

2-Conductor Female Connector Strips 1.5 mm²/AWG 16
Pin Spacing 5 mm/0.197 in, Series 806

Pin spacing 5 mm / 0.197 in
2 x 0.2 – 1.5 mm² | 2 x AWG 24 – 16
250 V/2.5 kV/3 ❶ | 300 V, 10 A
I_N 10 A
9 – 10 mm / 0.37 in
*

Pin spacing 5 mm / 0.197 in
2 x 0.2 – 1.5 mm² | 2 x AWG 24 – 16
250 V/2.5 kV/3 ❶ | 300 V, 10 A
I_N 10 A
9 – 10 mm / 0.37 in
*

❶ 250 V = rated voltage
2.5 kV = rated surge voltage
3 = pollution degree
(see also Full Line Catalog W4 Volume 2, Section 12)

Connection of solid conductors:
insert stripped wire up to the stop

Connection/disconnection of fine-stranded conductors:
open clamping unit using a screwdriver and insert stripped wire up to the stop

No. of poles	Item No.	No. of poles	Item No.
Female connector strips, grey		**Female connector strips with removal aid,** grey	
for solder pin strip		for solder pin strip	
2	**806-102**	2	**806-202**
3	**806-103**	3	**806-203**
4	**806-104**	4	**806-204**
5	**806-105**	5	**806-205**
6	**806-106**	6	**806-206**
7	**806-107**	7	**806-207**
8	**806-108**	8	**806-208**
9	**806-109**	9	**806-209**
10	**806-110**	10	**806-210**
11	**806-111**	11	**806-211**
12	**806-112**	12	**806-212**
For other lengths, please contact factory		For other lengths, please contact factory	
Additional item numbers for colored terminal strips		Additional item numbers for colored terminal strips	
blue	**.../000-006**	blue	**.../000-006**
orange	**.../000-012**	orange	**.../000-012**

Accessories

Solder pin strip,	connector pin Ø 1.3 mm solder pin Ø 1 mm 2 to 12 poles **806-902** to **806-912**	**Solder pin strip,**	connector pin Ø 1.3 mm solder pin Ø 1 mm 2 to 12 poles **806-902** to **806-912**
Marker card,	with self-adhesive marker strips	**Marker card,**	with self-adhesive marker strips
1 – 16 (160 x)	**210-332/0500-0202** 1 card	1 – 16 (160 x)	**210-332/0500-0202** 1 card
Direct printing on request		Direct printing on request	

Dimensions (in mm) **Diameter of drilled hole: 1.3 mm** **L = No. of poles x pin spacing + 1.5 mm**





Connecting the conductor directly into the connector …
…or pre-assembled



Removing the terminal blocks to place the board



Terminal strip insulation housings mixed in different colors on request



A = (No. of poles - 1) x pin spacing
B = (No. of poles - 1) x pin spacing + 4.8 mm

*Further approvals with corresponding ratings can be found at www.wago.com

Modular Terminal Blocks and Terminal Strips 6 mm²/AWG 10 CAGE CLAMP®S
Pin Spacing 7.5 mm/0.295 in; Series 746

Pin spacing 7.5 mm / 0.295 in
2 x 0.5 – 6 (10) mm² ❶ | 2 x AWG 20 – 8
400 V/6 kV/3 | 600 V, 50 A
I_N 41 A
13 – 15 mm / 0.55 in
*

❶ Push-in conductor sizes: 0,5 mm² – 10 mm² „e + f"; AWG 16 – 8 (1.5 mm² – 10 mm²) "s" and AWG 16 – 10 (1.5 mm² – 6 mm²) "insulated ferrules, 12 mm/0.472 in"





Connecting flexible wires using a screwdriver 5.5 mm



Solid wires and fine-stranded wires with ferrules can be simply pushed in

Testing with test plug Ø 2 mm/0.079 in



Terminal blocks of different colors upon request

No. of poles	Item No.	No. of poles	Item No.
2-conductor terminal strips, grey,			
2 x 2 pins / pole staggered			
2	**746-2302**		
3	**746-2303**		
4	**746-2304**		
5	**746-2305**		
6	**746-2306**		
7	**746-2307**		
8	**746-2308**		
9	**746-2309**		
10	**746-2310**		
12	**746-2312**		
For other lengths, please contact factory			
Additional item numbers for colored terminal strips			
light grey	**.../000-009**		
blue	**.../000-006**		
green-yellow	**.../000-016**		
light green	**.../000-017**		

Accessories (Marking see Full Line Catalog W4 Volume 2, Section 11)

Screwdriver with partially insulated shaft

(5.5 x 0.8) mm
210-621

Test plug with cable 500 mm/1'7.7"



210-136 2 mm/0.079 in Ø, red
210-137 2.3 mm/0.091 in Ø, yell.

Dimensions (in mm) Diameter of drilled hole: 2.2 $^{+0.1}$ mm L = No. of poles x pin spacing + 2.7 mm





Modular Terminal Blocks and Terminal Strips without Jumper Slot 4 mm²/AWG 12 Pin Spacing 5 mm/0.197 in; Series 745

Pin spacing 5 mm / 0.197 in
0.08 – 4 mm² | AWG 28 – 12
250 V/4 kV/3 | 300 V, 20 A
I_N 32 A
8 – 9 mm / 0.33 in
*

Pin spacing 5 mm / 0.197 in
0.08 – 4 mm² | AWG 28 – 12
250 V/4 kV/3 | 300 V, 20 A
I_N 32 A
8 – 9 mm / 0.33 in
*

Color	Item No.	Pack.-unit pcs
Modular terminal blocks without jumper slot, 2 solder pins/pole		
grey	**745-3801**	200 (2 x 100)
light grey	**745-3803**	200 (2 x 100)
blue	**745-3804**	200 (2 x 100)
green-yellow	**745-3807**	200 (2 x 100)
light green	**745-3808**	200 (2 x 100)

Accessoires

End plate, snap-on type, 1.5 mm / 0.059 in thick

grey **745-3100** 100

Spacer, 2.5 mm / 0.098 in thick

grey **745-3138**
for extending the pin spacing

Test plug, with cable 500 mm/17.7"



Ø 2 mm / 0.079 in, red **210-136**/50
Ø 2.3 mm / 0.091 in, yel. **210-137**/50

Dimensions (in mm)



Diameter of drilled hole: 1.5 $^{+0.1}$ mm

Saving space
2 terminal strips can be arranged in front of each other



Wire connection using a screwdriver 3.5 mm / 0.138 in

Testing with test plug Ø 2 mm / 0.079 in

No. of poles	Item No.
Terminal strips without jumper slot, grey, **2 solder pins/pole**	
2	**745-3102**
3	**745-3103**
4	**745-3104**
5	**745-3105**
6	**745-3106**
7	**745-3107**
8	**745-3108**
9	**745-3109**
10	**745-3110**
12	**745-3112**

For assemblies in other lengths and colours, please contact factory.

Dimensions (in mm)



Diameter of drilled hole: 1.5 $^{+0.1}$ mm
L = No. of poles x pin spacing + 1.5 mm

* Further approvals with corresponding ratings can be found at www.wago.com

Terminal Strips
without Jumper Slot 4 mm²/AWG 12
Pin Spacings 7.5 mm/0.295 in, 10 mm/0.394 in, 12.5 mm/0.492 in; Series 745

CAGE CLAMP®

Pin spacing 7.5 mm / 0.295 in	Pin spacing 10 mm / 0.394 in	Pin spacing 12.5 mm / 0.492 in
0.08 – 4 mm² / AWG 28 – 12	0.08 – 4 mm² / AWG 28 – 12	0.08 – 4 mm² / AWG 28 – 12
500 V/6 kV/3 / 300 V, 20 A	630 V/8 kV/3 / 300 V, 20 A	630 V/8 kV/3 / 600 V, 20 A
I_N 32 A	I_N 32 A	I_N 32 A
8 – 9 mm / 0.33 in	8 – 9 mm / 0.33 in	8 – 9 mm / 0.33 in
*	*	*

No. of poles	Item No.	No. of poles	Item No.	No. of poles	Item No.
Terminal strips		**Terminal strips**		**Terminal strips**	
without jumper slot, grey,		**without jumper slot,** grey,		**without jumper slot,** grey,	
2 solder pins/pole		**2 solder pins/pole**		**2 solder pins/pole**	
2	**745-3152**	2	**745-3202**	2	**745-3252**
3	**745-3153**	3	**745-3203**	3	**745-3253**
4	**745-3154**	4	**745-3204**	4	**745-3254**
5	**745-3155**	5	**745-3205**	5	**745-3255**
6	**745-3156**	6	**745-3206**	6	**745-3256**
7	**745-3157**	7	**745-3207**	7	**745-3257**
8	**745-3158**	8	**745-3208**	8	**745-3258**
9	**745-3159**	9	**745-3209**	9	**745-3259**
10	**745-3160**	10	**745-3210**	10	**745-3260**
12	**745-3162**	12	**745-3212**	12	**745-3262**
For assemblies in other lengths and colors, please contact factory.		For assemblies in other lengths and colors, please contact factory.		For assemblies in other lengths and colors, please contact factory.	

Additional item Nos. for colored terminal strips and end plates	
blue	.../...-006 (1)
light grey	.../...-009
green-yellow	.../...-016
light green	.../...-017

(1) Suitable for EEx i applications (only suitable for pin spacings 7.5 mm/0.295 in; 10 mm/0.394 in and 12.5 mm/0.492 in)

Ordering examples

Terminal strip, pin spacing 5 mm/0.197 in
8 poles, light grey: **745-3108/000-009**

Terminal strip pin spacing 12 mm/0.492 in
12 poles, blue: **745-3262/000-006**

Dimensions (in mm) (Mounting shall provide flexibility for the PCB.)



Diameter of drilled hole: $1.5^{+0.1}$ mm
L = (No. of poles – 1) x pin spacing + 5 mm + 1.5 mm



Diameter of drilled hole: $1.5^{+0.1}$ mm
L = (No. of poles – 1) x pin spacing + 5 mm + 1.5 mm



Diameter of drilled hole: $1.5^{+0.1}$ mm
L = (No. of poles – 1) x pin spacing + 5 mm + 1.5 mm

Modular Terminal Blocks 6 mm²/AWG 10, Series 745, Pin Spacings 7.5 mm / 0.295 in and 10 mm / 0.394 in

Pin spacing 7.5 mm / 0.295 in	Pin spacing 10 mm / 0.394 in	Spacer
0.2 – 6 mm² | AWG 24 – 10 400 V/6 kV/3 | 300 V, 30 A cULus I_N 32 A 11 – 12 mm / 0.45 in *cULus	0.2 – 6 mm² | AWG 24 – 10 630 V/8 kV/3 | 300 V, 30 A cULus I_N 32 A 11 – 12 mm / 0.45 in *cULus	

Color	Item No.	Pack.-unit pcs	Color	Item No.	Pack.-unit pcs	Color	Item No.	Pack.-unit pcs
Modular terminal blocks,			**Modular terminal blocks,**			**Spacer, 2.5 mm wide**		
2 solder pins / pole			**2 solder pins / pole**					
grey	**745-831**	100 (2 x 50)	grau	**745-841**	100 (2 x 50)	grey	**745-338**	
light grey	**745-833**	100 (2 x 50)	light grey	**745-843**	100 (2 x 50)			
blue	**745-834** (1)	100 (2 x 50)	blue	**745-844** (1)	100 (2 x 50)			
green-yellow	**745-837**	100 (2 x 50)	green-yellow	**745-847**	100 (2 x 50)			
light green	**745-838**	100 (2 x 50)	light green	**745-848**	100 (2 x 50)			
(1) suitable for Ex i applications			(1) suitable for Ex i applications					

Accessories

(for WMB marking accessories and miniature WSB marking accessories see Full Line Catalog W4 Volume 1, Section 11)

	**End plate,** snap-on type 1.6 mm / 0.063 in thick grey **745-300** 100			**End plate,** snap-on type 1.6 mm / 0.063 in thick grey **745-300** 100	
	**End plate with fixing flange,** grey **745-340** 100			**End plate with fixing flange,** grey **745-340** 100	
	**End plate with fixing flange,** grey **745-345** 100			**End plate with fixing flange,** grey **745-345** 100	
	**Test plug,** w. cable 500 mm/1'7.7" Ø 2 mm / 0.079 in, red **210-136** 50 Ø 2.3 mm / 0.091 in, yel. **210-137** 50			**Test plug,** w. cable 500 mm/1'7.7" Ø 2 mm / 0.079 in, red **210-136** 50 Ø 2.3 mm / 0.091 in, yel. **210-137** 50	
	**Comb type jumper bar** 1 to 3 **745-381** 250 (5 x 50)			**Comb type jumper bar** 1 to 3 **745-391** 250 (5 x 50)	
	2-way **745-382** 250 (5 x 50) 3-way **745-383** 250 (5 x 50) 4-way **745-384** 200 (4 x 50)			2-way **745-392** 250 (5 x 50) 3-way **745-393** 250 (5 x 50) 4-way **745-394** 200 (4 x 50)	
	5-way **745-385** 200 (4 x 50) 10-way **745-380** 200 (4 x 50)			5-way **745-395** 200 (4 x 50) 10-way **745-390** 200 (4 x 50)	

Dimensions (in mm)



Diameter of drilled hole: 1.8 $^{+0.1}$ mm



Diameter of drilled hole: 1.8 $^{+0.1}$ mm

Application notes

Higher rated voltages are possible using terminal strips with spacers so that. 600 V to UL 1059 can be achieved without limitation at only 12.5 mm / 0.492 in pin spacing.

*Further approvals with corresponding ratings can be found at www.wago.com

Terminal Strips 6 mm²/AWG 10 with Spacers
Pin Spacings 10 mm/0.394 in, 12.5 mm/0.492 in and 15 mm/0.591 in; Series 745

CAGE CLAMP®

Pin spacing 10 mm / 0.394 in	Pin spacing 12.5 mm / 0.492 in	Pin spacing 15 mm / 0.591 in
0.2 – 6 mm² | AWG 24 – 10	0.2 – 6 mm² | AWG 24 – 10	0.2 – 6 mm² | AWG 24 – 10
630 V/8 kV/3 | 300 V, 10 A ❶	800 V/8 kV/3 | 600 V, 30 A	1000 V/10 kV/3 | 600 V, 30 A
I_N 32 A	I_N 32 A	I_N 32 A
11 – 12 mm / 0.45 in	11 – 12 mm / 0.45 in	11 – 12 mm / 0.45 in
*	*	*

No. of poles	Item No.	Pack.-unit pcs
Terminal strips without fixing flanges, grey, **with spacers**		
2 solder pins / pole		
2	**745-1352**	104
3	**745-1353**	72
4	**745-1354**	48
5	**745-1355**	40
6	**745-1356**	32
7	**745-1357**	24
8	**745-1358**	24
9	**745-1359**	16
10	**745-1360**	16
12	**745-1362**	16
Additional item no. for terminal strips with fixing flanges	**.../005-000**	

❶ Using jumpers, the UL current is reduced to 10 A at pin spacing 10 mm

For assemblies in other lengths and colors, please contact factory.

No. of poles	Item No.	Pack.-unit pcs
Terminal strips without fixing flanges, grey, **with spacers**		
2 solder pins / pole		
2	**745-1402**	
3	**745-1403**	
4	**745-1404**	
5	**745-1405**	
6	**745-1406**	
7	**745-1407**	
8	**745-1408**	
9	**745-1409**	
10	**745-1410**	
12	**745-1412**	
Additional item no. for terminal strips with fixing flanges	**.../005-000**	

For assemblies in other lengths and colors, please contact factory.

No. of poles	Item No.	Pack.-unit pcs
Terminal strips without fixing flanges, grey, **with spacers**		
2 solder pins / pole		
2	**745-1452**	
3	**745-1453**	
4	**745-1454**	
5	**745-1455**	
6	**745-1456**	
7	**745-1457**	
8	**745-1458**	
9	**745-1459**	
10	**745-1460**	
12	**745-1462**	
Additional item no. for terminal strips with fixing flanges	**.../005-000**	

For assemblies in other lengths and colors, please contact factory.

Additional item nos. for colored terminal strips and end plates	
blue	.../...-006 ❶
light grey	.../...-009
green-yellow	.../...-016 ❶
light green	.../...-017

❶ Suitable for Ex i applications

Ordering examples

Terminal strip, pin spacing 12.5 mm/0.492 in
8 poles, light grey: **745-1408/000-009**

Terminal strip with fixing flanges,
pin spacing 15 mm/0.591 in
12 poles, blue: **745-1462/005-006**

Dimensions (in mm) (Mounting shall provide flexibility for the PCB.)



Diameter of drilled hole: 1.8 $^{+0.1}$ mm
L = (No. of poles – 1) x pin spacing + 7.5 mm
L1 = L + 1.6 mm ≙ without fixing flanges



Diameter of drilled hole: 1.8 $^{+0.1}$ mm
L = (No. of poles – 1) x pin spacing + 7.5 mm
L1 = L + 1.6 mm ≙ without fixing flanges



Diameter of drilled hole: 1.8 $^{+0.1}$ mm
L = (No. of poles – 1) x pin spacing + 7.5 mm
L1 = L + 1.6 mm ≙ without fixing flanges

MULTI CONNECTION SYSTEM ***MICRO***
Male and Female Connectors, 100 % Protected against Mismating, CAGE CLAMP®
Pin Spacing 2.5 mm / 0.098 in

Pin spacing 2.5 mm/0.098 in, light grey	**Pin spacing 2.5 mm/0.098 in,** light grey	**Pin spacing 2.5 mm/0.098 in,** light grey
0.08 – 0.5 mm² | **AWG 28 – 20**	**0.08 – 0.5 mm²** | **AWG 28 – 20**	**0.08 – 0.5 mm²** | **AWG 28 – 20**
250 V/2.5 kV/2 | **250 V, 4 A**	**250 V/2.5 kV/2** | **250 V, 4 A**	**250 V/2.5 kV/2** | **250 V, 4 A**
I_N 4 A | **150 V, 4 A**	**I_N 4 A** | **150 V, 4 A**	**I_N 4 A** | **150 V, 4 A**
5 – 6 mm / 0.22 in	**5 – 6 mm / 0.22 in**	**5 – 6 mm / 0.22 in**
* CCA GL BV LR NV ABS	* CCA GL BV LR NV ABS	



No. of poles	Item No.	No. of poles	Item No.	No. of poles	Item No.
Male connectors with CAGE CLAMP® connection, 100 % protected against mismating, light grey		**Female connectors with CAGE CLAMP® connection, 100 % protected against mismating,** with coding fingers, light grey		**Female connectors with CAGE CLAMP® connection and locking levers, 100 % protected against mismating,** with coding fingers, light grey	
2	**733-202**	2	**733-102**	2	**733-102/037-000**
3	**733-203**	3	**733-103**	3	**733-103/037-000**
4	**733-204**	4	**733-104**	4	**733-104/037-000**
5	**733-205**	5	**733-105**	5	**733-105/037-000**
6	**733-206**	6	**733-106**	6	**733-106/037-000**
7	**733-207**	7	**733-107**	7	**733-107/037-000**
8	**733-208**	8	**733-108**	8	**733-108/037-000**
10	**733-210**	10	**733-110**	10	**733-110/037-000**
12	**733-212**	12	**733-112**	12	**733-112/037-000**

Accessories

	**Operating tool,** see Full Line Catalog W4 Volume 2, Section 11		**Operating tool,** see Full Line Catalog W4 Volume 2, Section 11		**Operating tool,** see Full Line Catalog W4 Volume 2, Section 11
	**Coding key,** snap-on type, light grey **733-330**				
Marker card,		**Marker card,**		**Marker card,**	
	100 self-adhesive strips per card		100 self-adhesive strips per card		100 self-adhesive strips per card
Marking		Marking		Marking	
1 – 16 (400x)	**210-331/0250-0202**	1 – 16 (400x)	**210-331/0250-0202**	1 – 16 (400x)	**210-331/0250-0202**
For further printings Full Line Catalog W4 Volume 2, Section 11		For further printings Full Line Catalog W4 Volume 2, Section 11		For further printings Full Line Catalog W4 Volume 2, Section 11	
For direct printing please contact factory		For direct printing please contact factory		For direct printing please contact factory	

Dimensions (in mm)



T = 2.5 mm
L = (No. of poles + 1) x pin spacing



L = (No. of poles x pin spacing) + 2.1 mm



L = No. of poles x pin spacing

* Approvals with corresponding ratings see www.wago.com

MULTI CONNECTION SYSTEM ***MINI***
Headers with Solder Pins, Reflow Soldering
100 % Protected against Mismating, Pin Spacing 3.5 mm/0.138 in

Pin spacing 3.5 mm/0.138 in, black	**Pin spacing 3.5 mm/0.138 in,** black	
250 V/2.5 kV/2 | **300 V, 10 A**	**250 V/2.5 kV/2** | **300 V, 10 A**	
I_N 10 A	**I_N 10 A**	
*	*	

No. of poles	Item No.	No. of poles	Item No.	Width of reel (W)
Headers with solder pins,		**Headers with solder pins,**		
100 % protected against mismating, black,		**100 % protected against mismating,** black,		
straight solder pin 1 mm x 1 mm,		straight solder pin 1 mm x 1 mm,		
length of solder pin 2.4 mm/0.094 in		**length of solder pin 2.4 mm/0.094 in**		
		Headers in tape on reel acc. to IEC 60286-3		
		Reel diameter 330 mm/13 in		(mm)
2	**734-132/105-604**	2	**734-132/105-604/997-405**	32
3	**734-133/105-604**	3	**734-133/105-604/997-405**	32
4	**734-134/105-604**	4	**734-134/105-604/997-405**	32
5	**734-135/105-604**	5	**734-135/105-604/997-405**	32
6	**734-136/105-604**	6	**734-136/105-604/997-407**	56
8	**734-138/105-604**	8	**734-138/105-604/997-407**	56
10	**734-140/105-604**	10	**734-140/105-604/997-407**	56
12	**734-142/105-604**	12	**734-142/105-604/997-407**	56
		200 pieces per reel		

Accessories (fit after soldering)

	**Coding key,** light grey, snap-on type **734-130**		**Coding key,** light grey, snap-on type **734-130**

Dimensions Diameter of the plated through hole: 1.4 $^{+0.1}$ mm – optimized for PCB thickness up to 2 mm



L = (No. of poles – 1) x pin spacing + 5.9 mm



For use in reflow soldering processes in convection ovens based on EN 61 760-1

- apply solder paste
- place components on PCB
- begin reflow soldering process

Note: These connectors can only be mated and unmated at voltages below 42 V and in the "No load" condition.

For mating and unmating at low power values, please request data.

* Further approvals with corresponding ratings can be found at www.wago.com

MULTI CONNECTION SYSTEM ***MINI***
Headers with Solder Pins, Reflow Soldering
100 % Protected against Mismating, Pin spacing 3.5 mm/0.138 in

Pin spacing 3.5 mm/0.138 in, black **250 V/2.5 kV/2** | **300 V, 10 A** **I_N 10 A** *	**Pin spacing 3.5 mm/0.138 in,** black **250 V/2.5 kV/2** | **300 V, 10 A** **I_N 10 A** *	

No. of poles	Item No.	No. of poles	Item No.	Width of reel (W)
Headers with solder pins,		**Headers with solder pins,**		
100 % protected against mismating, black,		**100 % protected against mismating,** black,		
right angle solder pin 1 mm x 1 mm,		right angle solder pin 1 mm x 1 mm,		
length of solder pin 2.4 mm/0.094 in		**length of solder pin 2.4 mm/0.094 in**		
		Headers in tape on reel acc. to IEC 60286-3		
		Reel diameter 330 mm/13 in		(mm)
		2	**734-162/105-604/997-405**	32
2	**734-162/105-604**	3	**734-163/105-604/997-405**	32
3	**734-163/105-604**	4	**734-164/105-604/997-405**	32
4	**734-164/105-604**	5	**734-165/105-604/997-405**	32
5	**734-165/105-604**	6	**734-166/105-604/997-407**	56
6	**734-166/105-604**	8	**734-168/105-604/997-407**	56
8	**734-168/105-604**	10	**734-170/105-604/997-407**	56
10	**734-170/105-604**	12	**734-172/105-604/997-407**	56
12	**734-172/105-604**			
		280 pieces per reel		

Accessories (fit after soldering)

	**Coding key,** light grey, snap-on type **734-130**		**Coding key,** light grey, snap-on type **734-130**

For use in reflow soldering processes in convection ovens based on EN 61 760-1

- apply solder paste
- place components on PCB
- begin reflow soldering process

Dimensions **Diameter of the plated through hole: 1.4 $^{+0.1}$ mm – optimized for PCB thickness up to 2 mm**



L = (No. of poles – 1) x pin spacing + 5.9 mm





Position with even numbers of poles



Position with odd numbers of poles

MULTI CONNECTION SYSTEM ***MIDI*** – Reflow Soldering
Headers with Solder Pins, Pin Spacing 5 mm/0.197 in

Pin spacing 5 mm/0.197 in, black **250 V/4 kV/3** | **300 V, 10 A** **I_N 12 A** *	**Pin spacing 5 mm/0.197 in,** black **250 V/4 kV/3** | **300 V, 10 A** **I_N 12 A** *	



No. of poles	Item No.	No. of poles	Item No.	Width of reel (W)
Headers with solder pins, black, straight solder pin 1 mm x 1 mm, **length of solder pin 2.4 mm/0.094 in**		**Headers with solder pins,** black, straight solder pin 1 mm x 1 mm, **length of solder pin 2.4 mm/0.094 in**		
			Headers in tape on reel acc. to IEC 60286-3	
			Reel diameter 330 mm/13 in	(mm)
2	**231-132/001-000/105-604**	2	**231-132/001-000/105-604/997-405**	32
3	**231-133/001-000/105-604**	3	**231-133/001-000/105-604/997-405**	32
4	**231-134/001-000/105-604**	4	**231-134/001-000/105-604/997-407**	56
5	**231-135/001-000/105-604**	5	**231-135/001-000/105-604/997-407**	56
6	**231-136/001-000/105-604**	6	**231-136/001-000/105-604/997-407**	56
8	**231-138/001-000/105-604**	8	**231-138/001-000/105-604/997-407**	56
10	**231-140/001-000/105-604**	10	**231-140/001-000/105-604/997-409**	88
12	**231-142/001-000/105-604**	12	**231-142/001-000/105-604/997-409**	88
			170 pieces per reel	

Accessories (fit after soldering)

	**Coding key,** snap-on type, light grey **231-129**		**Coding key,** snap-on type, light grey **231-129**
	**Separator,** for formation of groups, light grey **231-500**		**Separator,** for formation of groups, light grey **231-500**

Dimensions **Diameter of the plated through hole: 1.4 $^{+0,1}$ mm – optimized for PCB thickness up to 2 mm**



A = (No. of poles x pin spacing) + 3.2 mm



For use in reflow soldering processes in convection ovens based on EN 61760-1

- apply solder paste
- place components on PCB
- begin reflow soldering process

Note: These connectors can only be mated and unmated at voltages below 42 V and in the "No load" condition.

For mating and unmating at low power values, please request data.

* Further approvals with corresponding ratings can be found at www.wago.com

Headers with Solder Pins, Pin Spacing 5 mm/0.197 in

Pin spacing 5 mm/0.197 in, black **250 V/4 kV/3** | **300 V, 10 A** **I_N 12 A** *	**Pin spacing 5 mm/0.197 in,** black **250 V/4 kV/3** | **300 V, 10 A** **I_N 12 A** *	

No. of poles	Item No.	No. of poles	Item No.	Width of reel (W)
Headers with solder pins, black, right angle solder pin 1 mm x 1 mm, **length of solder pin 2.4 mm/0.094 in**		**Headers with solder pins,** black, right angle solder pin 1 mm x 1 mm, **length of solder pin 2.4 mm/0.094 in**		
			Headers in tape on reel acc. to IEC 60286-3	
			Reel diameter 330 mm/13 in	(mm)
2	**231-432/001-000/105-604**	2	**231-432/001-000/105-604/997-405**	32
3	**231-433/001-000/105-604**	3	**231-433/001-000/105-604/997-405**	32
4	**231-434/001-000/105-604**	4	**231-434/001-000/105-604/997-407**	56
5	**231-435/001-000/105-604**	5	**231-435/001-000/105-604/997-407**	56
6	**231-436/001-000/105-604**	6	**231-436/001-000/105-604/997-407**	56
8	**231-438/001-000/105-604**	8	**231-438/001-000/105-604/997-407**	56
10	**231-440/001-000/105-604**	10	**231-440/001-000/105-604/997-409**	88
12	**231-442/001-000/105-604**	12	**231-442/001-000/105-604/997-409**	88
			330 pieces per reel	

For use in reflow soldering processes in convection ovens based on EN 61 760-1

- apply solder paste
- place components on PCB
- begin reflow soldering process

Accessories (fit after soldering)

	**Coding key,** snap-on type, light grey **231-129**		**Coding key,** snap-on type, light grey **231-129**
	**Separator,** for formation of groups, light grey **231-500**		**Separator,** for formation of groups, light grey **231-500**

Dimensions

Diameter of the plated through hole: 1.4 $^{+0.1}$ mm – optimized for PCB thickness up to 2 mm



A = (No. of poles x pin spacing) + 3.2 mm
B = A + 4.8 mm; C = B + 7.2 mm





Position with even numbers of poles



Position with odd numbers of poles

MULTI CONNECTION SYSTEM ***MINI*** **– Extension of Pole Number**
Connectors, 100 % Protected against Mismating
Pin Spacing 3.5 mm **see also Full Line Catalog W4 Volume 2, pages 5.4 – 5.9**



No. of poles	Item No.	No. of poles	Item No.	
Headers with solder pins, straight solder pin 1 mm x 1 mm		**Headers with solder pins,** right angle solder pin 1 mm x 1 mm		
14	**734-144**	14	**734-174**	





No. of poles	Item No.	No. of poles	Item No.	No. of poles	Item No.
Male connector with CAGE CLAMP® connection		**Femal connector with CAGE CLAMP® connection,** coding fingers		**Femal connector with CAGE CLAMP® connection and locking device,** coding fingers	
14	**734-314**	14	**734-114**	14	**734-114/037-000**







Combi Strip, 100 % Protected against Mismating, Pin Spacing 3.5 mm / 0.138 in

Pin spacing 3.5 mm/0.138 in, light grey **0.08 – 1.5 mm²** | **AWG 28 – 14**** **250 V/2.5 kV/2** | **300 V, 10 A** **I_N 10 A** **7 mm / 0.28 in** *	**Pin spacing 3.5 mm/0.138 in,** light grey **0.08 – 1.5 mm²** | **AWG 28 – 14**** **250 V/2.5 kV/2** | **300 V, 10 A** **I_N 10 A** **7 mm / 0.28 in** *

No. of poles	Item No.	No. of poles	Item No.
Combi strip with CAGE CLAMP® connection, 100% protected against mismating, pin and socket connection, with coding fingers, light grey		**Combi strip with CAGE CLAMP® connection and locking levers, 100 % protected against mismating,** with coding fingers, light grey	
2	**734-362**	2	**734-362/037-000**
3	**734-363**	3	**734-363/037-000**
:	:	:	:
6	**734-366**	6	**734-366/037-000**
7	**734-367**	7	**734-367/037-000**
8	**734-368**	8	**734-368/037-000**
9	**734-369**	9	**734-369/037-000**
10	**734-370**	10	**734-370/037-000**
12	**734-372**	12	**734-372/037-000**

Combi strip

The combination of pin and socket connections allows the assembly of many combi strips.

2 CAGE CLAMP® connections allow the looping through of potentials .

Accessories

Marker cards, 80 self-adhesive strips per card		**Marker cards,** 80 self-adhesive strips per card	
Marking		Marking	
1 – 16 (240x)	**210-332/0350-0202**	1 – 16 (240x)	**210-332/0350-0202**
17 – 32 (240x)	**210-332/0350-0204**	17 – 32 (240x)	**210-332/0350-0204**
For further printings see W4 Volume 2, Section 11		For further printings see W4 Volume 2, Section 11	
For direct printing please contact factory		For direct printing please contact factory	
	**Screwdriver,** (2.5 x 0.4) mm (0.098 x 0.016) in **210-619**		**Screwdriver,** (2.5 x 0.4) mm (0.098 x 0.016) in **210-619**
	**Coding key,** snap-on type, light grey **734-130**		**Coding key,** snap-on type, light grey **734-130**

Dimensions (in mm) L_4 = (No. of poles –1) x pin spacing + 5.9 mm + 0.45 mm





Other dimensions see drawings on the left

* Approvals with corresponding ratings see www.wago.com
** AWG 14: THHN, THWN

MULTI CONNECTION SYSTEM ***MINI***
IP 20 Protection using Cover for Male Connectors, Pin Spacings 3.5 mm/0.138 in / 3.81 mm/0.15 in

Pin spacings 3.5 mm/0.138 in / 3.81 mm/0.15 in, black		

No. of poles	Item No.
Cover for male connetors, Series 734	
IP 20 protection, black	
4	**734-420**

Insert the cover into the male connector to be protected





The cover is flush with the front edge of the male connector

Cut the cover to the required number of poles without singularization.



Pull out the cover using a suitable tool

Connection tool for pin spacings 3.5 mm/0.138 in and 3.81 mm/0.15 in	**Connection tool for pin spacings 5 mm/0.197 in and 5.08 mm/0.2 in and 7.5 mm/0.295 in and 7.62 mm/0.3 in**	

Item No.		Item No.	
Connection tool		**Connection tool**	
for male and female connectors		**for male and female connectors**	
with CAGE CLAMP® connection,		**with CAGE CLAMP® connection,**	
Series 734		**Series 231, 232, 721, 722, 723, 731, 732**	
black	**734-231**	natural	**231-159**

Wire connection

Wire entry and operation of the clamp are parallel to each other

Wire connection

Wire entry and operation of the clamp are parallel to each other

Wire connection

Wire entry and operation of the clamp is done at a right angle to each other



Wire connection

Wire entry and operation of the clamp is done at a right angle to each other

MULTI CONNECTION SYSTEM ***MINI***
Female Connectors with Solder Pins, 100 % Protected against Mismating
Pin Spacing 3.5 mm/0.138 in

Pin spacing 3.5 mm/0.138 in, light grey **250 V/2.5 kV/2** | **300 V, 10 A** **I_N 10 A** *	**Pin spacing 3.5 mm/0.138 in,** light grey **250 V/2.5 kV/2** | **300 V, 10 A** **I_N 10 A** *	**Female connectors with solder pins and locking device** *

No. of poles	**Item No.**	**No. of poles**	**Item No.**	**Additional item No.** for . . .
Female connectors with straight solder pins,		**Female connectors with right angle solder pins,**		. . . Female connectors with straight or right angle
100 % protected against mismating,		**100 % protected against mismating,**		solder pins and **locking device**
with coding fingers, with two latches, light grey,		with coding fingers, with two latches, light grey,		
solder pin 0.9 mm x 0.9 mm		solder pin 0.9 mm x 0.9 mm		
2 (one latch only)	**734-462**	2 (one latch only)	**734-532**	**. . ./037-000**
3	**734-463**	3	**734-533**	
:	:	:	:	
6	**734-466**	6	**734-536**	
:	:	:	:	Ordering example:
10	**734-470**	10	**734-540**	Female connector with straight solder pins
12	**734-472**	12	**734-542**	and locking device,
:	:	:	:	100 % protected against mismating,
14	**734-474**	14	**734-544**	pin spacing 3.5 mm/0.138 in, light grey,
16	**734-476**	16	**734-546**	12-pole **734-472/037-000**
18	**734-478**	18	**734-548**	
20	**734-480**	20	**734-550**	
24	**734-484**	24	**734-554**	

Accessories

Marker cards,		**Marker cards,**		**Marker cards,**	
	80 self-adhesive strips per card		80 self-adhesive strips per card		80 self-adhesive strips per card
Marking		Marking		Marking	
1 – 16 (240 x)	**210-332/0350-0202**	1 – 16 (240 x)	**210-332/0350-0202**	1 – 16 (240 x)	**210-332/0350-0202**
17 – 32 (240 x)	**210-332/0350-0204**	17 – 32 (240 x)	**210-332/0350-0204**	17 – 32 (240 x)	**210-332/0350-0204**
other markings		other markings		other markings	
see Full Line Catalog W4 Volume 2, Section 11		see Full Line Catalog W4 Volume 2, Section 11		see Full Line Catalog W4 Volume 2, Section 11	
For direct printing, please contact factory		For direct printing, please contact factory		For direct printing, please contact factory	

Dimensions (in mm)

Diameter of drilled hole: $1.4^{+0.1}$ mm



L = No. of poles – 1 x pin spacing + 1.5 mm



L = No. of poles – 1 x pin spacing + 1.5 mm



L = No. of poles – 1 x pin spacing

* Approvals with corresponding ratings see www.wago.com

MULTI CONNECTION SYSTEM ***MINI***
Female Connectors with Solder Pins, 100 % Protected against Mismating
Pin Spacing 3.81 mm/0.15 in

Pin spacing 3.81 mm/0.15 in, orange **250 V/2.5 kV/2 | 300 V, 10 A** **I_N 10 A** *	**Pin spacing 3.81 mm/0.15 in, orange** **250 V/2.5 kV/2 | 300 V, 10 A** **I_N 10 A** *	**Female connectors with solder pins and locking device** *

No. of poles	Item No.	No. of poles	Item No.	Additional item No. for . . .
Female connectors with straight solder pins,		**Female connectors with right angle solder pins,**		. . . Female connectors with straight or right angle
100 % protected against mismating,		**100 % protected against mismating,**		solder pins and **locking device**
with coding fingers, with two latches, light grey,		with coding fingers, with two latches, light grey,		
solder pin 0.9 mm x 0.9 mm		solder pin 0.9 mm x 0.9 mm		
2 (one latch only)	**734-502**	2 (one latch only)	**734-562**	**. . ./037-000**
3	**734-503**	3	**734-563**	
4	**734-504**	4	**734-564**	
5	**734-505**	5	**734-565**	
6	**734-506**	6	**734-566**	Ordering example:
7	**734-507**	7	**734-567**	Female connector with straight solder pins
8	**734-508**	8	**734-568**	and locking device,
9	**734-509**	9	**734-569**	100 % protected against mismating,
10	**734-510**	10	**734-570**	pin spacing 3.81 mm/0.15 in, light grey,
12	**734-512**	12	**734-572**	8-pole **734-568/037-000**
14	**734-514**	14	**734-574**	
16	**734-516**	16	**734-576**	
20	**734-520**	20	**734-580**	

Accessories

Marker cards,		**Marker cards,**		**Marker cards,**	
	80 self-adhesive strips per card		80 self-adhesive strips per card		80 self-adhesive strips per card
Marking		Marking		Marking	
1 – 16 (240 x)	**210-332/0381-0202**	1 – 16 (240 x)	**210-332/0381-0202**	1 – 16 (240 x)	**210-332/0381-0202**
17 – 32 (240 x)	**210-332/0381-0204**	17 – 32 (240 x)	**210-332/0381-0204**	17 – 32 (240 x)	**210-332/0381-0204**
other markings		other markings		other markings	
see Full Line Catalog W4 Volume 2, Section 11		see Full Line Catalog W4 Volume 2, Section 11		see Full Line Catalog W4 Volume 2, Section 11	
For direct printing, please contact factory		For direct printing, please contact factory		For direct printing, please contact factory	

Dimensions (in mm) **Diameter of drilled hole: 1.4 $^{+0.1}$ mm**



L = No. of poles – 1 x pin spacing + 1.5 mm



L = No. of poles – 1 x pin spacing + 1.5 mm



L = No. of poles – 1 x pin spacing

MULTI CONNECTION SYSTEM ***MIDI***
Angled Female Connectors, 100 % Protected against Mismating, CAGE CLAMP®
Pin Spacing 5 mm/0.197 in

Pin spacing 5 mm/0.197 in, light grey	**Pin spacing 5 mm/0.197 in, light grey**	
0.08 – 2.5 mm² | **AWG 28 – 12****	**0.08 – 2.5 mm²** **AWG 28 – 12****	
250 V/4 kV/3 | **300 V, 15 A**	**250 V/4 kV/3** **300 V, 15 A**	
I_N 14 A | **300 V, 15 A**	**I_N 14 A** **300 V, 15 A**	
8 – 9 mm / 0.33 in	**8 – 9 mm / 0.33 in**	
*	*	

No. of poles	Item No.	No. of poles	Item No.	
Angled female connectors with CAGE CLAMP® connection, 100 % protected against mismating, conductor exit **same direction** as latches, with coding fingers, with 2 latches, light grey		**Angled female connectors with CAGE CLAMP® connection, 100 % protected against mismating,** conductor exit **same direction** as latches, with coding fingers, with 2 latches, light grey		
2 (one latch only)	**722-202/026-000**	2 (one latch only)	**722-102/026-000**	
3	**722-203/026-000**	3	**722-103/026-000**	
4	**722-204/026-000**	4	**722-104/026-000**	
5	**722-205/026-000**	5	**722-105/026-000**	
6	**722-206/026-000**	6	**722-106/026-000**	
:	:	:	:	
10	**722-210/026-000**	10	**722-110/026-000**	
12	**722-212/026-000**	12	**722-112/026-000**	
14	**722-214/026-000**	14	**722-114/026-000**	
16	**722-216/026-000**	16	**722-116/026-000**	
20	**722-220/026-000**	20	**722-120/026-000**	
Accessories				
	Test plug, w. cable 500 mm/1'7.7" Ø 2 mm/0.079 in, red **210-136** Ø 2.3 mm/0.091 in, yel. **210-137**		**Test plug,** w. cable 500 mm/1'7.7" Ø 2 mm/0.079 in, red **210-136** Ø 2.3 mm/0.091 in, yel. **210-137**	
	Insulation stop, 5 pcs/strip 0.08 - 0.2 mm² ❷ (white) **231-670** 0.25 - 0.5 mm² (light gr.) **231-671** 0.75 - 1 mm² (dark grey) **231-672** ❷ 0.2 mm² solid / 0.14 mm² f-st		**Insulation stop,** 5 pcs/strip 0.08 - 0.2 mm² ❷ (white) **231-670** 0.25 - 0.5 mm² (light gr.) **231-671** 0.75 - 1 mm² (dark grey) **231-672** ❷ 0.2 mm² solid / 0.14 mm² f-st	
Dimensions (in mm)				



L = (No. of poles x pin spacing) + 1.5 mm + 0.9 mm



L = (No. of poles x pin spacing) + 1.5 mm + 0.9 mm

* Approvals with corresponding ratings see www.wago.com
** AWG 12: THHN, THWN

MULTI CONNECTION SYSTEM ***MIDI*** **– Extension of Pole Number**
Connectors with Right Angle Solder Pins
Pin Spacing 5 mm/0.197 in see also Full Line Catalog W4 Volume 2, page 7.15

Pin spacing 5 mm/0.197 in, light grey
250 V/4 kV/3 | 300 V, 10 A ❶
I_N 12 A ❶/ I_N 16 A ❷ | 300 V, 15 A ❷

* CCA GL LR ABS



No. of poles	Item No.	Item No.
Headers with right angle solder pins and fixing flanges, grey,		
solder pin	1 mm x 1 mm ❶	1.2 mm x 1.2 mm ❷
3	**231-433/040-000**	**231-463/040-000**

Female connectors with locking devices cannot be used.

Coding key, snap-on type, light grey **231-129**

Separator, for formation of groups, light grey **231-500**

Additional mechanical safety

The additional mechanical securing on the PCB or the fixing on panels/front plates in case of feedthrough applications are the main features of these headers.

Depending on the wall thickness a recessed, flush or projecting mounting can be realized.

Fixing of the header may be made with standard nuts and bolts (size M 2 or M 2.5).

Note: These connectors can only be mated and unmated at voltages below 42 V and in the "No load" condition.

For mating and unmating at low power values, please request data.



A = (No. of poles x pin spacing) + 3.2 mm

MULTI CONNECTION SYSTEM ***MIDI***
Comb type jumper bars
Pin Spacings 5 mm / 0.197 in and 5.08 / 0.2 in

Pin spacings 5 mm/0.197 in, grey
5.08 mm/0.2 in, grey





Attention! Insert jumper bar according to direction symbols.
☐ Symbol shows direction to operating slot
○ Symbol shows direction to conductor entry

	Item No.	Pack.-unit pcs
Comb type jumper bars, insulated		
for straight and angled male and female connectors		
of Series 231		
with CAGE CLAMP® connection		
Suitable for pin spacings 5 mm/0.197 in and		
5.08 mm/0.2 in		
Attention!		
Not suitable for 2-conductor female connectors with		
CAGE CLAMP®S connection		
3-way	**231-903**	
5-way	**231-905**	
7-way	**231-907**	
10-way	**231-910**	

Insert comb type jumper bars with maximum 5 contacts using operating tool. Comb type jumper bars with more than 7 contacts are pre-assembled by WAGO

Accessories

Operating tool, insulated,

3-way	**280-433**	1
5-way	**280-435**	1

Individual comb type jumper bars are created by breaking out jumper contacts

Note: The maximum wire size is reduced to 1.5 mm²/ AWG 16 solid and stranded ("s" + "f-st")

MULTI CONNECTION SYSTEM ***MIDI*** **– Extension of Pole Number**
Connectors with Screw/Threaded flanges
Pin Spacing 5.08 mm / 0.2 in see also Full Line Catalog W4 Volume 2, pages 7.32 – 7.33







No. of poles	Item No.	No. of poles	Item No.	
Headers with straight solder pins and threaded flanges, orange, solder pin 1 mm x 1 mm		**Headers with right angle solder pins and threaded flanges,** orange, solder pin 1 mm x 1 mm		
7	**231-337/108-000**	7	**231-537/108-000**	
:	:	:	:	
10	**231-340/108-000**	10	**231-540/108-000**	
12	**231-342/108-000**	12	**231-542/108-000**	
14	**231-344/108-000**	14	**231-544/108-000**	
:	:	:	:	
16	**231-346/108-000**	16	**231-546/108-000**	





Pin spacing 5.08 mm/0.2 in, orange

0.2 – 2.5 mm² | **AWG 24 – 12**

250 V/4 kV/3 | **300 V, 20/5 A**

I_N 16 A

9 – 10 mm / 0.37 in



No. of poles	Item No.	No. of poles	Item No.	No. of poles	Item No.
Male connectors with CAGE CLAMP® and threaded flanges, orange		**Female connectors with CAGE CLAMP® and screw flanges,** with coding fingers, with two latches, orange		**2-conductor female connectors with CAGE CLAMP® and screw flanges,** with coding fingers, with two latches, orange	
7	**231-637/109-000**	7	**231-307/107-000**	2 (only 1 latch)	**231-2302/107-000**
:	:	:	:	3 (only 1 latch)	**231-2303/107-000**
10	**231-640/109-000**	10	**231-310/107-000**	4	**231-2304/107-000**
12	**231-642/109-000**	12	**231-312/107-000**	:	:
14	**231-644/109-000**	14	**231-314/107-000**	10	**231-2310/107-000**
:	:	:	:	:	:
16	**231-646/109-000**	16	**231-316/107-000**	16	**231-2316/107-000**







L_1 = (No. of poles –2) x 5.08 mm + 20 mm

MULTI CONNECTION SYSTEM ***MIDI***
Strain relief plates for 2-Conductor Female Connectors
Pin Spacings 5 mm/0.197 in; 5.08 mm/0.2 in; 7.5 mm/0.295 in and 7.62 mm/0.3 in

CAGE CLAMP®S

Ordering examples for
for 2-conductor female connectors
with CAGE CLAMP®S connection
and **strain relief plates**

Description	Width	Additional item No.
Strain relief plate, fied	6 mm	**.../132-000**
	12.5 mm	**.../133-000**
	25 mm	**.../134-000**
	35 mm	**.../135-000**
	55 mm	**.../136-000**
	75 mm	**.../137-000**

2-conductor female connectors with CAGE CLAMP®S connection can be fitted with a strain relief plate retrospectively or directly at the factory. Plates are available in 6 different sizes.

An "additional item no.", referring to the width of the strain relief plate, is added to the "basic item no." and determines the type of connector (see ordering examples).

The arrangement of the fixing holes for cable ties allow single conductors or multicore cables to be attached in several different orientations.

Application notes

Strain relief plate			... female conn. ranges as stated below		Cable ties*		
Item No.	Color	Width	Pin spacings 5 mm/5.08 mm	Pin spacings 7.50 mm/7.62 mm	Width	Type	MIL
734-127 **734-327** **734-227**	light grey grey orange	6 mm	2 poles		2.5 mm	T 18 R	MS 3367
734-128 **734-328** **734-228**	light grey grey orange	12.5 mm	3 – 4 poles	2 – 3 poles	2.5 mm	T 18 R	
734-129 **734-329** **734-229**	light grey grey orange	25 mm	5 – 7 poles	4 – 6 poles	2.5 mm 3.6 mm	T 18 R T 30 R	
734-126 **734-326** **734-226**	light grey grey orange	35 mm	8 – 11 poles	7 – 9 poles	2.5 mm 3.6 mm	T 18 R T 30 R	
734-426 **734-430** **734-428**	light grey grey orange	❶ 55 mm	12 – 16 poles	10 – 12 poles	2.5 mm 3.6 mm 4.0 mm 4.7 mm	T 18 R T 30 R T 40 R T 50 R	
734-427 **734-431** **734-429**	light grey grey orange	❷ 75 mm	17 – 24 poles	13 – 16 poles	2.5 mm 3.6 mm 4.0 mm 4.7 mm	T 18 R T 30 R T 40 R T 50 R	

* Cable binding tool MK III — Item No.

Female connector, pin spacing 5 mm/0.197 in, grey
8 poles, with strain relief plate
231-2108/026-000/135-000



Female connector, pin spacing 5 mm/0.197 in, grey
11 poles, with strain relief plate
231-2111/026-000/135-000

Dimensions (in mm)



* Recommended cable ties and cable binding tool from Tyton or Hellermann, not offered by WAGO

MULTI CONNECTION SYSTEM ***MAXI***
Headers with Solder Pins, 100 % Protected against Mismating, Pin Spacing 7.62 mm / 0.3 in

Pin spacing 7.62 mm/0.3 in, light grey	**Pin spacing 7.62 mm/0.3 in,** light grey	
500 V/6 kV/3 | 300/600 V, 42/5 A **I_N 41 A | 300/600 V, 50/5 A** *	**500 V/6 kV/3 | 300/600 V, 42/5 A** **I_N 41 A | 300/600 V, 50/5 A** *	



No. of poles	Item No.	No. of poles	Item No.
Headers with straight solder pins, 100 % protected against mismating, light grey, 3 x solder pins	1 mm x 1.2 mm	**Headers with right angle solder pins, 100 % protected against mismating,** light grey, 3 x solder pins	1 mm x 1.2 mm
2	**831-3602**	2	**831-3622**
3	**831-3603**	3	**831-3623**
4	**831-3604**	4	**831-3624**
5	**831-3605**	5	**831-3625**
6	**831-3606**	6	**831-3626**
7	**831-3607**	7	**831-3627**
8	**831-3608**	8	**831-3628**

Note:
On request, headers with straight solder pins are also available with protection against positioning error on the PCB

Dimensions (in mm) **Diameter of drilled hole: 1.7 $^{+0.1}$mm L = (No. of poles - 1) x pin spacing + 10.5 mm**

Break or cut-off coding pin on the female connector . . .

. . . Fit the coding pin into the connector (break first) so that the pin engages

Printed female connector on request





* Further approvals with corresponding ratings can be found at www.wago.com

MULTI CONNECTION SYSTEM ***MAXI***
Male Connectors, 100 % Protected against Mismating, Pin Spacing 7.62 mm / 0.3 in

CAGE CLAMP®S

Pin spacing 7.62 mm/0.3 in, light grey		Pin spacing 7.62 mm/0.3 in, light grey	
0.5 – 6 (10) mm² ❶	AWG 20 – 8	0.5 – 6 (10) mm² ❶	AWG 20 – 8
800 V/8 kV/3	300/600 V, 42/5 A	800 V/8 kV/3	300/600 V, 42/5 A
I_N 41 A	300/600 V, 50/5 A	I_N 41 A	300/600 V, 50/5 A
*		*	

❶ can be connected:
0.5 mm² – 10 mm² "s + f-st";
can be pushed in directly: 1.5 mm² – 10 mm² "s" and
1.5 mm² – 6 mm² "insulated ferrule, 12 mm / 0.472 in"



No. of poles	Item No.	No. of poles	Item No.
Male connectors with CAGE CLAMP®S connection, 100 % protected against mismating, with coding fingers, light grey		**Male connectors with CAGE CLAMP®S connection, for DIN 35 rail mounting 100 % protected against mismating,** with coding fingers, light grey	
2	**831-3202**	2	**831-3202/007-000**
3	**831-3203**	3	**831-3203/007-000**
4	**831-3204**	4	**831-3204/007-000**
5	**831-3205**	5	**831-3205/007-000**
6	**831-3206**	6	**831-3206/007-000**
7	**831-3207**	7	**831-3207/007-000**
8	**831-3208**	8	**831-3208/007-000**

Accessories

Test plug, with cable 500 mm / 1'7.7"	Ø 2 mm/0.079 in, red **210-136**	**Test plug,** with cable 500 mm / 1'7.7"	Ø 2 mm/0.079 in, red **210-136**
Marker card, 1 – 16 (100 x)	80 self-adhesive strips per card, Height of marker strip 5 mm / 0.197 in, Marking **210-334/0762-0202**	**Marker card,** 1 – 16 (100 x)	80 self-adhesive strips per card, Height of marker strip 5 mm / 0.197 in, Marking **210-334/0762-0202**
For direct printing, please contact factory		For direct printing, please contact factory	
Marker strip, white, plain, on roll	for center marking, 11 mm / 0.039 in wide, 50 m **2009-110**, 300 m **2009-130**	**Marker strip,** white, plain, on roll	for center marking, 11 mm / 0.039 in wide, 50 m **2009-110**, 300 m **2009-130**
DIN 35 carrier rail adapter, for snap-fit mounting	to male connectors with CAGE CLAMP®S connection **831-137**	**Screwdriver with partially insulated shaft,**	(5.5 x 0.8) mm / (0.217 x 0.031) in **210-621**

Dimensions (in mm) **L = (No. of poles - 1) x pin spacing + 9.5 mm**



The new WAGO MULTI CONNECTION SYSTEM MAXI can be used as "high-power" sub-assemblies on carrier rails or printed circuit boards in such applications like drive technology, converters or power supply units.

Equipped with CAGE CLAMP® S connection up to AWG 10/ AWG 8 (6 mm²/10 mm²) ❶, it handles a rated current of 41 A and has a pin spacing of 7.62 mm / 0.3 in, which makes it ideally suited for such applications.

Product features

- 100 % protected against mismating
- Coding without the loss of poles
- Male and female connectors with CAGE CLAMP®S connection for all conductor types Additional benefit: Time-saving push-in wiring of fine-stranded wires with ferrules
- Vibration proof - fast - maintenance free
- Male and female connectors with separate test slot for test plugs Ø 2.3 mm / 0.091 in
- Pole marking using marker strips or direct printing







* Further approvals with corresponding ratings can be found at www.wago.com

MULTI CONNECTION SYSTEM ***MAXI***
Female Connectors, 100 % Protected against Mismating, Pin Spacing 7.62 mm / 0.3 in

CAGE CLAMP®S

Pin spacing 7.62 mm/0.3 in, light grey **0.5 – 6 (10) mm² ❶** | **AWG 20 – 8** **800 V/8 kV/3** | **300/600 V, 42/5 A** **I_N 41 A** | **300/600 V, 50/5 A** *	**Pin spacing 7.62 mm/0.3 in,** light grey **0.5 – 6 (10) mm² ❶** | **AWG 20 – 8** **800 V/8 kV/3** | **300/600 V, 42/5 A** **I_N 41 A** | **300/600 V, 50/5 A** *	

❶ can be connected:
0.5 mm² – 10 mm² "s + f-st";
can be pushed in directly: 1.5 mm² – 10 mm² "s" and
1.5 mm² – 6 mm² "insulated ferrule, 12 mm / 0.472 in"



No. of poles	Item No.	No. of poles	Item No.	
Female connectors with CAGE CLAMP®S connection, 100 % protected against mismating, with coding fingers, light grey		**Female connectors with CAGE CLAMP®S connection and locking device, 100 % protected against mismating,** with coding fingers, light grey		
2	**831-3102**	2	**831-3102/037-000**	
3	**831-3103**	3	**831-3103/037-000**	
4	**831-3104**	4	**831-3104/037-000**	
5	**831-3105**	5	**831-3105/037-000**	
6	**831-3106**	6	**831-3106/037-000**	
7	**831-3107**	7	**831-3107/037-000**	
8	**831-3108**	8	**831-3108/037-000**	

Accessories

Test plug, with cable 500 mm / 1'7.7"		**Test plug,** with cable 500 mm / 1'7.7"		
	2 mm/0.079 in Ø, red **210-136**		2 mm/0.079 in Ø, red **210-136**	
Marker card,		**Marker card,**		
	80 self-adhesive strips per card Height of marker strip 5 mm/0197 in Marking		80 self-adhesive strips per card Height of marker strip 5 mm/0197 in Marking	
1 – 16 (100 x)	**210-334/0762-0202**	1 – 16 (100 x)	**210-334/0762-0202**	
For direct printing, please contact factory		For direct printing, please contact factory		
Marker strip, white, plain, on roll		**Marker strip,** white, plain, on roll		
	for center marking 11 mm / 0.039 in wide 50 m **2009-110** 300 m **2009-130**		for center marking 11 mm / 0.039 in wide 50 m **2009-110** 300 m **2009-130**	
Screwdriver with partially insulated shaft,		**Screwdriver with partially insulated shaft,**		
	(5.5 x 0.8) mm / (0.217 x 0.031) in **210-621**		(5.5 x 0.8) mm / (0.217 x 0.031) in **210-621**	

Dimensions (in mm) **L = (No. of poles - 1) x pin spacing + 9.5 mm** **L1 = L + 24.8 mm**





Operating Tools

Screwdriver acc. to DIN 5264, for optimum handling in terminal blocks and connectors	TOPJOB® S tool	

Item No.	Pack.-unit pcs	Item No.	Pack.-unit pcs	
Short screwdriver, with partially insulated shaft, blade 3.5 x 0.5 mm / 0.137 in x 0.020 in, suitable for series 260, 261, 262, 264, 280, 281, 869		TOPJOB® S tool with partially insulated shaft, Special blades 3.5 mm / 0.137 in and 5.5 mm / 0.217 in suitable for 2003 and 2005 Series multilevel installation terminal blocks		
210-657	1	**2009-310**	1	
Short angled screwdriver, with partially insulated shaft, blade 3.5 x 0.5 mm / 0.137 in x 0.020 in, particularly suitable for actuator and sensor terminal blocks of Series 280 and also for Series 260, 261, 262, 264, 280, 281, 869, 870, 880				
210-658	1			

Application notes

The blade dimensions of the a. m. screwdrivers (DIN 5264) are particularly appropriate for easy operation of front-entry sensor and actuator terminal blocks of series 280.

Index of Item Nos.

Item No.	Page

Item No.	Page

Item No.	Page

Item No.	Page

Notes

Notes

Notes

Notes

WAGO Worldwide – Companies and Representations –

Argentina
Bruno Schillig S.A.
Arenales 4030, B1604CFD
Florida, PBA
Phone +54 11 4730 1100
Fax +54 11 4761 7244
robertor@schillig.com.ar

Australia
NHP ELECTRICAL ENGINEERING PRODUCTS PTY LTD
43-67 River Street
Richmond, Victoria, 3121
P.O. Box 199
Phone +61 3 9429 2999
Fax +61 3 9429 1075
export@wago.com

Austria
WAGO Kontakttechnik Ges.m.b.H.
Laxenburger Straße 244
1230 Wien
Phone +43 1 6150780
Fax +43 1 6150775
info.at@wago.com

Belgium
WAGO Kontakttechnik
Excelsiorlaan 11
1930 Zaventem
Phone +32 2 7179090
Fax +32 2 7179099
info-be@wago.com

Bosnia and Herzegovina
please contact WAGO Bulgaria

SC_Technik doo
Kadić Mahala 47
Bosnia-Herzegovina
Phone +387 35 821815
Fax +387 35 821816
sc_technik@yahoo.de

Brasil
WAGO Eletroeletrônicos Ltda
Rua Américo Simões 1470
Sãu Roque da Chave
Itupeva SP Brasil 13295-000
Phone +55 11 4591 0199
Fax +55 11 4591 0190
info.br@wago.com

Bulgaria
WAGO Kontakttechnik GmbH & Co. KG
Representative Office Sofia Bulgaria
Twardischiki Prohod 21, ap.5
1404 Sofia
Phone +359 2 489 46 10
Fax +359 2 859 21 31
info-BG@wago.com

RIM Project Ltd.
Probuda - 12 A str., et. 7
Sofia
Bulgaria
Phone +359 2 9310666
Fax +359 2 9313839
office@rim-bg.com

Canada
WAGO CORPORATION
N120 W19129 Freistadt Road
Germantown, WI 53022
Phone +1 262 255 6222
Fax +1 262 255 3232
Toll-Free: 1-800 DIN Rail (346-7245)
info.us@wago.com

Chile
Desimat Chile
Av Puerto Vespucio 9670
Pudahuel Santiago
Phone +56 2 7470152
Fax +56 2 7470153
ventaschile@desimat.cl

China
WAGO ELECTRONIC (TIANJIN) Co. LTD
No.5, Quan Hui Road
Wuqing Development Area
Tianjin 301700
Phone +86 22 59617688
Fax +86 22 59617668
info-cn@wago.com

Columbia
T.H.L. Ltda.
Cra. 49 B # 91-33
Bogotá
Phone +57 1 621 85 50
Fax +57 1 621 60 28
ventas-thl@thl-ltda.com

Croatia
M.B.A. d.o.o. za trgovinu i zastupanje
Frana Supila 5
51211 Matulji HR
Phone +00385 51 275-736
Fax +00385 51 275-066
mba@ri.htnet.hr

Czech Republic
WAGO Elektro spol. sr. o.
Nad lesem 21
14700 Praha 4 - Hodkovicky
61400 Brno - Husovice
Phone +420 261 090 143
Fax +420 261 090 144
info.cz@wago.com

Denmark
WAGO Danmark
Filial of WAGO Kontakttechnik GmbH & Co. KG
Lejrvej 29
3500 Værløse
Phone +45 44 357777
Fax +45 44 357787
salg.dk@wago.com

Ecuador
INSETEC CIA. LTDA.
El Zurriago 177 y El Vengador
P.O. Box 17-16-016
Quito
Phone +593 2 2 26 91 48
Fax +593 2 2 46 18 33
g.castro@insetec.com.ec

Egypt
IBN Engineering Instrumentation & Control
71 a El Shaheed Ahmed Hamdi St.
King Faisal, Giza
Phone +20 2 7214350
Fax +20 2 7221709
sales@ibnengineering.com

Estland
Eltarko OÜ
Laki 14 - 502
10621 Tallinn
Phone +372 651 7731
Fax +372 651 7786
andres@eltarko.ee

Finland
WAGO Kontakttechnik GmbH & Co. KG
Filial i Finland
Vellamonkatu 30 B
00550 Helsinki
Phone +358 9 7744 060
Fax +358 9 7744 0660
export@wago.com

France
WAGO CONTACT S.A.
Paris Nord 2
83 Rue des Chardonnerets
B.P. 55065 - Tremblay en France
95947 - ROISSY CDG CEDEX
Phone +33 1 48172590
Fax +33 1 48632520
info-fr@wago.com

Germany
WAGO Kontakttechnik GmbH & Co. KG
Postfach 28 80 32385 Minden
Hansastrasse 27
32423 Minden
Phone +49 571 887-0
Fax +49 571 887-169
info@wago.com

Great Britian
WAGO Limited
Triton Park, Swift Valley Industrial Estate
RUGBY
Warwickshire, CV21 1SG
Phone +44 1788 568008
Fax +44 1788 568050
uksales@wago.com

Greece
PANAGIOTIS SP. DIMOULAS - BIOMAT
Kritis Str. 26
10439 Athen
Phone +30 210 883 3337
Fax +30 210 883 4436
export@wago.com

Hong Kong
National Concord Eng., Ltd.
Unit A-B, 5/F.
Southeast Industrial Building
611-619 Castle Peak Road
Tsuen Wan, N.T.
Phone +852 24292611
Fax +852 24292164
sales@nce.com.hk

Hungary
WAGO Hungária KFT
Ipari Park, Gyár u. 2
2040 Budapest
Phone +36 23 502-170
Fax +36 23 502-166
info@wago.hu

Iceland
S. Gudjonsson ehf.
Audbrekku 9-11
202 Kopavogur
Phone +354 520-4500
Fax +354 520-4501
export@wago.com

India
WAGO & CONTROLS (INDIA) LTD.
C-27, Sector-58, Phase-III
Noida-201 301
Gautam Budh Nagar (U.P)
Phone +91 120 2 580409 10
Fax +91 120 2 580081
info@wagoindia.com

Indonesia
PT. Timur Agungmulia Kencana
Graha Mulxindo Lt. 2
Jl. Sultan Iskandar Muda No. 88 L
Jakarta Selatan 12240
Phone +62 21 722 8888
Fax +62 21 722 8565
tak_electric@cbn.net.id

Iran
Patsa Industry
No. 2 Bahar St.
South Shiraz Ave
P.O. Box.: 15875-1698
14369 Tehran
Phone +98 21 8726869
Fax +98 21 8719666
export@wago.com

Ireland
Drives & Controls
Unit F4, Riverview Business Park
Nangor Road
Dublin 12
Phone +353 1 4604474
Fax +353 1 4604507
wago@drivesandcontrols.ie

Israel
Comtel Israel Electronic Solutions Ltd.
Bet Hapaamon
20 Hataas Street
P.O.Box 66
44425 Kefar-Saba
Phone +972 9 76 77 240
Fax +972 9 76 77 243
sales@comtel.co.il

Italy
WAGO ELETTRONICA SRL
Via Vittoria, 5/b
40068 San Lazzaro di Savena (BO)
Phone +39 051 6272170
Fax +39 051 6272174
info-ita@wago.com

Japan
WAGO Co. of JAPAN Ltd.
Nittetsu ND-Tower Building 4F
Kameido 1-5-7
Koto-Ku
Tokyo 136-0071
Phone +81 3 5627 2050
Fax +81 3 5627 2055
info-jp@wago.com

Korea
Hankuk Sangsa Co. &
Mahani Electric Co. Ltd.
576-8, Bisan-2dong, Dongan-Ku
Anyang-City
Kyungki-Do., 431-821
Phone +82 31 4633300
Fax +82 31 4633398 9
export@wago.com

Kosovo
please contact WAGO Bulgaria

Kuwait
Kuwait Controls Company
Al Sour Street, Above Lufthansa Airline
Safat Kuwait 13062
Phone +965 822 522
Fax +965 243 3698

Latvia
INSTABALT LATVIA SIA
Vestienas iela 6
Rīga, LV-1035
Phone +371 790 1188
Fax +371 790 1180
info@instabalt.lv

Lebanon
G.T.C.
Antonine Project – Block G
P.O.BOX 70-1096 Antelias
Lebanon
Phone +961 4 521 029
Fax +961 4 521 029
rgemayel@inco.com.lb

Lithuania
INSTABALT LIT UAB
Savanorių 187
Vilnius, 2053
Phone +370 52 322 295
Fax +370 52 322 247
info@instabalt.lt

Luxembourg
please contact WAGO Belgium

Macedonia
please contact WAGO Bulgaria

Malaysia
WAGO Representative Office Malaysia
No 806, Block A4, Leisure Commerce Square,
No 9, Jalan PJS 8/9, 46150 Petaling Jaya,
Selangor Darul Ehsan, Malaysia
Phone +60 3 7877 1776
Fax +60 3 7877 2776
kian.guan.tan@wago.com

Mexico
WAGO CORPORATION
N120 W19129 Freistadt Road
Germantown, WI 53022
Phone +52 55 26 44 69 16
Fax +52 55 26 44 69 15
Toll-Free: 001-800-309-5975
info.mx@wago.com

Netherlands
WAGO Nederland
van Leeuwenhoekstraat 20-1
3846 CB Harderwijk
Phone +31 341 439039
Fax +31 341 439030
info-nl@wago.com

New Zealand
NHP NZ
7 Lockhart Place
Mt Wellington
New Zealand
Phone +64 9 2761967
Fax +64 9 2761992
export@wago.com

Norway
WAGO Norge NUF
Jerikoveien 20
1067 Oslo
Phone +47 22 30 94 50
Fax +47 22 30 94 51
info.no@wago.com

Peru
Desimat Peru
Av. E. Salazar Barreto No. 280
Surco - Lima 33
Phone +51 1 2731892
Fax +51 1 2720054
export@wago.com

Philippines
WAGO Electronic Pte Ltd
10 Upper Aljunied Link, # 04-04
York International, Industrial Building
Singapore 367904
Phone +65 62866776
Fax +65 62842425
info.sing@wago.com

Poland
WAGO ELWAG sp. z o. o.
ul. Piękna 58 a
50-506 Wrocław
Phone +48 71 3604670 78
Fax +48 71 3604699
wago.elwag@wago.com

Portugal
MORGADO & CA. LDA - SEDE
Estrada Exterior da
Circunvalação 3558/3560
Apartado 1057
4435 Rio Tinto
Phone +351 22 9770600
Fax +351 22 9770699
export@wago.com

Romania
please contact WAGO Bulgaria

VDR & Servicii srl
Str. Valeriu Braniște, nr. 60, ap.1, sector 3
Romania
Phone +40 21 3225074/76
Fax +40 21 3225075
office@componente-automatizari.ro

ETA Automatizari Industriale SRL
Str. Gh. Dima Nr. 1
Romania
Phone +40 256 294608
Fax +40 256 294609
automatizari@eta2u.ro

Russia
ООО ВАГО Контакт Рус
ул. Лесная, 43, офис 329
127055 Москва
Phone +7 499 9786670
Fax +7 499 9786690
info@wago.ru

Saudi Arabia
Al Quraishi Electrical Services of S. A.
P.O. Box 7386
Dammam-31462
Phone +966 3 85 725 37
Fax +966 3 85 725 41
export@wago.com

Serbia
please contact WAGO Bulgaria

Singapore
WAGO Electronic Pte Ltd
10 Upper Aljunied Link, # 04-04
York International, Industrial Building
Singapore 367904
Phone +65 62866776
Fax +65 62842425
info.sing@wago.com

Slovakia
WAGO Elektrik spol.s r. o
Odborárska 52
83102 Bratislava
Phone +421 2 44458301
Fax +421 2 44458301
export@wago.com

South Africa
Shorrock Automation (Pty) Ltd
Postnet Suite # 219
Private Bag X 8,Elardus Park
0047 PRETORIA
Phone +27 12 3454449
Fax +27 12 3455145
sales@shorrock.co.za

Spain
DICOMAT S.L.
Avda. de la Industria, 36
Apartado Correos, 1.178
28108-Alcobendas (Madrid)
Phone +34 91 6621362 (6 lineas)
Fax +34 91 6610089
madrid@dicomat-asetyc.com

Sweden
WAGO Sverige
WAGO Kontakttechnik GmbH
Tyskland Filial
Box 639, 17527 Järfälla
Datavägen 9 A, 17543 Järfälla
Phone +46 858410680
Fax +46 858410699
info.se@wago.com

Switzerland
WAGO CONTACT SA
Rte. de l Industrie 19
Case Postale 168
1564 Domdidier
Phone +41/26 676 75 86 (Phone German)
Fax +41/26 676 75 88 (Phone Italian)
info.switzerland@wago.com

Syria
Zahabi Co.
8/5 Shouhadaa St., P.O. Box 8262
Aleppo
Phone +963 21 21 22 235 / 6
Fax +963 21 21 24 768
export@wago.com

Taiwan R.O.C.
WAGO Taiwan
8/F., No. 48, Jing-An Road
Chung-Ho City, 23556
Taipei Hsien. T a i w a n
Phone +886 2 2244 2569
Fax +886 2 2244 2658

Thailand
WAGO Representative Office Thailand
4th Floor, KS Building
213/6-8 Rachada-Phisek Road
Dingdaeng Bangkok 10320
Phone +66 2 6935611
Fax +66 2 6935612
pote.c@wago.com

Turkey
WAGO Elektronik Sanayi ve Ticaret Ltd. Şti.
Barbaros Mahallesi Mimar Sinan Caddesi No 169
34746 Yenisahra - Kadıköy Istanbul
Turkey
Phone +90 216 472 1133
Fax +90 216 472 9910
info.tr@wago.com

United Arab Emirates (UAE)
Binghalib Engineering Ent.
Trading Division
Al Khabeshi Area
P.O. Box 14743
Dubai
Phone +971 4 2674555
Fax +971 4 2674117
export@wago.com

USA
WAGO Corporation
N120 W19129 Freistadt Road
Germantown, WI 53022
Phone +1 262 255 6222
Fax +1 262 255 3232
Toll-Free: 1-800 DIN Rail (346-7245)
info.us@wago.com

Venezuela
PETROBORNAS, C.A.
Av. Principal UD 304-Zona Ind. Los Pinos
C.C. Los Pinos-Local E
8015-Puerto Ordaz-Edo, Bolivar
Phone +58 286 994 3406
Fax +58 286 994 5249
info@petrobornas.net

Vietnam
please contact WAGO Singapore

20.08.07/E

51188216 · 0888-0125/4410-3601 · Suppl. to W4 Volume 1+2 E · 04/07 · JA 70468 · Printed in Germany · Subject to design changes

WAGO®
INNOVATIVE CONNECTIONS